ADA035843

NAVAL POSTGRADUATE SCHOOL
Monterey, California

THESIS

FINITE ELEMENT SOLUTION OF THE NONLINEAR
COUPLED NEUTRONIC-ENERGY EQUATIONS
FOR A FAST REACTOR FUEL CELL

by

Roy Edward Kasdorf

December 1976

Thesis Advisor: D. Nguyen
Thesis Advisor: D. Salinas

Approved for public release; distribution unlimited.

REPRODUCED BY
NATIONAL TECHNICAL
INFORMATION SERVICE
U.S. DEPARTMENT OF COMMERCE
SPRINGFIELD, VA. 22161

156P

REPORT DOCUMENTATION PAGE

READ INSTRUCTIONS BEFORE COMPLETING FORM

1. REPORT NUMBER

2. GOVT ACCESSION NO.

3. RECIPIENT'S CATALOG NUMBER

4. TITLE (and Subtitle)

Finite Element Solution of the Non-linear Coupled Neutronic-Energy Equations for a Fast Reactor Fuel Cell

5. TYPE OF REPORT & PERIOD COVERED

Master's & Mechanical Engineer's Thesis; December 1976

6. PERFORMING ORG. REPORT NUMBER

7. AUTHOR(s)

Roy Edward Kasdorf

8. CONTRACT OR GRANT NUMBER(s)

9. PERFORMING ORGANIZATION NAME AND ADDRESS

Naval Postgraduate School
Monterey, California 93940

10. PROGRAM ELEMENT, PROJECT, TASK AREA & WORK UNIT NUMBERS

11. CONTROLLING OFFICE NAME AND ADDRESS

Naval Postgraduate School
Monterey, California 93940

12. REPORT DATE

December 1976

13. NUMBER OF PAGES

14. MONITORING AGENCY NAME & ADDRESS(if different from Controlling Office)

Naval Postgraduate School
Monterey, California 93940

15. SEC. CLASS. (of this report)

Unclassified

15a. DECLASSIFICATION/DOWNGRADING SCHEDULE

16. DISTRIBUTION STATEMENT (of this Report)

Approved for public release; distribution unlimited.

17. DISTRIBUTION STATEMENT (of the abstract entered in Block 20, if different from Report)

18. SUPPLEMENTARY NOTES

19. KEY WORDS (Continue on reverse side if necessary and identify by block number)

20. ABSTRACT (Continue on reverse side if necessary and identify by block number)

A transient overpower (TOP) accident in a Liquid Metal Fast Breeder Reactor (LMFBR) is considered. The analysis is formulated to model the dynamic response of the reactor fuel subassembly during the initial period of the postulated overpower transient. An equivalent cylindrical cell is used to model the fuel subassembly. The governing neutronic and heat transport equations for each region (fuel, clad, and

DD FORM 1 JAN 73 1473 (Page 1)

EDITION OF 1 NOV 65 IS OBSOLETE
S/N 0102-014-6601

SECURITY CLASSIFICATION OF THIS PAGE (When Data Entered)

coolant) of the equivalent cylindrical cell are developed. Nuclear Doppler broadening feedback is included in the dynamic model making the coupled equations non-linear. The resulting non-linear partial differential field equations are transformed into a system of ordinary differential equations by the finite element method. An isoparametric, quadratic, rectangular element is used for the discretization of the spatial domain. When using the finite element method, large system matrices may result. To facilitate solution of these large systems, an optimum compacting scheme is utilized. The implicit Gear's method is used for the solution of the system of ordinary differential equations. The results for a sample problem are presented.

Finite Element Solution of the Nonlinear
Coupled Neutronic-Energy Equations
for a Fast Reactor Fuel Cell

by

Roy Edward Kasdorf
Lieutenant, United States Navy
B.S.M.E., New Mexico State University, 1970

Submitted in partial fulfillment of the
requirements for the degrees of

MASTER OF SCIENCE IN MECHANICAL ENGINEERING

and

MECHANICAL ENGINEER

from the

NAVAL POSTGRADUATE SCHOOL
December 1976

Author Roy E. Kasdorf

Approved by: Dong H. Nguyen
Thesis Advisor

David Salinas
Thesis Advisor

Richard Franke
Second Reader

Allen E. Fuhs
Chairman, Department of Mechanical Engineering

Robert R. Fossum
Dean of Science and Engineering

ABSTRACT

A transient overpower (TOP) accident in a Liquid Metal Fast Breeder Reactor (LMFBR) is considered. The analysis is formulated to model the dynamic response of the reactor fuel subassembly during the initial period of the postulated overpower transient. An equivalent cylindrical cell is used to model the fuel subassembly. The governing neutronic and heat transport equations for each region (fuel, clad, and coolant) of the equivalent cylindrical cell are developed. Nuclear Doppler broadening feedback is included in the dynamic model making the coupled equations non-linear. The resulting non-linear partial differential field equations are transformed into a system of ordinary differential equations by the finite element method. An isoparametric, quadratic, rectangular element is used for the discretization of the spatial domain. When using the finite element method, large system matrices may result. To facilitate solution of these large systems, an optimum compacting scheme is utilized. The implicit Gear's method is used for the solution of the system of ordinary differential equations. The results for a sample problem are presented.

TABLE OF CONTENTS

I. INTRODUCTION - 13

II. DESCRIPTION OF PROBLEM - - - - - - - - - - - - - - 16

A. PHYSICAL SYSTEM - - - - - - - - - - - - - - - - 16

B. SYSTEM MODEL - - - - - - - - - - - - - - - - - - 18

C. NUMERICAL SOLUTION - - - - - - - - - - - - - - - 20

III. MODEL DEVELOPMENT - - - - - - - - - - - - - - - - - 22

A. NEUTRONIC ANALYSIS - - - - - - - - - - - - - - - 22

1. Fuel Region - - - - - - - - - - - - - - - - - 23

2. Cladding Region - - - - - - - - - - - - - - - 25

3. Coolant Region - - - - - - - - - - - - - - - - 26

4. Infinite Multiplication Factor - - - - - - 26

5. Boundary Conditions - - - - - - - - - - - - 30

B. HEAT TRANSFER ANALYSIS - - - - - - - - - - - - - 32

1. Fuel Region - - - - - - - - - - - - - - - - - 32

2. Cladding Region - - - - - - - - - - - - - - - 33

3. Coolant Region - - - - - - - - - - - - - - - - 33

4. Interface Conditions - - - - - - - - - - - - 34

5. Boundary Conditions - - - - - - - - - - - - 36

IV. FINITE ELEMENT FORMULATION - - - - - - - - - - - - 39

A. BASIC THEORY - - - - - - - - - - - - - - - - - - 39

B. SHAPE FUNCTIONS - - - - - - - - - - - - - - - - 42

C. COORDINATE TRANSFORMATIONS - - - - - - - - - - 43

V. APPLICATION OF FEM TO GOVERNING FIELD EQUATIONS - - - - - - - - - - - - - - - - - - 48

A. GAUSSIAN QUADRATURE - - - - - - - - - - - - - - 48

B. NEUTRONIC FIELD EQUATIONS - - - - - - - - - - 49

1. Fuel Region - - - - - - - - - - - - - - - - 49

2. Clad Region - - - - - - - - - - - - - - - - 53

3. Coolant Region - - - - - - - - - - - - - - 53

C. HEAT TRANSPORT FIELD EQUATIONS - - - - - - - 54

1. Fuel Region - - - - - - - - - - - - - - - - 54

2. Clad Region - - - - - - - - - - - - - - - - 57

3. Coolant Region - - - - - - - - - - - - - - 58

D. DISCRETIZATION OF THE SPATIAL DOMAIN - - - - 60

E. OPTIMUM COMPACTING SCHEME - - - - - - - - - - 63

VI. NUMERICAL SOLUTION - - - - - - - - - - - - - - - - 66

A. SELECTION OF METHOD - - - - - - - - - - - - - 66

B. USER SUPPLIED SUBROUTINES TO IMPLEMENT THE IMPLICIT GEAR'S METHOD - - - - - - - - - 67

1. DIFFUN - - - - - - - - - - - - - - - - - - - 67

2. JACMAT - - - - - - - - - - - - - - - - - - - 68

3. NUITSL - - - - - - - - - - - - - - - - - - - 69

VII. PROCEDURE - 71

A. INPUT DATA - - - - - - - - - - - - - - - - - - 72

VIII. RESULTS - 75

IX. RECOMMENDATIONS - - - - - - - - - - - - - - - - - 87

APPENDIX A: DEVELOPMENT OF TRANSFORMATIONS - - - - - - 89

APPENDIX B: REDUCTION OF SECOND ORDER TERM - - - - - - 92

APPENDIX C: LIST OF RELATIONS FOR MATERIAL THERMAL PROPERTIES - - - - - - - - - - - - - 93

COMPUTER PROGRAM - - - - - - - - - - - - - - - - - - - 95

LIST OF REFERENCES - - - - - - - - - - - - - - - - - - 153

INITIAL DISTRIBUTION LIST - - - - - - - - - - - - - - 155

LIST OF T S

I. Physical Parameters - - - - - - - - - - - - - - - - - 73

LIST OF FIGURES

1. Equivalent Cylindrical Cell - - - - - - - - - - - - - 17
2. Doppler Broadening of a Resonance Peak - - - - - - - 28
3. Gap Heat Transfer Coefficient - - - - - - - - - - - - 35
4. Element Transformation - - - - - - - - - - - - - - - - 44
5. Normalized Shape Functions - - - - - - - - - - - - - - 45
6. Finite Element Discretization - - - - - - - - - - - - 62
7. Sample Data Deck - - - - - - - - - - - - - - - - - - - 74
8. Convergence of the Finite Element Method - - - - - 76
9. Determination of the Critical Fission Cross Section - 77
10. Flux Profile (ρ = \$10) - - - - - - - - - - - - - - - 79
11. Temperature Profile (ρ = \$10) - - - - - - - - - - - 80
12. Radial Flux (ρ = \$10) - - - - - - - - - - - - - - - 82
13. Axial Flux (ρ = \$10) - - - - - - - - - - - - - - - - 83
14. Radial Temperature Profile (ρ = \$10) - - - - - - - - 84
15. Axial Temperature Profile (ρ = \$10) - - - - - - - - 85

LIST OF SYMBOLS AND NOTATION

A. NOTATION

$\langle\ \rangle$	Row vector
$\{\ \}$	Column vector
$[\ ]$	Square matrix or indicates a reference
$[\ ]^{-1}$	Inverse of a square matrix
∇	Del operator
$\frac{\partial}{\partial x}$	Partial derivative with respect to x
Δx	Change in x
$\int_V$	Volume integral
$\int_x$	Integration with respect to x
det [x]	Determinant of x

B. SYMBOLS

b	Nuclear Doppler constant	
C	Concentration of delayed neutron precursors	
C_p	Specific heat	[cal/gm °C]
$D(\underline{r})$	Neutron diffusion coefficient	[cm]
e	Nuclear energy released per fission	[cal/fission]
h	Heat transfer coefficient	[cal/cm^{2}sec °C]
J	Jacobian matrix	
$J(\underline{r},t)$	Neutron current	$[\frac{\text{neutrons}}{\text{cm}^2\ \text{sec}}]$
k_∞	Infinite multiplication factor	
K_D	Doppler constant	
$k(\underline{r})$	Thermal conductivity	[cal/cm sec °C]
LMFBR	Liquid Metal Fast Breeder Reactor	

LOCA	Loss of Coolant Accident	
N	Shape function	
n	Number of delay neutron groups	
$n(\underline{r},t)$	Neutron density	$[\frac{\text{neutrons}}{\text{cm}^3}]$
N,x	Derivative of N with respect to x	
$\dot{q}(\underline{r},t)$	Nuclear generation	$[\text{cal/cm}^3\text{sec}]$
R	Residual	
$\underline{r}$	Spatial coordinate	[cm]
r,z	Global coordinates	
$S(\underline{r},t)$	Neutron production	$[\frac{\text{neutrons}}{\text{cm}^3\ \text{sec}}]$
T	Temperature	[°C]
t	Time	[sec]
TOP	Transient Overpower	
v	Neutron velocity	[cm/sec]
V_{co}	Velocity of coolant flow	[cm/sec]
W	Weighting function	
β	Fraction of fission neutrons which appear as delayed neutrons	
$\phi(\underline{r},t)$	Neutron flux	$[\frac{\text{neutrons}}{\text{cm}^2\ \text{sec}}]$
λ	Decay constant of the delayed neutron precursors	[1/sec]
η,ξ	Local coordinates	
ν	Average number of neutrons released per fission	
ρ	Reactivity	
$\rho(\underline{r})$	Density	$[\text{gm/cm}^2]$
Σ	Neutron cross section	$[\text{cm}^{-1}]$

C. SUBSCRIPTS

a	Absorption
c	Clad
co	Coolant
CR	Critical
D	Delayed, Doppler
f	Fission
F	Fuel
gap	Fuel-clad interface
i,j	Group, equation
P	Prompt
s-f	Clad-coolant interface

D. SUPERSCRIPTS

e	Element
e*	Adjacent element
o	At time zero
'	Derivative with respect to time

ACKNOWLEDGEMENTS

The author wishes to express his appreciation to Dr. Dong Nguyen and to Dr. David Salinas, Professors of Mechanical Engineering, for their advice and guidance throughout the course of this work.

The author is obligated to Dr. Richard Franke, Professor of Mathematics, for his assistance in implementing the integration procedure and for his assistance as second reader.

The author wishes to thank Dr. Gilles Cantin, Professor of Mechanical Engineering, for his invaluable discussions concerning the finite element method.

Finally, the author wishes to thank his wife, Gail, for her encouragement and understanding throughout the course of this study.

I. INTRODUCTION

As the world's fossil fuel resources are depleted, more emphasis is being placed on the breeder reactor as a potential means of solving the coming energy crisis. While the development of new energy sources is being pushed, equal effort is being given to the maintenance of an environmentally clean world. To this end, the safety of breeder reactors is receiving a considerable amount of attention before assuming that the breeder reactor is the answer to the energy problem.

The Liquid Metal Fast Breeder Reactor (LMFBR) appears to be one of the most promising breeder reactors. Most engineers will concede there is little probability of a nuclear explosion occurring in the operation of a nuclear reactor. Of major concern to engineers is the loss of coolant accident (LOCA) and the transient overpower accident (TOP). The present analysis is concerned with a TOP accident in a LMFBR. The analysis is formulated to model the dynamic response of the reactor fuel subassembly during the initial period of the postulated overpower transient. The primary consideration is given to the early response of this fuel subassembly to various conditions of disturbances. The phenomenon which occurs after core disassembly (i.e., clad melting) is not the concern of this analysis. Only the time prior to clad melting is being considered.

No consideration is given here as to how the overpower transient occurs or to why the safety features of the reactor did not operate properly. It is postulated that the accident has occurred. In this analysis, the TOP accident is created by either a step increase in reactivity, a ramp increase in reactivity, or a combination of both.

An inherent safety feature of most reactors, nuclear Doppler broadening feedback, is included in the dynamic model of the fuel subassembly. The Doppler feedback acts to reduce the effect of the excursion. Consideration of this feedback creates a non-linear system model which is described by a non-linear, initial-boundary-value problem.

The conventional method of solution uses the standard point kinetics formulation. Recent studies have pointed out a non-negligible error in this model [1], particularly with asymmetric disturbances [2], or space-dependent feedback [3]. In Ref. [4], a somewhat novel approach of using the finite element method (FEM) for the space-time dependent solution of the reactor dynamics problem was demonstrated. The FEM is effective in handling these asymmetric disturbances and space-dependent feedbacks. Therefore, the finite element method was used so that the spatial effects on the postulated problem may be studied further.

The purpose of this work was to demonstrate further the applicability of the FEM to the non-linear reactor dynamics problem as well as to investigate the dynamic response of the reactor fuel subassembly. The analysis required a novel

approach to handle the gap conductances present at the interfaces of the equivalent cell model of the fuel subassembly; this will be clarified in the analysis.

II. DESCRIPTION OF PROBLEM

A. PHYSICAL SYSTEM

The typical Liquid Metal Fast Breeder Reactor (LMFBR) core consists of many hexagonal modules, each containing several hundred fuel pins. For this analysis, an equivalent cylindrical cell is used to model the fuel subassembly; see Figure 1. The use of equivalent cells as models for larger systems has been common practice in nuclear analysis (i.e., the well known Wigner-Sietz method). In using an equivalent cell, the actual shape of the reactor core is not important, and the analysis is applicable to any reactor which has the same equivalent cell.

The equivalent cell considered in this analysis, Figure 1, is fueled with enriched uranium dioxide, has a stainless steel cladding, and has liquid sodium for a coolant. The dimensions used are

$$a = 0.254 \text{ cm},$$

$$b = 0.292 \text{ cm},$$

$$c = 0.365 \text{ cm},$$

and

$$H = 33.0 \text{ cm}.$$

The gap between the fuel and cladding is very small and, in fact, may be nonexistent as in bonded fuels. The dimension of this gap has been assumed negligible. The height, H, of the fuel rod is shorter than many proposed systems (Fast Flux Testing Facility and Clinch River Breeder Reactor). However,



Figure 1. Equivalent Cylindrical Cell

to facilitate the numerical solution a smaller rod was used. The dynamic behavior prior to fuel pin failure for this system should be similar to the behavior of larger systems.

The treatment of this problem in three dimensions would be prohibitive in computer usage. Therefore, azimuthal symmetry is assumed, and the problem becomes a two-dimensional cylindrical (r,z) problem.

B. SYSTEM MODEL

The analysis considers the monoenergetic neutron diffusion approximation to model the transient neutron transport problem. A simple conduction-convection heat transfer model is used for the energy transport problem. The temperatures in the model are directly coupled to the neutron flux through the nuclear heat generation within the fuel. The neutron population is in turn coupled to the temperature through any of a number of reactivity feedback mechanisms. The nuclear Doppler effect is perhaps the most important of these mechanisms since it provides a negative temperature coefficient which increases the inherent stability of the reactor. Prior to core disassembly and fuel melting, the nuclear Doppler effect is the most dominant feedback and is, therefore, the only feedback mechanism considered in this analysis.

For irradiated, mixed-oxide fuels, a phenomenon of fuel restructuring has been commonly observed. This restructuring, essentially a change of phase of the fuel material, presents a unique heat transfer problem particularly during transient conditions. The problem has not been fully characterized and

is beyond the scope of this analysis. The fuel was, therefore, assumed to be a homogeneous mixture of enriched uranium dioxide.

At the fuel-cladding interface, there exists a gap which produces a thermal resistance. This thermal resistance is one of the most significant deterrents to the energy transfer to the coolant. The interface may be in physical contact or an actual gap may exist. The prediction of the thermal resistance is extremely complicated and must take into consideration many parameters: initial dimensions, type of bond, fill gas composition, fuel restructuring, fuel swelling, prior fuel life cycle, to mention a few. Reference [5] documents a computer program which attempts to predict the gap conductance, H_{gap}. This treats the thermal resistance at the interface in the same manner as a convection heat transfer coefficient when considering convection heat transfer. Since it is not the objective of this analysis to predict the gap coefficient, a representative set of values for gap coefficient, as given in Ref [6], is used in this analysis. These values are assumed to remain static during the transient. The gap conductance profile actually varies with time and will have an effect upon the transient, as noted in Ref. [7]. The prediction of this variance was not considered important for this analysis; therefore, the static assumption was made.

An average convection heat transfer coefficient was used to determine the heat transfer from the cladding to the coolant. The value used was determined from an empirical formula given in Ref. [5] and repeated in Appendix C.

In this work, consideration is given to step and ramp increases in reactivity, although any reactivity transient may easily be considered. The step and ramp increases in reactivity probably represent the most realistic physical reactivity inputs in a reactor. Once the reactivity has been inserted, the transient overpower excursion begins. Unless the Doppler feedback can override the inserted reactivity, the excursion will continue until there is physical core disassembly.

C. NUMERICAL SOLUTION

The system of equations which models the proposed problem is a non-linear, initial-boundary-value problem. The conventional method of solution of the reactor dynamics is the point kinetics formulation. It was pointed out in Refs. [1], [2], [3], and [4], that there is a non-negligible error in this model, particularly under conditions of asymmetric disturbances or space-dependent feedback. Reference [4] demonstrates the somewhat novel approach of using the finite element method (FEM) to solve the space-time dependent reactor dynamics problem. As shown in Ref. [4], the FEM is quite effective in handling localized perturbations and space-dependent feedback. In this work, only uniform disturbances were considered; however, the feedback model was space-dependent. Therefore, the finite element method is used to solve the non-linear, coupled, space-time dependent neutronic and heat transport field equations. The solution technique results in a large computer storage requirement; therefore, an optimum compact storage scheme, Ref. [8], is utilized for storage of the discretized matrices.

Once the domain has been discretized by the FEM, the solution of the resulting ordinary differential equations was to be accomplished by the implicit Gear's method, Ref. [9].

III. MODEL DEVELOPMENT

A. NEUTRONIC ANALYSIS

In this section the governing field equations for the neutron population (flux) for each of the three regions (fuel, clad, and coolant) of the domain will be formulated. The monoenergetic, diffusion theory will be used.

Consider an arbitrary volume of material within a reactor. Applying the condition of conservation to the monoenergetic neutrons leads to the neutron equation of continuity [10]

$$\frac{\partial n(\underline{r},t)}{\partial t} = S(r,t) - \Sigma_a(r)\phi(r,t) - \text{div } J(r,t) \qquad (1)$$

where

$\underline{r}$ - spatial point

t - time

$n(\underline{r},t)$ - neutron density

$S(\underline{r},t)$ - neutron production

$\Sigma_a(\underline{r})$ - neutron absorption cross section

$\phi(\underline{r},t)$ - neutron flux

$J(\underline{r},t)$ - neutron current

The left-hand side of equation (1) represents the time rate of change of the neutron density which is related to flux, ϕ , by

$$n(\underline{r},t) = \frac{1}{v}\,\phi(r,t) \qquad (2)$$

where

v - neutron velocity

On the right-hand side of equation (1), the first term is neutron production, the second term is a neutron loss through absorption, and the third term is a neutron loss through leakage from the control volume.

Using equation (2) and applying Fick's Law to the equation of continuity results in the classical neutron diffusion equation

$$\nabla\cdot(D(\underline{r})\nabla\phi(r,t)) - \Sigma_a(\underline{r})\phi(\underline{r},t) + S(\underline{r},t) = \frac{1}{v}\frac{\partial\phi(\underline{r},t)}{\partial t} \quad (3)$$

where $D(\underline{r})$ - neutron diffusion coefficient

The vector notation used here is intended to include only two dimensions (r,z) since azimuthal symmetry has been assumed.

Equation (3) is applicable to each of the three regions of the equivalent cylindrical cell. The subscripts F (fuel), c (cladding), and co (coolant), will be used to denote these regions.

1. Fuel Region

In applying equation (3) to the fuel region the material properties of the fuel must be used. Within the fuel the neutron souce term is due to the nuclear fission process. During fission, neutrons are released as both prompt neutrons and delayed neutrons so that

$$S(\underline{r},t) = S_p(\underline{r},t) + S_D(\underline{r},t) \quad (4)$$

where $S_p(\underline{r},t)$ - prompt neutron source

$S_D(\underline{r},t)$ - delayed neutron source

The neutron sources are commonly represented as [10]

$$S_p = k_\infty \bar{\Sigma}_{aF} \phi_F (1-\beta) \tag{5}$$

and

$$S_D = \sum_{i=1}^{n} C_i \lambda_i \tag{6}$$

where

k_∞ - infinite multiplication factor

β - fraction of fission neutrons which appear as delayed neutrons

n - number of delayed neutron groups

C_i - concentration of delayed neutron precursors in the $i\underline{th}$ group

λ_i - decay constant of the delayed neutrons

The space and time variables, $\underline{r}$ and t, will be dropped except where needed for clarification.

The concentration of delayed neutron precursors, C_i, is given by the following first order partial differential equation [10]

$$\frac{\partial C_i}{\partial t} = \beta_i k_\infty \Sigma_{aF} \phi_F - \lambda_i C_i \tag{7}$$

where

β_i - fraction of delayed neutrons which appear as delayed neutrons in the $i\underline{th}$ group

The solution of equation (7) is

$$C_i = \beta_i \int_0^t e^{-\lambda_i(t-t')} k_\infty(r,t')\Sigma_{aF}\phi_F dt' + C_i^o e^{-\lambda_i t} \qquad (8)$$

C_i^o - concentration of delayed neutron precursors of the i<u>th</u> group at time zero

Reference [10] develops an expression for the initial concentration of delayed neutrons

$$C_i^o = \beta_i k_\infty^o \Sigma_{aF} \phi^o/\lambda_i \qquad (9)$$

where

k_∞^o - initial finite multiplication factor

ϕ^o - initial neutron flux

Combining equations (3), (4), (5), (6), (8), and (9), yields the governing equation for the fuel region

$$\nabla\cdot(D_F\nabla\phi_F) + \Sigma_{aF}\phi_F[k_\infty(1-\beta) -1]$$

$$+ \sum_{i=1}^{n}\lambda_i[\beta_i \int_0^t e^{-\lambda_i(t-t')} k_\infty(\underline{r},t')\phi_F\Sigma_{aF}dt'$$

$$+ \beta_i k_\infty^o \Sigma_{aF}\phi_F/\lambda_i \; e^{-\lambda_i t}] = \frac{1}{v}\frac{\partial\phi_F}{\partial t} \qquad (10)$$

2. <u>Cladding Region</u>

The cladding separates the fuel and coolant and contains the fuel and the fission by-products. Equation (3) governs the neutron flux in the clad. Since the clad contains

no fissile material, the neutron source term is zero. The field equation is, then,

$$\nabla\cdot(D_c\nabla\phi_c) - \Sigma_{ac}\phi_c = \frac{1}{v}\frac{\partial\phi_c}{\partial t} \qquad (11)$$

3. Coolant Region

The annular region around the cladding of the equivalent cell contains the coolant. As in the clad, there is no fissile material in the coolant and, therefore, no neutron source term. The equation governing the neutron flux in the coolant is

$$\nabla\cdot(D_{co}\nabla\phi_{co}) - \Sigma_{aco}\phi_{co} = \frac{1}{v}\frac{\partial\phi_{co}}{\partial t} \qquad (12)$$

Equations (10), (11), and (12) are the one-velocity, diffusion approximation used to model the neutron transport problem.

4. Infinite Multiplication Factor

The infinite multiplication factor, k_∞, may be expressed as the infinite multiplication factor at time zero (start of transient), k_∞^o, plus the postulated reactivity insertion (such as a step or a ramp), ρ, minus the change in the Doppler reactivity feedback, $\Delta\rho_D$. Other feedback mechanisms are normally not as significant as the Doppler broadening feedback prior to fuel melting and have been neglected in this analysis. Therefore,

$$k_\infty = k_\infty^o + \rho - \Delta\rho_D \qquad (13)$$

For a fast reactor, k_∞° may be approximated as

$$k_\infty^\circ = \nu \frac{\Sigma_{fF}}{\Sigma_{aF}} \tag{14}$$

where

ν - average number of neutrons released per fission

Σ_{fF} - fission cross section of the fuel

Σ_{aF} - absorption cross section of the fuel

The nuclear Doppler effect is a very important safety feature in a nuclear reactor. Nuclei in an atom are in continual motion due to their own thermal energy. As a result of this motion, even when monoenergetic neutrons interact with the atom, there appears to be a spread in the energy of the neutron - the Doppler effect. It can be shown that the cross section of a resonance becomes less in magnitude and wider as the motion of the nuclei increases [10]. As the temperature increases, the motion increases, and the shape of a resonance cross section broadens. This broadening increases the average cross section, thus, providing a negative temperature coefficient. This effect is shown in Figure 2. It is this nuclear Doppler broadening effect which provides one of the few inherent, reliable, negative reactivity feedbacks which slows an overpower transient and possibly stops a mild overpower transient.



Figure 2. Doppler Broadening of a Resonance Peak

The Doppler reactivity change with respect to fuel temperature changes should be written as [6]

$$\frac{d\rho_D}{dT} = aT^{-3/2} + bT^{-1} + cT^{m-1} \tag{15}$$

where a, b, and c are parameters determined from experimental work and m is an integer. However, as noted in Ref. [6], a substantial amount of work has shown that $T\frac{d\rho_D}{dT}$ is very nearly constant over the temperature range under consideration. Therefore, the coefficients a and c have been set equal to zero, and b is defined as

$$b = K_D = T\frac{d\rho_D}{dT} \tag{16}$$

The constant, K_D, is commonly called the Doppler constant. Solving equation (16) for ρ_D yields

$$\rho_D = b \ln T_F + K \tag{17}$$

where K is an integration which may be obtained from initial conditions.

$$K = \rho_D^o - b \ln T_F^o \tag{18}$$

where

ρ_D^o - Doppler effect at time zero

T_F^o - fuel temperature at time zero

Substituting for K in equation (17) will give

$$\rho_D - \rho_D^o = \Delta\rho_D = b \ln(T_F/T_F^o) \tag{19}$$

The infinite multiplication factor now becomes

$$k_\infty = k_\infty^o + \rho - b \ln(T_F/T_F^o) \tag{20}$$

The effect of delayed neutrons is small compared to the prompt neutron effect; therefore, it may be assumed that the Doppler effect on delayed neutrons is insignificant to the overall problem. The k_∞ of equation (8) is, then, assumed to be k_∞^o. With this assumption and equation (20), the neutron diffusion equation in the fuel, equation (10), may be rewritten as

$$\nabla\cdot(D_F\nabla\phi_F) + \Sigma_{aF}\phi_F[k_\infty^o(1-\beta)-1+\rho(1-\beta)-b(1-\beta)\ln(T_F/T_F^o)]$$

$$+\sum_{i=1}^{n}\lambda_i\{\beta_i\Sigma_{aF}\int_0^t e^{-\lambda_i(t-t')}[k_\infty^o+\rho]\phi_F dt'+C_i^o e^{-\lambda_i t}\} = \frac{1}{v}\frac{\partial\phi_F}{\partial t} \tag{21}$$

To facilitate the present analysis, the number of delayed neutron groups is taken as one averaged group. So that, λ_i and β_i become $\bar{\lambda}$ and $\bar{\beta}$, respectively. This approximation should have little effect on the problem under consideration.

5. <u>Boundary Conditions</u>

The neutron diffusion problem involves solution of the partial differential equations (11), (12), and (21), with the following boundary, interface, and initial conditions:

1) $\frac{\partial \phi_F}{\partial r}(0,z,t) = 0$

2) $\phi_F(a,z,t) = \phi_c(a,z,t)$

3) $D_F \frac{\partial \phi_F}{\partial r}(a,z,t) = D_c \frac{\partial \phi_c}{\partial r}(a,z,t)$

4) $\phi_c(b,z,t) = \phi_{co}(b,z,t)$

5) $D_c \frac{\partial \phi_c}{\partial r}(b,z,c) = D_{co} \frac{\partial \phi_{co}}{\partial r}(b,z,t)$

6) $\frac{\partial \phi_{co}}{\partial r}(c,z,t) = 0$

7) $\phi_F(r,\pm \frac{H}{2},t) = \phi_c(r,\pm \frac{H}{2},t) = \phi_{co}(r,\pm \frac{H}{2},t) = 0$

8) $\phi_F(\underline{r},0) = \phi_F^o(\underline{r})$

9) $\phi_c(\underline{r},0) = \phi_c^o(\underline{r})$

10) $\phi_{co}(\underline{r},0) = \phi_{co}^o(\underline{r})$

Boundary condition 1) results from the assumed azimuthal symmetry. Interface conditions 2), 3), 4), and 5) are continuity conditions of the flux. Boundary condition 6) results from the use of an equivalent cell and basically indicates there is an equal number of neutrons transferred in and out of the cell at the outer boundary. This should be valid unless the cell is located near the outer edge of the reactor. Boundary condition 7) is an assumption that the flux is zero at the axial boundaries of the cell. Initial conditions 8), 9), and 10) are the assumed initial distributions of the neutron flux.

B. HEAT TRANSFER ANALYSIS

In this section, the principle of conservation of energy will be used to formulate the governing field equations for the heat transport in each of the three regions. A simple heat conduction model with convection heat transfer to the coolant is used to model the heat transport problem. A gap conductance model is used to describe the heat transport across the gap at the fuel-clad interface.

1. Fuel Region

Conservation of energy within the fuel region yields the unsteady heat conduction equation with a generation term

$$\nabla\cdot(k_F(\underline{r})\nabla T_F(\underline{r},t))+\dot{q}(\underline{r},t)=\rho_F(\underline{r})C_{pF}(\underline{r})\frac{\partial T_F}{\partial t}(\underline{r},t) \qquad (22)$$

where

$k_F(\underline{r})$ - thermal conductivity of the fuel

$T_F(\underline{r},t)$ - fuel temperature

$\dot{q}(\underline{r},t)$ - nuclear energy generation per unit volume

$\rho_F(\underline{r})$ - fuel density

$C_{pF}(\underline{r})$ - fuel specific heat

As in the neutronic analysis, the vector notation is intended to include only two dimensions, (r,z). The $\underline{r}$ and t will be dropped except where needed for clarification.

The nuclear generation term may be expressed as

$$\dot{q} = e\,\Sigma_{fF}\,\phi_F \qquad (23)$$

where e - nuclear energy released per fission

As can be seen, it is through the nuclear generation term that the temperature is directly coupled to the neutron flux. This coupling and the temperature dependent Doppler reactivity feedback combine to make the coupled problem non-linear.

Substituting equation (23) into equation (22) yields the governing thermal equation for the fuel

$$\nabla\cdot(k_F \nabla T_F) + e\, \Sigma_{fF}\, \phi_F = \rho_F\, C_{pF} \frac{\partial T_F}{\partial t} \tag{24}$$

2. <u>Cladding Region</u>

Conservation of energy within the clad will yield the heat conduction equation. With nuclear generation, a relatively small amount (~5%) of the energy will be released in the cladding and the coolant. However, in this analysis it is assumed that the total energy release is in the fuel region. This should not create any significant error. Using this assumption, the unsteady heat conduction equation for the cladding becomes

$$\nabla\cdot(k_c \nabla T_c) = \rho_c\, C_{pc} \frac{\partial T_c}{\partial t} \tag{25}$$

3. <u>Coolant Region</u>

Once again, conservation of energy will lead to the heat conduction equation plus an additional term which

takes into consideration the coolant flow. The governing equation is

$$\nabla\cdot(k_{co}\nabla T_{co}) - V_{co}\frac{\partial}{\partial z}(\rho_{co}C_{pco}T_{co}) = \rho_{co}\,C_{pco}\frac{\partial T_{co}}{\partial t} \tag{26}$$

where V_{co} - coolant flow velocity

Equations (24), (25), and (26) are the governing equations used to model the energy transport problem.

4. Interface Conditions

The interface between the fuel and the cladding may be an actual gap with a finite distance, or the surfaces may be in intermittent contact on a microscopic scale. To model the heat transfer across this interface, a gap heat transfer coefficient is introduced. The gap coefficient must take into consideration many items (e.g., radiation heat transfer across the gap, heat transfer by solid-to-solid contact, heat conduction across a gas filled gap). The prediction of this gap coefficient is extremely complicated and beyond the scope of this work. In Ref. [6], a set of values for H_{gap} is given and the axial variation of H_{gap} in this analysis is approximately the same. A cosine curve has been fitted to the sample data to determine the gap coefficient, see Figure 3. The heat flux across the fuel-clad interface is, then,

$$q = H_{gap}\,(T_F - T_c) \tag{27}$$



Figure 3. Gap Heat Transfer Coefficient

The heat conducted out of the fuel is governed by Fourier's equation and is equal to the heat transferred across the gap

$$q = -k_F \frac{\partial T_F}{\partial r} \tag{28}$$

Equating equations (27) and (28) gives the fuel-clad interface condition

$$T_F(a,z,t) + \frac{k_F(a,z)}{H_{gap}(z)} \frac{\partial T_F}{\partial r}(a,z,t) = T_c(a,z,t) \tag{29}$$

and from continuity

$$k_F(a,z) \frac{\partial T_F}{\partial r}(a,z,t) = k_c(a,z) \frac{\partial T_c}{\partial r}(a,z,t) \tag{29a}$$

As is common practice in convection heat transfer analysis, a coolant surface heat transfer coefficient, hsurf, is used to account for the thermal resistance at the clad-coolant interface. Similar to the fuel-clad interface analysis, the clad-coolant interface conditions may be determined

$$T_c(b,z,t) + \frac{k_c(b,z)}{h_{surf}} \frac{\partial T_c}{\partial r}(b,z,t) = T_{co}(b,z,t) \tag{30}$$

and

$$k_c(b,z) \frac{\partial T_c}{\partial r}(b,z,t) = k_{co}(b,z) \frac{\partial T_{co}}{\partial r}(b,z,t) \tag{30a}$$

5. <u>Boundary Conditions</u>

The boundary and initial conditions for the heat transport problem are:

1) $\frac{\partial T_F}{\partial r}(0,z,t) = 0$

2) $T_{co}(r,-\frac{H}{2},t) = T_{PLENUM}$

3) $\frac{\partial T_{co}}{\partial z}(r,\frac{H}{2},t) = 0$

4) $\frac{\partial T_{co}}{\partial r}(c,z,t) = 0$

5) $\frac{\partial \bar{T}_F}{\partial z}(r,\pm\frac{H}{2},t) = \frac{\partial T_c}{\partial z}(r,\pm\frac{H}{2},t) = 0$

6) $T_F(\underline{r},0) = T_F^o(\underline{r})$

7) $T_c(\underline{r},0) = T_c^o(\underline{r})$

8) $T_{co}(\underline{r},0) = T_{co}^o(\underline{r})$

Boundary condition 1) results from the assumed azimuthal symmetry. The coolant has been assumed to enter the flow channel at a constant temperature, T_{PLENUM}. This results in condition 2). Boundary conditions 3) and 5) result from an assumption that no heat is transferred axially from the fuel rod. Boundary condition 4) is the result of the use of the equivalent cell. Conditions 6), 7), and 8) are the assumed initial conditions.

Solution of the nonlinear coupled neutronic and energy transport problem involves the solution of the partial differential equations (11), (12), (21), (24), (25), and (26), with the appropriate boundary, interface, and initial conditions.

Several works, Refs. [4], [11], [12], have demonstrated the feasibility and success of the finite element method in solving nuclear reactor dynamics problems. The FEM

is used to reduce the partial differential equations developed in this analysis to a system of ordinary differential equations. Integration of these ordinary differential equations (ODE) yields the solution.

IV. FINITE ELEMENT FORMULATION

In this section, the basic theory underlying the finite element method is formulated. Selection of the finite elements and the shape functions for the elements are given. Some simple transformations which facilitate the integration necessary in the FEM are also presented.

A. BASIC THEORY

To obtain a numerical solution, the governing partial differential field equations are transformed into a system of ODE in finite dimensional vector space. This may be accomplished in several manners such as the finite-difference method, the variational method, or the weighted residual method. In this work, the Galerkin method (a weighted residual method) is utilized for the discretization of the spatial domain. The Galerkin procedure will be applied to each of the governing field equations. Any of these equations may be considered to be in the following form

$$\frac{\partial \psi}{\partial t}(\underline{r},t) - \ell\psi(\underline{r},t) = f(\underline{r},t) \qquad (31)$$

where ψ represents the unknown function, e.g., in equation (21), ψ represents ϕ_F, ℓ represents the operator for each individual equation, and f is a forcing function. In the finite element method the solution is approximated as

$$\psi(\underline{r},t) \cong \tilde{\psi}(\underline{r},t) = \sum_{i=1}^{N} N_i(\underline{r})\,\psi_i(t) = \langle N_i \rangle \{\psi_i\} \qquad (32)$$

where N - the number of degrees of freedom

N_i - the element shape function

ψ_i - unknown coordinate function

$< >$ - matrix notation for a row vector

$\{ \}$ - matrix notation for a column vector

$$\langle N_i \rangle - \langle N_1 \; N_2 \; \ldots \; N_i \; \ldots \; N_N \rangle$$

$$\{N_i\} - \begin{Bmatrix} N_1 \\ N_2 \\ \vdots \\ N_i \\ \vdots \\ N_N \end{Bmatrix}$$

The residual, $R(\underline{r},t)$, is a measure of the error in this finite element approximation. The residual may be considered as

$$R = \frac{\partial \psi}{\partial t} - \ell \psi - f \tag{33}$$

The best solution for $\tilde{\psi}$ is one which "minimizes" this residual. Various "minimums" are obtained by the weighted residual method by setting

$$\int_V W_i(\underline{r}) \, R \, dV = 0 \qquad i=1,2,\ldots N \tag{34}$$

$W_i(\underline{r})$ - weighting functions

With the Galerkin method, the weighting functions are the shape functions defining the approximation of equation (32) (i.e., $W_i = N_i$). A noteworthy attribute of the Galerkin method is the opportunity of using an integration-by-parts

of the terms involving the second order spatial derivatives. A lower order finite element may be used than would have been possible otherwise. Once the weighting functions have been chosen, the problem becomes

$$\int_V N_i \left\{\frac{\partial\psi}{\partial t} - \ell\psi - f\right\} dV = 0 \qquad i=1,2,\ldots N \qquad (35)$$

The integration involved in equation (35) is carried out on the element level, taking advantage of the use of a "local" coordinate system. Once the integration is accomplished, the results are merged into a system using "global" coordinates. On the element level

$$\tilde{\psi}^e = \langle N_j\rangle^e \{\psi_j\}^e \qquad j=1,2,\ldots,N \qquad (36)$$

where the superscript e indicates the element level. Substituting $\tilde{\psi}^e$ into equation (35) and noting $\{\psi_j\}^e$ is not a function of the spatial domain yields

$$\int_V \langle N_i\rangle^e \{N_j\}^e dV^e \{\dot{\psi}_j\}^e - \int_V [\langle N_i\rangle^e \ \ell \{N_j\}^e - \langle N_i\rangle^e f^e] dV^e \{\psi_j\}^e = 0 \qquad (37)$$

where $i,j = 1,2,\ldots N^e$

N^e - number of degrees of freedom for an element

The operator ℓ will vary depending upon which governing equation is under consideration.

B. SHAPE FUNCTIONS

The shape functions, N_i, are chosen to satisfy certain completeness and convergence criteria [13] and will depend upon the finite-element used for the spatial discretization.

Many previous works, Refs. [4], [11], and [12], utilized linear triangular shaped elements to discretize the spatial domain. This element was the first element considered. However, because the width of the cladding is very thin, elements in the cladding region would have extremely large aspect ratios (ratio of base to height) unless an extremely large number of elements in the axial direction were used. A large number of elements becomes numerically untractable. Previous experience with triangular elements had shown that large aspect ratios yield inaccurate results. Zlamal, Ref. [14], showed the error, e, when using triangular elements, is proportional to the square of the longest side, h, and inversely proportional to the sine of the smallest angle, γ

$$e \propto h^2/\sin\gamma$$

A triangular element with a large aspect ratio necessarily must have a small related angle which adversely affects the error in the FEM. Hopefully to alleviate the problem, an isoparametric, quadratic, rectangular element was selected. The aspect ratio would still be large, but experience, Ref. [15], with the use of rectangular elements indicated that a large aspect ratio is not always a detrimental factor.

The shape functions for this element are well documented, Ref. [13]. Utilizing a "local" coordinate system (See Figure 4), the shape functions may be written as

Corner nodes $\quad i = 1,3,5,7$

$$N_i = \frac{1}{4}(1+\xi_0)(1+\eta_0)(\xi_0+\eta_0-1) \tag{38}$$

Midside nodes

$$N_i = \frac{1}{2}(1-\xi^2)(1+\eta_0) \quad i=2,6 \tag{38a}$$

$$N_i = \frac{1}{2}(1+\xi_0)(1-\eta^2) \quad i=4,8 \tag{38b}$$

where

$$\xi_0 = \xi\xi_i$$

$$\eta_0 = \eta\eta_i$$

These normalized shape functions are shown in Figure 5.

The local and global coordinates are related by the following

$$r = \langle N_i \rangle^e \{r_i\}^e \tag{39}$$

and

$$z = \langle N_i \rangle^e \{z_i\}^e \tag{39a}$$

C. COORDINATE TRANSFORMATIONS

When using a local coordinate system, some simple transformations facilitate the integrations required by equation (37). In cylindrical coordinates with azimuthal symmetry

$$dV = 2\pi r dr dz \tag{40}$$

The derivative terms may be transformed by the following

$$\begin{Bmatrix} \dfrac{\partial N_i}{\partial r} \\ \dfrac{\partial N_i}{\partial z} \end{Bmatrix} = [J]^{-1} \begin{Bmatrix} \dfrac{\partial N_i}{\partial \xi} \\ \dfrac{\partial N_i}{\partial \eta} \end{Bmatrix} \tag{41}$$



Figure 4. Element Transformation



CORNER NODE



MIDSIDE NODE

Figure 5. Normalized Shape Functions

where $[J]^{-1}$ is the inverse of the 2x2 Jacobian matrix defined in Appendix A. As shown in Appendix A, this inverse can be easily shown to be (for this problem)

$$[J]^{-1} = \begin{bmatrix} J_{11}^{*} & J_{12}^{*} \\ J_{21}^{*} & J_{22}^{*} \end{bmatrix} \tag{42}$$

where

$J_{11}^{*} = 2/\Delta r$, $J_{12}^{*} = 0$

$J_{21}^{*} = 0$, $J_{22}^{*} = 2/\Delta Z$

Δr - radial length of the element

ΔZ - axial length of the element

Elements of area transform as

$$drdz = \det[J]\, d\xi d\eta \tag{43}$$

For this particular problem, $\det[J]$ may be shown to be (Appendix A)

$$\det[J] = \frac{A^e}{4} \tag{44}$$

where A^e - area of the element

Elements of axial length become

$$dz = \frac{L^e}{2} \tag{45}$$

where L^e - axial length of the element

Utilization of these transformations makes the integrations required in equation (37) amenable to integration by numerical Gaussian quadrature.

V. APPLICATION OF FEM TO GOVERNING FIELD EQUATIONS

In this chapter, equation (37) is applied to the governing field equations previously derived. The element matrices for each of the operators are developed so that the discretization of the spatial domain may be accomplished. The integrations required by the application of equation (37) are performed numerically using Gaussian quadrature.

A. GAUSSIAN QUADRATURE

Prior to the application of equation (37), it is appropriate to discuss briefly the procedure used for the numerical integration. The product Gaussian quadrature formula is [16]

$$I_A = \int_{-1}^{1}\int_{-1}^{1} g(\xi,\eta)d\eta d\xi = \sum_{i=1}^{m}\sum_{j=1}^{m} W_i W_j \, g(\xi_i,\eta_j) \qquad .(46)$$

where
- I_A - area integration
- $g(\xi,\eta)$ - any function of ξ and η
- $W_{i,j}$ - weight associated with location i or j
- m - number of Gauss sampling points in one-dimension

The values of the weights associated with each Gauss point are given in Ref. [16]. Equation (42) may be simplified somewhat by combining the summations and weights

$$I_A = \sum_{k=1}^{m^2} W_k \, g(\xi_k,\eta_k) \qquad (47)$$

where $k = i \times j$

$W_k = W_i \times W_j$

For line integrations, the Gaussian quadrature formula involves only one summation

$$I_L = \int_{-1}^{1} f(\eta)d\eta = \sum_{i=1}^{m} W_i \; f(\eta_i) \tag{48}$$

B. NEUTRONIC FIELD EQUATIONS

The discretization of the spatial domain by the finite element method is accomplished by applying equation (37) to the governing field equations, using

$$\phi_k = \langle N_j \rangle^e \; \{\psi_{kj}\}^e \qquad j=1,2,\ldots,8 \qquad k=F,c,co \tag{49}$$

1. Fuel Region

The governing equation for the fuel region, equation (20) after applying equation (37) becomes

$$2\pi \int_r \int_z \frac{N_i}{v} \frac{\partial \phi_F}{\partial t} \, r dr dz - 2\pi \int_r \int_z N_i \{ \frac{1}{r} \frac{\partial}{\partial r}(r D_F \frac{\partial \phi_F}{\partial r})$$

$$+ \frac{\partial}{\partial z}(D_F \frac{\partial \phi_F}{\partial z}) + \Sigma_{aF} \phi_F (1-\beta)[k_\infty^\circ + \rho - b \ln(T_F/T_F^\circ)]$$

$$+ \bar{\lambda} \bar{\beta} \Sigma_{aF} \int_0^t e^{-\lambda_i (t-t')} (k_\infty^\circ + \rho) \phi_F dt' + \bar{\lambda} C^\circ e^{-\lambda t} \} r dr dz = 0 \tag{50}$$

The second order terms in equation (50) may be reduced to a first order term by application of Green's Theorem or equivalently integration-by-parts (See Appendix B). Dividing through by 2π and reducing the second order terms yields

$$\int_z rN_i D_F \frac{\partial\phi_F}{\partial r}\,dz + \int_r rN_i D_F \frac{\partial\phi_F}{\partial z}\,dr + \int_r\int_z \frac{N_i}{v}\frac{\partial\phi_F}{\partial t}\,rdrdz$$

$$+\int_r\int_z \Big\{D_F\Big[\frac{\partial N_i}{\partial r}\frac{\partial\phi_F}{\partial r} + \frac{\partial N_i}{\partial z}\frac{\partial\phi_F}{\partial z}\Big] - N_i\Sigma_{aF}\phi_F(1-\beta)[k_\infty^\circ+\rho-b\ln(T_F/F_{Fo})]$$

$$-N_i\bar{\lambda}\bar{\beta}\Sigma_{aF}\int_0^t e^{-\lambda(t-t')}(k_\infty^\circ+\rho)\phi_F dt' - N_i\bar{\lambda}C^\circ e^{-\bar{\lambda}t}\Big\}\,rdrdz = 0 \quad (51)$$

From continuity and boundary conditions the line integrals are zero. Now using the approximate functions of equation (49) and noting that $\{\psi_F\}^e$ is not a function of space, equation (51) may be written as

$$\frac{1}{v}\iint_{rz}\{N_i\}^e\langle N_j\rangle^e\,rdrdz\{\dot{\psi}_F\}^e + \iint_{rz}D_F[\{N_{i,r}\}^e\langle N_{j,r}\rangle^e + \{N_{i,z}\}^e\langle N_{j,z}\rangle^e]rdrdz\{\psi_F\}^e$$

$$-\iint_{rz}\Sigma_{aF}(1-\beta)[k_\infty^\circ+\rho-b\ln(T_F/T_F^\circ)]\{N_i\}^e\langle N_j\rangle^e rdrdz\{\psi_F\}^e - \bar{\lambda}\bar{\beta}\Sigma_{aF}\int_0^t e^{-\bar{\lambda}(t-t')}(k_\infty^\circ+\rho)dt'$$

$$\iint_{rz}\{N_i\}\langle N_j\rangle rdrdz\{\psi_F\}^e - \bar{\lambda}C^\circ e^{-\bar{\lambda}t}\iint_{rz}\{N_i\}rdrdz = 0 \quad (52)$$

The integrations may not be easily carried out with a shift to local coordinates and with use of the previously derived transformations. Rearranging equation (52) and assuming the properties are constant for each time step gives

$$D_F \int_{-1}^{1}\int_{-1}^{1} [\{N_{i,\xi}J_{11}^*\}\langle J_{11}^* N_{j,\xi}\rangle + \{N_{i,\eta}J_{22}^*\}\langle J_{22}^* N_{j,\eta}\rangle] r\det[J] d\xi d\eta \{\psi_F\}^e$$

$$-\Sigma_{aF}(1-\beta)(k_\infty^\circ+\rho) \int_{-1}^{1}\int_{-1}^{1} \{N_i\}\langle N_j\rangle \, r\det[J] d\xi d\eta \{\dot{\psi}_F\}^e$$

$$-\Sigma_{aF}(1-\beta)b \int_{-1}^{1}\int_{-1}^{1} \ln \frac{\hat{T}_F}{T_F^\circ} \{N_i\}\langle N_j\rangle r\det[J] d\xi d\eta \, \{\psi_F\}^e$$

$$-\bar{\lambda}\bar{\beta}\Sigma_{aF} f(t) \int_{-1}^{1}\int_{-1}^{1} \{N_i\}\langle N_j\rangle r\det[J] d\xi d\eta \{\psi_F\}^e - \bar{\lambda}C^\circ e^{-\bar{\lambda}t} \int_{-1}^{1}\int_{-1}^{1} \{N_i\} r\det[J] d\xi d\eta$$

$$+\frac{1}{v}\int_{-1}^{1}\int_{-1}^{1} \{N_i\}\langle N_j\rangle r\det[J] d\xi d\eta \, \{\dot{\psi}_F\}^e = 0 \qquad (53)$$

Since the element chosen has eight degrees of freedom (nodal points), the discretized matrices which result from the integration of equation (53) will be 8x8 matrices and the forcing function will be an 8x1 vector at the element level. Defining the matrices as

$$\int_{-1}^{1}\int_{-1}^{1} [\{N_{i,\xi}J_{11}^*\}\langle J_{11}^* N_{j,\xi}\rangle + \{N_{i,\eta}J_{22}^*\}\langle J_{22}^* N_{j,\eta}\rangle] r\det[J] \, d\xi d\eta$$

$$= [H12_{ij}]_{8x8} = \frac{A^e}{4}\sum_{k=1}^{m^2} [(N_{i,\xi})_k (N_{j,\xi})_k J_{11}^{*2}$$

$$+ (N_{i,\eta})_k (N_{j,\eta})_k \, J_{22}^*] \, r_k W_k \qquad (54)$$

where $\qquad W_k = W_i W_j \quad \text{and} \quad r_k = \sum_{i=1}^{8} r_i (N_i)_k$.

$$\int_{-1}^{1}\int_{-1}^{1} \{N_i\}\langle N_j\rangle r\det[J]d\xi d\eta = [H3_{ij}]_{8x8} = \frac{A^e}{4}\sum_{k=1}^{m^2} (N_i)_k (N_j)_k r_k W_k \qquad (55)$$

$$\int_{-1}^{1}\int_{-1}^{1} \{N_i\} r\det[J]d\xi d\eta = \{F_i\}_{8x1} = \frac{A^e}{4}\sum_{k=1}^{m^2} (N_i)_k r_k W_k \qquad (56)$$

$$\int_{-1}^{1}\int_{-1}^{1} \ln(T_F/T_D)\{N_i\}\langle N_j\rangle r\det[J]d\xi d\eta = [H4_{ij}]_{8x8}$$

$$= \frac{A^e}{4}\sum_{k=1}^{m^2} \ln(T_F/T_{F\circ})_k (N_i)_k (N_j)_k r_k W_k \ . \qquad (57)$$

To carry out the summation of equation (57), the temperature T_F must be known; however, the temperature is exactly what is being sought. To alleviate this problem, a linearization is used.

In the solution technique, the temperature is predicted for the next time step. It is this temperature which is used for the determination of matrix H4.

Equation (53) simplifies to

$$\{D_F[H12_{ij}]-[\Sigma_{aF}(1-\beta)(k_\infty^\circ+\rho)+\bar{\lambda}\bar{\beta}\Sigma_{aF}f(t)][H3_{ij}]+\Sigma_{aF}(1-\beta)b[H4_{ij}]\}\{\dot{\psi}_F\}^e$$

$$-\bar{\lambda}C^\circ c^{-\bar{\lambda}t}\{F_i\}^e + \frac{1}{v}[H3_{ij}]\{\dot{\psi}_F\} = 0 \qquad (58)$$

The function $f(t)$ is evaluated by summing the values at each time step using the trapezoid rule for numerical integration.

$$f(t) = e^{-\bar{\lambda}t} \int_0^t e^{-\bar{\lambda}t'} [k_\infty^o + \rho] dt' \tag{59}$$

Defining

$$I_i[g(t)] = \frac{1}{2} h_i \{g(t_i) + g(t_{i-1})\} \tag{60}$$

$$g(t) = e^{\bar{\lambda}t}(k_\infty^o + \rho)$$

h_i - time step taken

$g_o = 0$

The function may be expressed as

$$f(t) = e^{-\lambda t} \sum_{i=1}^{S} I_i \; [g(t)] \tag{61}$$

S - number of time steps

2. <u>Clad Region</u>

Following the same procedure as with the fuel equation, the discretized form of equation (11) becomes

$$\{D_c[H12_{ij}] + \Sigma_{ac}[H3_{ij}]\}\{\psi_c\}^e + \frac{1}{V}[H3_{ij}]\{\dot{\psi}_c\}^e = 0 \tag{62}$$

3. <u>Coolant Region</u>

The governing equation for the coolant region, equation (12), may be discretized into the form

$$\{D_{co}[H12_{ij}] + \Sigma_{aco}[H3_{ij}]\}\{\psi_{co}\}^e + \frac{1}{V}[H3_{ij}]\{\dot{\psi}_{co}\}^e = 0 \tag{63}$$

Once the governing equations have been discretized at the element level, they are combined into a system of equations at the global level. On the global level the governing equation for neutron transport takes the form of

$$[H]_{nxn}\{\psi\}_{nx1} + [P]_{nxn}\{\dot{\psi}\}_{nx1} + \{F\}_{nx1} = 0 \qquad (64)$$

where [H], [P], and [F] represent the system matrices and n is the number of nodal points used in the discretization. There are, then, n simultaneous ordinary differential equations used to describe the neutron transport problem.

C. HEAT TRANSPORT FIELD EQUATIONS

The spatial domain for the heat transport problem is discretized in the same manner as the domain for the neutronics problem. The same element matrices previously defined are valid. Let

$$T_k = \langle N_j \rangle^e \{\tau_{kj}\}^e \qquad j=1,2,\ldots,8 \qquad k=F,c,co \qquad (65)$$

1. Fuel Region

The governing field equation for the fuel, equation (24), is discretized by applying equation (37). Using an integration by part to lower the order of the second order terms allows equation (24) to be written as

$$\int_r [N_1 k_F \frac{\partial T_F}{\partial z}\Big|_0^z \, rdrdz + \int_z [N_1 k_F \frac{\partial T_F}{\partial r}\Big|_0^a \, dz - \int_r \int_z \{k_F[\frac{\partial N_1}{\partial r}\frac{\partial T_F}{\partial r} + \frac{\partial N_1}{\partial z}\frac{\partial T_F}{\partial z}]$$

$$-e\Sigma_{fF}N_1\phi_F + N_1\rho_F C_{pF}\frac{\partial T_F}{\partial t}\} \, rdrdz = 0 \qquad (66)$$

From continuity considerations the line integrals are zero except along the boundaries of a region. It is assumed that no heat is transferred from the cell in the axial direction (boundary condition 5); therefore, the first line integral of equation (66) is zero. In the neutron diffusion problem there was continuity of flux at the interfaces so that the line integrals were zero; however, the heat transfer at the interfaces is affected by the gap and film conductances. The fuel-clad interface condition, equation (29), may be rewritten as

$$-k_F \frac{\partial T_F}{\partial r} = H_{gap}(T_F - T_c) = -k_c \frac{\partial T_c}{\partial r} \tag{67}$$

Substituting equation (67) into (66), dividing by minus one and utilizing equation (65) yields

$$\int_z [rH_{gap}\{N_i\}^e \langle N_j\rangle^e |_0^a dz \{\tau_F\}^e - \int_z [rH_{gap}\{N_i\}^e \langle N_j\rangle^e |_0^a dz \{\tau_c\}^{e*}$$

$$+ \int_r \int_z k_F[\{N_{i,r}\}^e \langle N_{j,r}\rangle^e + \{N_{i,z}\}^e \langle N_{j,z}\rangle^e] r dr dz \{\tau_F\}^e$$

$$- \int_r \int_z e\Sigma_{fF}\{N_i\}^e \langle N_j\rangle^e r dr dz \{\psi_F\}^e$$

$$+ \int_r \int_z \rho_F C_{pF} \{N_i\}^e \langle N_j\rangle^e r dr dz \{\dot{\tau}_F\}^e = 0 \tag{68}$$

e^* - element across the interface

Transforming to local coordinates and integrating by Gaussian quadrature yields the same element matrices as given for the neutron flux, equations (54) and (55), except for the line integrals between regions. It should be noted that the line integrals exist only on the interfaces, along which there is a discontinuity of temperature. For the fuel equation the interface corresponds to the local coordinate $\xi=1$. Define

$$\int_{-1}^{1} \{N_i\}\langle N_j\rangle d\eta = [k1_{ij}]_{8x8} = \frac{L^e}{2} \sum_{k=1}^{m^2} (N_i)_k (N_j)_k W_k \tag{69}$$

where the N's are evaluated at $\xi=1$. Many of the terms of K1 will be zero since only the nodes on the $\xi=1$ boundary will have shape functions which are non-zero. It is through K1 that the temperatures for each region are coupled together. Equation (68) may now be written as

$$r_a H_{gap}\{[K1]\{\tau_F\}^e-[K1]\{\tau_c\}^{e*}\}+k_F[H12]\{\tau_F\}^e$$

$$-e\Sigma_{fF}[H3]\{\psi_F\}^e + \rho_F C_{pF}[H2]\{\dot{\tau}_F\} = 0 \tag{70}$$

In obtaining this equation, it was assumed that material properties for each nodal point were constant at each time step. Perhaps a better assumption would have been to assume an average value for the properties of each element. The difference should not be significant, and the assumed constant nodal properties were numerically more tractable.

2. Clad Region

Applying equation (37) to the governing field equation for the clad, equation (25) gives the discretized form of the equation. Assuming no heat transfer in the axial direction on the boundaries (Boundary condition 5), equation (25) becomes

$$-\int_z [N_i r k_c \frac{\partial T_c}{\partial r}\Big|_a^b dz + \int_r \int_z k_c [\frac{\partial N_i}{\partial r}\frac{\partial T_c}{\partial r} + \frac{\partial N_i}{\partial z}\frac{\partial T_c}{\partial z}] \, r dr dz$$

$$+ \int_r \int_z \rho_c C_{pc} N_i \frac{\partial T_c}{\partial t} r dr dz = 0 \qquad (71)$$

In the cladding, there are two interfaces along which the line integral of equation (71) is not zero, along the fuel-clad interface and along the clad-coolant interface. For the fuel-clad interface, equation (61) applies. For the clad-coolant interface, the interface condition, equation (30), may be rewritten as

$$k_c \frac{\partial T_c}{\partial r} = hsurf\ (T_c - T_{co}) = -k_{co} \frac{\partial T_{co}}{\partial r} \qquad (72)$$

Along the fuel-clad interface, the local coordinate corresponds to $\xi=-1$. Define the new element matrix

$$\int_{-1}^{1} \int_{-1}^{1} \{N_i\}^e \langle N_j \rangle^e d\eta = [K2_{ij}]_{8x8} = \frac{L^e}{2} \sum_{k=1}^{m^2} (N_i)_k \, (N_j)_k \, W_k$$

where the N's are evaluated at $\xi=-1$. As with K1, K2 will have many zero values because the shape functions are evaluated at $\xi=-1$.

Along the clad-coolant interface, the local coordinate corresponds to $\xi=1$ and the K1 matrix is appropriate.

Substituting equations (67) and (72), equation (71) becomes

$$\int_z [rh_{surf}N_i(T_c-T_{co})|_b \, dz - \int_z [rH_{gap}N_i(T_F-T_c)|_a \, dz$$

$$+ \int_r \int_z k_c\left[\frac{\partial N_i}{\partial r}\frac{\partial T_c}{\partial r} + \frac{\partial N_i}{\partial z}\frac{\partial T_c}{\partial z}\right] rdrdz$$

$$+ \int_r \int_z \rho_c \, C_{pc} \, N_i \frac{\partial T_c}{\partial t} \, rdrdz = 0 \qquad (73)$$

The governing equation for the clad region may now be written as

$$r_a H_{gap}\{[K2]\{\tau_c\}^e - [K2]\{\tau_F\}^{e*}\} + r_b h_{surf}\{[K1]\{\tau_c\}^e - [K1]\{\tau_{co}\}^{e*}\}$$

$$+ k_c[H12]\{\tau_F\}^e + \rho_c \, C_{pc}[H3]\{\dot{\tau}_c\} = 0 \qquad (74)$$

The line integrals of equation (73) affect only nodes which are on one of the boundaries; therefore, the nodal inputs into K1 and K2 are zero unless the node is on one of the boundaries.

3. <u>Coolant Region</u>

The field equation governing the coolant may be discretized in the same manner as above. After applying the Galerkin method and performing an integration by parts

on the second order terms, equation (25) becomes

$$-\int_z [rN_i k_{co} \frac{\partial T}{\partial r}\Big|_b^c dz + \int_r \int_z k_{co}[\frac{\partial N_i}{\partial r}\frac{\partial T_{co}}{\partial r} + \frac{\partial N_i}{\partial z}\frac{\partial T_{co}}{\partial z}]\, rdrdz$$

$$+ \int_r \int_z V_{co}\, \rho_{co}\, C_{pco}\, N_i \frac{\partial T_{co}}{\partial z}\, rdrdz$$

$$+ \int_r \int_z \rho_{co}\, C_{pco}\, N_i \frac{\partial T_{co}}{\partial t}\, rdrdz = 0 \qquad (75)$$

The line integral, when evaluated at c, is zero (boundary condition 4). When evaluated at b, or correspondingly at $\xi=-1$, equation (72) is valid and K2 matrix is appropriate. All the terms of equation (75) have been defined except the flow term. Define

$$\int_{-1}^{1}\int_{-1}^{1} \{N_i\}^e \langle N_{i,\eta}\rangle^e r \det[J] d\xi d\eta = [H5_{ij}]_{8x8}$$

$$= \frac{A^e}{4} \sum_{k=1}^{m^2} (N_i)_k\, (N_{i,\eta})_k\, r_k W_k \qquad (76)$$

Transforming to local coordinates and integrating reduces equation (75) to

$$r_b h_{surf}\{[K2]\{\tau_{co}\}^e - [K2]\{\tau_c\}^{e*}\} + k_{co}[H12]\{\tau_{co}\}^e$$

$$+ V_{co}\rho_{co}C_{pco}[H5]\{\tau_{co}\}^e + \rho_{co}C_{pco}[H3]\{\dot{\tau}_{co}\}^e = 0 \qquad (77)$$

Now that the governing equations have been defined for each region on the element level, equations (70), (74), and (77), they may be assembled into a system equation on the global level. The equation will be in the general form of

$$[K]_{nxn}\{\tau\}_{nx1} + [M]_{nxn}\{\psi\}_{nx1} + [G]_{nxn}\{\dot{\tau}\}_{nx1} = 0 \tag{78}$$

D. DISCRETIZATION OF THE SPATIAL DOMAIN

Prior to the numerical solution of the governing equations, equations (64) and (78), the spatial domain must be divided into a number of elements. For this work the domain was subdivided as shown in figure 5.

Since there is a discontinuity of temperatures at the interfaces, as described by equations (29) and (30), a noval application of the FEM method was necessary. The common practice for handling these "flux" type boundary conditions is to define a constant reference temperature, T_∞, as when working with a convection heat transfer problem [17], or to define a known function, as when working with a fracture mechanics problem [18]. In either case the reference condition was known. The novel application here lies in the use of a different field equation to describe the reference temperature, e.g., the clad equation (74) is the reference condition for heat transfer from the fuel across the gap interface.

The discontinuity of temperature at the interface necessitated another novel application of the FEM. Since there is a temperature drop along each interface, a single node there is not adequate. In the discretization of the domain, two nodes were used for each interface point (for example, points 62 and 63 in figure 6). This allows the temperature drop due to the gap and film conductances to be taken into consideration. Since two nodes are used, the governing equations for each region are not directly coupled together. The coupling of the regions is accomplished by the "flux" boundary or interface conditions since it is assumed that any heat flux leaving a region enters the adjacent region. Consider a typical set of elements on an interface





Figure 6. Finite Element Discretization

The coupling terms K1 and K2 may be combined into a system K matrix which shows the coupling. The K matrix for the simple set shown is

$$
\begin{array}{c}
\begin{array}{cccccccccccccc} 1 & 2 & 3 & 4 & 5 & 6 & 7 & 8 & \cdots & 13 & 14 & 15 & 16 \end{array} \\
\begin{array}{c} 1 \\ 2 \\ 3 \\ 4 \\ 5 \\ 6 \\ 7 \\ 8 \\ \vdots \\ 13 \\ 14 \\ 15 \\ 16 \end{array}
\begin{bmatrix}
 & & & & & & & & & & & & \\
 & a & -a & & & & c & -c & & c & -c & & \\
 & -a & a & & & & -c & c & & -c & c & & \\
 & & & & & & & & & & & & \\
 & & & & & & & & & & & & \\
 & & & & & & & & & & & & \\
 & c & -c & & & & b & -b & & d & -d & & \\
 & -c & c & & & & -b & b & & -d & d & & \\
 & & & & & & & & & & & & \\
 & c & -c & & & & d & -d & & b & -b & & \\
 & -c & c & & & & -d & d & & -b & b & & \\
 & & & & & & & & & & & & \\
 & & & & & & & & & & & &
\end{bmatrix}
\end{array}
\qquad
\begin{array}{l}
a = 16/15 \\
b = 4/15 \\
c = 2/15 \\
d = 1/15
\end{array}
$$

As can be seen, the nodes on the interface are coupled to the adjacent element interface nodes. For example, node 2 in element I is coupled to nodes 3, 8, and 14 in element II.

E. OPTIMUM COMPACTING SCHEME

The system matrices (H, P , etc.) are nxn matrices, where n is the number of nodal points used in the discretization of the domain. In terms of computer storage, these matrices may become excessively large if they are stored as nxn. There are several techniques available to reduce this storage requirement. The most common method is the banded storage scheme, whereby only the banded portion of the matrices are stored. With judicious numbering of the nodes,

considerable savings may be realized. However, it is not the optimum storage scheme [8].

Since the shape functions, N_i, for the $k^{\underline{th}}$ nodal equation are nonzero over only the element containing k, the system matrices are not only banded but sparse as well. The sparseness is due to the non-consecutive numbering of the nodes surrounding the $k^{\underline{th}}$ node. The optimum compact storage (OCS) scheme compacts the matrices by storing only the non-zero elements of the matrices. The implementation of the OCS scheme requires two additional integer arrays, say JA and NAME. The NAME array identifies the nodal points which contribute to each nodal equation. The JA array acts as a pointer to indicate where the nodal equation starts in NAME. Consider the following simple 2x2 system with nodes as indicated



The NAME array starts with node 1 and identifies the nodes which contribute to node 1 (i.e., 5, 4, and 2). The NAME array would, then, give the nodes contributing to node 2 and so forth, so that

```
                1234 : 5678910 :11 1213 14 : ... :   JC
<NAME> = <1542 : 254163  : 3 6 5 2  : ... : 9856>
and
                1 2 3
<JA>   = <1 5 11 ...>
```

The algorithm to assemble the element matrices into a compact storage vector is straightforward and represents a significant savings in computer storage [8]. The system matrices are stored as a vector rather than a two-dimensional array. For example, the value which would be stored in position (1,5) of the nxn array is stored in position 2 of the system vector.

VI. NUMERICAL SOLUTION

This section contains a brief description of possible solution techniques in addition to the solution technique chosen. Computer subroutines necessary to implement the technique are also described.

A. SELECTION OF METHOD

The numerical solution of the system of implicit ordinary differential equations, equations (64) and (78), may be accomplished by any of a number of different techniques such as Houbolt's method, Crank-Nicolson's method, Gear's method, or implicit Gear's method. It was not the objective of this analysis to determine which of the numerical solution schemes is the most efficient. Each method has its advantages and disadvantages. The Crank-Nicolson method is a single-step, implicit equation solver and, therefore, does not require storage of previous time solutions. When analyzing neutronic problems, the system of equations which arises is commonly very stiff (i.e., a rapid change in flux over a short period of time). The Crank-Nicolson method has, in a past work [8], demonstrated difficulty in tracking these stiff systems. Gear's method was specifically developed for stiff systems and can handle the problem very well. However, Gear's method is a multi-step, predictor-corrector method requiring storage of previous time solutions. In addition to this disadvantage, Gear's method requires the

transformation of the developed implicit O.D.E.'s into an explicit system of O.D.E.'s. After this transformation is done, the system matrices are no longer sparse or banded, thus eliminating the use of the optimum compacting scheme. In an effort to overcome these difficulties, Gear's method was modified, Ref. [9], to treat the implicit system of equations as well as to allow use of the optimum compacting scheme. A previous work, Ref. [8], has shown that the implicit Gear's method is particularly attractive in solving the type problem developed in this analysis. Therefore, the implicit Gear's method is used for the solution of the system of O.D.E.'s arising in this analysis.

No attempt will be made here to give the mathematics involved in developing the implicit Gear's method. Reference [9] may be consulted if details are desired. A listing of the computer program developed will be given in the Computer Program section. In order to utilize the implicit Gear's method, several user supplied subroutines must be developed: 1) DIFFUN, 2) JACMAT, and 3) RUITSL.

B. USER SUPPLIED SUBROUTINES TO IMPLEMENT THE IMPLICIT GEAR'S METHOD

1. DIFFUN

Subroutine DIFFUN evaluates equations (64) and (78) for a given time and for given values of ψ, $\dot{\psi}$, τ and $\dot{\tau}$. Since at each nodal point, i, there is a solution for the flux and for the temperature, the solution was set equal to DYI and DYII, respectively. In addition to having flux and

temperature at each nodal point, there are also three different regions in the domain which have different governing equations. An integer array, ITYPE, was developed to indicate for each nodal point whether it was: 0) a fuel node not in an interface element, 1) a fuel node in an interface element, 2) a cladding node or, 3) a coolant node. Using ITYPE, the computer program is directed to a different section depending upon the type of node being considered. After all the nodes have been considered, boundary conditions are established by changing DYI and DYII for the appropriate boundary nodes. Since in this analysis there is continuity of flux at the interfaces, special considerations must be given to these nodes. At the fuel-clad interface, the value of DYI for the clad node was set to the value of the flux at that node minus the value of the flux at the adjacent node (i.e., $DYI_i = \psi_i - \psi_{i-1}$). Similarly, at the clad-coolant interface, the value of DYI for the coolant node was set to the value of the flux at that node minus the value of the flux at the adjacent node. During the solution of the problem, DYI is driven toward zero, which in the limit forces ψ_i to equal ψ_{i-1}. This is the desired continuity result.

2. <u>JACMAT</u>

Subroutine JACMAT, evaluates the Jacobian matrix (for Gear's method) at the given time and for the current values of the dependent variables. The Jacobian for an equation of the type,

$$F(y, \dot{y}, t) = 0 \qquad (79)$$

may be represented as [19],

$$J = [\frac{\partial F}{\partial y} - \frac{\alpha_o}{\beta_o h} \frac{\partial F}{\partial \dot{y}}] \tag{80}$$

where α_o and β_o are coefficients from Gear's method and h is the time step. Using the notation of DIFFUN, let DYI and DYII represent equations (64) and (78), respectively. The Jacobian matrix may, then, be written as (J is called PW in JACMAT.)

$$PW = [\frac{\partial DYI}{\partial \psi} - \frac{\alpha_o}{\beta_o h} \frac{\partial DYI}{\partial \dot{\psi}} , \frac{\partial DYII}{\partial \tau} - \frac{\alpha_o}{\beta_o h} \frac{\partial DYII}{\partial \dot{\tau}}] \tag{81}$$

It is the form of equation (81) which is programmed in JACMAT. As in DIFFUN, the integer array ITYPE is used to indicate the appropriate section of the program to be utilized. The problem boundary conditions must also be accounted for in JACMAT. In DIFFUN, the value of DYI or DYII was set to zero for constant boundary conditions (i.e., zero). This cannot be done in JACMAT since a division by zero would occur. For a constant boundary condition at the ith node, the value of PW is set to one for the diagonal term and zero for all other terms of the ith equation.

3. <u>NUITSL</u>

Subroutine NUITSL solves the system of equations for the quasi-Newton iterates. In this analysis the system is solved using a successive over-relaxation (SOR) method. In this work, the optimum amount of over-relaxation was not determined. Since no effort was made to find the optimum,

it was felt a small over-relaxation would be best. The over-relaxation factor of 0.02 was used. For small values of this factor, the SOR method approaches the Gauss-Siedel iteration technique.

VII. PROCEDURE

In this section, the method utilized to obtain a solution is described. The input data necessary to run the developed computer program will be documented.

Prior to initiating a transient overpower excursion, the steady-state conditions for the fuel cell must be known. Since the system of equations which were developed are not specifically designed to obtain a steady-state solution, the initial steady-state conditions must be part of the input data. The initial temperature distribution was obtained from the steady-state conditions given in Ref. [7].

The axial temperature distribution for the fuel centerline, fuel surface, clad, and coolant have been determined for several different fuel life cycles [7]. For this analysis, the beginning of life cycle for channel 10 was used. Although this distribution is somewhat artificial, it should be adequate for this analysis. It is the trends of the results which are considered important. The distribution within the fuel radially is taken to vary as the square of the radial distance; then

$$T_F(r,z,0) = T_F(0,z,0)\left(1-\frac{r^2}{a^2}\right) + T_F(a,z,0)\left(\frac{r^2}{a^2}\right)$$

Within the cladding and the coolant, the initial radial temperature distribution is assumed to be constant.

The initial flux distribution is assumed to be radially constant, a flat flux assumption. In the axial direction the flux is assumed to vary as the shape of the sine function. The maximum flux, the flux at the axial center, is an input parameter. For this analysis, the maximum initial flux was taken to be 10^{14} neutron/cm^{2}sec.

To obtain a steady state flux distribution, the value of fission cross section for the fuel is varied. A trial-and-error method is used until a critical fission cross section, Σ_{fF}^{cr}, which gives a steady flux is obtained.

Once the steady-state conditions have been determined, the excess reactivity may be inserted. This starts the transient overpower excursion.

A. INPUT DATA

The first data card contains: the order of Gauss quadrature, the number of radial elements in the fuel, the number of axial elements, number of nodal points in the radial direction, and the height of the fuel rod. The next cards, one for each radial nodal point, contain the nodal radial distances. The next cards contain the fuel centerline, fuel surface, clad and coolant temperatures. There is one card for each axial node. The next card contains the maximum flux. The next four cards contain the physical parameters listed in Table I. The last input cards contain the time, end time, estimated initial time step, minimum time step, and maximum time step. A sample data deck is shown in figure 7.

TABLE I. Physical Parameters

Fuel Diffusion Coefficient (DCF)	0.93 [cm]
Doppler constant (B)	0.006
Energy release per fission (E)	7.652×10^{-12} [cal/fissions]
Fraction of delayed neutrons (BETA)	0.0064
Fraction of delayed neutrons for the ith group (BETAI)	0.0064
Decay constant for ith delayed neutron group (DCLAMI)	0.0784
Initial flux for delayed neutrons	1×10^{10} [neutron/cm^{2}sec]
Average number of neutrons released per fission (ANU)	2.44
Neutron velocity (VEL)	4.8×10^8 [cm/sec]
Fual absorption cross section (SIGAF)	0.088 [cm^{-1}]
Critical fuel fission cross section (SIGFF)	0.0586875 [cm^{-1}]
Blanket absorption cross section (SIGAB)	0.0 [cm^{-1}]
Blanket fission cross section (SIGFB)	0.0 [cm^{-1}]
Step reactivity input (RHOA)	Variable
Ramp reactivity input (RHOB)	Variable
Fuel density (DENF)	10.9 [gm/cm^3]
Clad diffusion coefficient (DCC)	1.1 [cm]
Clad specific heat (CPC)	0.12 [cal/gm °C]
Clad density (DENC)	8.0 [gm/cm^3]
Clad thermal conductivity (TKC)	0.0526 [cal/cm sec °C]
Clad absorption cross section (SIGAC)	0.0015 [cm^{-1}]
Coolant diffusion coefficient (DCCO)	1.55 [cm]
Coolant absorption cross section (SIGACO)	0.00004 [cm^{-1}]
Coolant flow velocity (VCO)	396.0 [cm/sec]
Surface heat transfer coefficient(HSURF)	0.7 [cal/cm^{2}sec °C]

```
0.0      2.0      1.0E-12  1.0E-20  0.1
1.55     4.0E-05  396.0    0.7
1.1      0.12     8.0      0.0526   0.0015
4.0E08   0.086    .588800E-1  0.049   0.0      0.0      0.064    10.9
0.98     0.006    7.652E-12   0.0064  0.0064   0.0764   1.0E10   2.44
1.80E14
1420.    847.     594.     575.
1460.    853.     591      571.
```

ONE DATA CARD PER AXIAL NODE

```
1500.    755.     413.     387.
1540.    743.     407.     380.
0.365
0.3285
0.292
0.292
0.273
0.254
0.254
0.127
0.0
3   1   22   9   33.0
```

SAMPLE DATA DECK



Figure 7. Sample Data Deck

VIII. RESULTS

When using the finite element method, one of the first considerations must be given to the convergence of the method. To determine convergence, the results for a given point are compared for different finite element discretizations. As shown in figure 8, the results are comparable but no definite claim of convergence can be made. However, for this work, it was felt that these results were adequate. It was not the object of this analysis to arrive at the "final" result; it was the trends and methods that were of interest. Since the 66-element mesh appears to give a fair approximation of the results, the 66-element mesh was used as the discretized domain.

The next item of consideration was the determination of a neutronic steady-state condition. This proved to be a very time consuming task. The fission cross section for the fuel was varied by a trial-and-error method in an attempt to find the critical cross section which would give a steady state. As may be seen in figure 9, a change in cross section of less than one percent significantly affected the state of the problem. It was felt that the critical value was between the values of 0.05875 and 0.058625. Time did not permit investigation for critical value; therefore, it was assumed that the value for the critical fission cross section was half way between the values (i.e., $\Sigma_f^{cr} = 0.0586875$).



Figure 6. Convergence of Finite Element Method



Figure 9. Determination of Critical Fission Cross Section

Even if this value is in error, which it most probably is, the net effect would only be a small decrease or increase in the proposed reactivity insertion. The reactivity insertion would, then, be an approximation of the actual reactivity of the problem.

The first test problem considered was a step increase in reactivity of approximately ten dollars. For the uranium dioxide fuel, one dollar of reactivity was taken to be 0.0064. Figure 10 shows the time history of the flux at the center of the fuel rod. Figure 11 gives the corresponding temperature profile. The temperatures were taken at the hottest point of each region at the axial center (i.e., the fuel centerline, clad inside surface, and coolant inside surface). As seen on the fuel temperature time history, the fuel rapidly reaches the fuel melting point. The model developed does not take into consideration melting of the fuel. This melting would tend to decrease the effect of the transient. The problem was allowed to continue despite this inconsistency in the mathematical model. A short time after fuel melting, the inside surface of the clad reaches its melting point. The temperature in the coolant experienced what is felt to be a numerical phenomenon. The coolant temperature decreased prior to the small rise at the end of the transient. Intuitively, this decrease does not seem to be realistic. A similar occurrence was observed while conducting sample tests on the developed computer program. Reference [20] reported the same phenomenon. It is felt that this



Figure 10. Flux Profile



Figure 11. Temperature Profile

phenomenon is a quirk of the finite element method. The radial and axial distributions of the neutron flux are presented in figures 12 and 13 for time equal to 7.39×10^{-3} seconds. The distributions are, basically, as anticipated. The neutron flux peaks slightly before the axial center. It was expected to peak at the axial center. The radial and axial temperature distributions for the same time are presented in figures 14 and 15. As with the flux, the temperature profiles were, basically, as expected. The fuel temperature peaks slightly below the expected location, most likely in response to the peak in axial fluxes. The coolant unexpectedly drops near the outlet of the fuel rod. The finite element method characteristically has some problems on the boundaries of the domain; this may account for the drop in coolant temperature.

The temperature of the fuel and cladding do not appear to be as closely coupled as anticipated. As seen in figure 14, a significant increase in fuel temperature has resulted in a relatively small clad temperature increase. As noted in figure 11, there appears to be a time lag in temperature response for each region which may account for part of the apparent temperature disagreement. It is felt that the temperatures should be more closely related, which indicates a higher gap heat transfer coefficient should be utilized. Since values of the gap heat transfer coefficient were assumed, it is not unreasonable to believe the values used are too low.



Figure 12. Radial Flux



Figure 13. Axial Flux Profile



Figure 14. Radial Temperature Profile



Figure 15. Axial Temperature Profile

Time did not permit investigation of other reactivity insertions. Other reactivity inputs may be investigated by students in the future.

This work does not represent a solution to the very complicated nuclear reactor problem. It does represent an application of a numerical technique which is relatively new to nuclear applications. Methods for implementing the finite element method have been discussed, and a computer code has been developed for the simplistic model considered.

IX. RECOMMENDATIONS

For the model developed, perhaps the most important item to pursue is the critical fission cross section. A better determination of this value is necessary so that the reactivity insertion is more accurately known. Different test cases for the prompt critical and prompt subcritical reactor could then be conducted.

In further developing the model, more consideration should be given the gap heat transfer coefficient. As noted in the results, the value used appears to be too small. Sample problems for different gap heat transfer coefficients would give a better indication of the values to use.

Melting of the fuel during the transient would probably be the next major improvement on the model. With relatively few changes, the model could be adapted to allow melting element by element. This, too, would be an approximation but, still, an improvement to the model. Perhaps at the same time, a simplified model to take into consideration the fuel restructuring could be implemented.

Another improvement would be to consider reactivity feedbacks in addition to the Doppler feedback. Sodium voiding and fuel rod expansion are two of the more important feedback effects to consider.

On the numerical side, probably the most important thing to do would be to run the computer program on the

"H-compiler", which optimizes the program. However, on several runs using the H-compiler, erroneous results were obtained. With sufficient time, this could be corrected to allow use of the H-compiler. The use of the H-compiler results in a savings in computer time. The present program runs on a "G-compiler" and takes excessive amounts of computer time (two to four hours per run).

In addition to this, the optimum over-relaxation factor in the implicit Gear's method could be determined by trial-and-error.

Implementation of these recommendations should enhance the analysis and lead to a more efficient computer code.

APPENDIX A

DEVELOPMENT OF TRANSFORMATIONS

The Jacobian matrix [J] may be written (8) for two dimensions as

$$[J] = \begin{bmatrix} \sum_{i=1}^{N} N_{i,\xi} r_i & \sum_{i=1}^{N} N_{i,\xi} z_i \\ \sum_{i=1}^{N} N_{i,\eta} r_i & \sum_{i=1}^{N} N_{i,\eta} z_i \end{bmatrix}. \quad \text{(A1)}$$

For a simple 2x2 matrix [A] the inverse is

$$[A] = \begin{bmatrix} a & b \\ c & d \end{bmatrix}$$

$$[A]^{-1} = \frac{1}{\det[A]} \begin{bmatrix} d & -b \\ -c & a \end{bmatrix}$$

Applying this fact to equation (A1) gives

$$[J]^{-1} = \frac{1}{\det[J]} \begin{bmatrix} \sum_{i=1}^{N} N_{i,\eta} z_i & -\sum_{i=1}^{N} N_{i,\xi} z_i \\ \sum_{i=1}^{N} N_{i,\eta} r_i & \sum_{i=1}^{N} N_{i,\xi} r_i \end{bmatrix} \quad \text{(A2)}$$

$$= \begin{bmatrix} J_{11}^{*} & J_{12}^{*} \\ J_{21}^{*} & J_{22}^{*} \end{bmatrix}$$

From matrix algebra

$$\det[J] = \sum_{i=1}^{N} N_{i,\xi} r_i \sum_{i=1}^{N} N_{i,\eta} z_i - \sum_{i=1}^{N} N_{i,\eta} r_i \sum_{i=1}^{N} N_{i,\xi} z_i \quad \text{(A3)}$$

The derivatives of the shape functions may be found from equations (38).

$$\begin{aligned}
N_{1,\xi} &= \tfrac{1}{4}(1+\eta)(2\xi+\eta) & N_{1,\eta} &= \tfrac{1}{4}(1+\xi)(2\eta+\xi) \\
N_{2,\xi} &= -\xi(1-\eta) & N_{2,\eta} &= \tfrac{1}{2}(1-\xi^2) \\
N_{3,\xi} &= \tfrac{1}{4}(1+\eta)(2\xi-\eta) & N_{3,\eta} &= \tfrac{1}{4}(1-\xi)(2\eta-\xi) \\
N_{4,\xi} &= -\tfrac{1}{2}(1-\eta^2) & N_{4,\eta} &= -\eta(1-\xi) \\
N_{5,\xi} &= \tfrac{1}{4}(1-\eta)(2\xi+\eta) & N_{5,\eta} &= \tfrac{1}{4}(1-\xi)(2\eta+\xi) \\
N_{6,\xi} &= -\xi(1-\eta) & N_{6,\eta} &= -\tfrac{1}{2}(1-\xi^2) \\
N_{7,\xi} &= \tfrac{1}{4}(1-\eta)(2\xi-\eta) & N_{7,\eta} &= \tfrac{1}{4}(1+\xi)(2\eta-\xi) \\
N_{8,\xi} &= \tfrac{1}{2}(1-\eta^2) & N_{8,\eta} &= -\eta(1+\xi)
\end{aligned} \quad \text{(A4)}$$

If one now considers an arbitrary element



with the midside nodes exactly at the midpoint (not a necessary criteria for the FEM) and substitutes into equation (A3),

the result is

$$\det[J] = \frac{(z_3-z_1)(r_3-r_1)}{4} = \frac{A^e}{4} \tag{A5}$$

Substituting into equation (A2) and using (A5) will yield

$$J_{11}^* = \frac{4}{A^e}\left[\tfrac{1}{2}(z_3-z_1)\right] = 2/r_3-r_1 \ , \tag{A6}$$

$$J_{12}^* = 0 \ , \tag{A7}$$

$$J_{21}^* = 0 \ , \tag{A8}$$

and

$$J_{22}^* = \frac{4}{A^e}\left[\tfrac{1}{2}(r_3-r_1)\right] = 2/z_3-z_1 \ . \tag{A9}$$

The inverse of the Jacobian matrix now becomes

$$[J]^{-1} = \begin{bmatrix} 2/r_3-r_1 & 0 \\ 0 & 2/z_3-z_1 \end{bmatrix} \ . \tag{A10}$$

For integration along a line, the transformation used is

$$dz = \det[J']d\eta \tag{A11}$$

in this case

$$\det[J'] = \sum_{i=1}^{N} N_{i,\eta} z_i \tag{A12}$$

Again considering the arbitrary element and substituting (A4) into (A12) will result in

$$\det[J'] = \frac{z_3-z_1}{2} = \frac{L^e}{2} \tag{A13}$$

APPENDIX B

REDUCTION OF SECOND ORDER TERM

The second order term of the governing field equations may be reduced to first order by integration by parts. Consider, for example,

$$\int_r\int_z N_i\left[\frac{1}{r}\frac{\partial}{\partial r}\left(rD\frac{\partial\psi}{\partial r}\right) + \frac{\partial}{\partial z}\left(D\frac{\partial\psi}{\partial z}\right)\right] rdrdz \tag{B1}$$

which may be expanded as

$$\int_r\int_z \left[N_i rD\frac{\partial^2\psi}{\partial r^2} + N_i r\frac{\partial D}{\partial r}\frac{\partial\psi}{\partial r} + N_i D\frac{\partial\psi}{\partial r} + N_i rD\frac{\partial^2\psi}{\partial z^2} + N_i r\frac{\partial D}{\partial z}\frac{\partial\psi}{\partial z}\right] drdz \tag{B2}$$

Integrating just the second order terms by parts will yield

$$\int_r\int_z N_i D\frac{\partial^2\psi}{\partial r^2} rdrdz = \int_z \left[N_i rD\frac{\partial\psi}{\partial r}\Big|_r dz - \int_r\int_z \frac{\partial\psi}{\partial r}\left[DN_i + rN_i\frac{\partial D}{\partial r} + rD\frac{\partial N_i}{\partial r}\right] drdz \tag{B3}$$

and

$$\int_r\int_z N_i D\frac{\partial^2\psi}{\partial z^2} rdrdz = \int_r \left[N_i D\frac{\partial\psi}{\partial z}\Big|_z rdr - \int_r\int_z \frac{\partial\psi}{\partial z}\left[\frac{\partial N_i}{\partial z} D + N_i\frac{\partial D}{\partial z}\right] rdrdz \tag{B4}$$

Substituting the results of (B3) and (B4) into equation (B2) will give

$$\int_z \left[N_i rD\frac{\partial\psi}{\partial r}\Big|_r dz + \int_r \left[N_i D\frac{\partial\psi}{\partial z}\Big|_z rdr - \int_r\int_z D\left[\frac{\partial N_i}{\partial r}\frac{\partial\psi}{\partial r} + \frac{\partial N_i}{\partial z}\frac{\partial\psi}{\partial z}\right] rdrdz \tag{B5}$$

APPENDIX C

LIST OF RELATIONS FOR MATERIAL THERMAL PROPERTIES

A. FUEL (UO_2)

1. Specific Heat, Ref. [19]

$$C_{pF} = [18.45+2.431\times10^{-3}T-2.272\times10^{-5}T^2]/270.07$$

[cal/gm °C]

T - °C

2. Thermal Conductivity, Ref. [5]

$$Tk_F = [1-2.5(1-\rho_{TD})]\times[\frac{45.1}{135+T} + 4.79\times10^{-13}T^3]\times0.239$$

[cal/cm sec °C]

ρ_{TD} - percent theoretical density

T - °K

B. CLAD (Stainless Steel)

Properties are assumed to be temperature independent, and average values from Ref. [5] were used for the clad properties.

C. COOLANT (Liquid Sodium)

1. Specific Heat, Ref. [5]

$$C_{p_{co}} = 0.34574-0.79226\times10^{-4}T+0.34086\times10^{-7}T^2$$

[cal/gm °C]

T - °F

2. Density, Ref. [5]

$$\rho_{co} = [59.566-7.9504\times10^{-3}T-0.2872\times10^{-6}T^2 + 0.06035\times10^{-9}T^3] \times 0.01601 \quad [gm/cm^3]$$

T - °F

3. Thermal Conductivity, Ref. [5]

$$Tk_{co} = [54.306-1.878\times10^{-2}T+2.0914\times10^{-6}T^2] \times 4.134\times10^{-3} \quad [\text{cal/cm sec } °C]$$

T - °F

D. SURFACE HEAT-TRANSFER COEFFICIENT

$$h_{surf} = \frac{Tk_{co}}{De}\left[7.0+0.025\left(\frac{De\ V_{co}\rho_{co}C_{p_{co}}}{Tk_{co}}\right)^{0.8}\right] \quad [\text{BTU/hr ft}^2\ °F]$$

Tk_{co} - [BTU/hr ft °F]

ρ_{co} - [lbm/ft^3]

V_{co} - [ft/sec]

$C_{p_{co}}$ - [BTU/lbm °F]

De - equivalent diameter [ft]

```
C     MAIN PROGRAM CALLS THE VARIOUS SUBROUTINES
C
      IMPLICIT INTEGER*2(I-N)
      INTEGER*4 NY,NL,M,JSKF
      REAL*8 SN,DESN,DXSN,WT,GP,STJ11,STJ22,DETJ,XW,XSN
C
C     THE FOLLOWING DIMENSION STATEMENTS MUST BE
C     CHANGED FOR EACH DIFFERENT PROBLEM CONSIDERED
C
      DIMENSION BIGH12(5525),BIGH3(5525),BIGH4(5525),BIGH5(5525),
     1   BIGK(5525),NAME(5525)
      DIMENSION BIGF(350),R(350),Z(350),YIT(350),JA(350),JB(350),
     1   ITYPE(350),NAME(26,350)
      DIMENSION Y(7,700),W(28000),NELCON(11,66),NSTART(66),IBP(66)
C
C     APPROPRIATE DIMENSIONS ARE
C             BIGH12,BIGH3,BIGH4,BIGH5,BIGK,NAME-----------JC
C             BIGF,R,Z,YIT,JA,JB,ITYPE---------------------NP
C             NAME(26, BY ----------------------------------NP
C             NELCON(11, BY --------------------------------NEL
C             NSTART,IBP------------------------------------NEL
C             Y,W AS REQUIRED BY FRANKE'S SUBROUTINES
C             JC IS THE TOTAL NUMBER OF NODES SEEN BY THE NODES
C             NP IS THE NUMBER OF NODAL POINTS
C             NEL IS THE NUMBER OF ELEMENTS
C     ALL THE REST OF THE SUBROUTINES WILL HAVE THEIR DIMENSIONS
C     CHANGED THOUGH THE CALLING STATEMENTS SO THAT THE ABOVE
C     DIMENSIONS ARE THE ONLY ONES WHICH REQUIRE CHANGING
C
      DIMENSION DR(13)
      DIMENSION H12(8,8),H3(8,8), F(8)
      DIMENSION H4(8,8)
      DIMENSION GP(5), SN(8,25), DESN(8,25), DXSN(8,25), STJ11(25),XW(5)
      DIMENSION STJ22(25), XSN(5,5), WT(25)
      DIMENSION NDUM(3)
      DIMENSION XK1(8,8), XK2(8,8)
      COMMON/CLAD/ DCC,CPC,DENC,TKC,SIGAC,HGAP
      COMMON/COMN/ NP,NEL,JC
      COMMON/COOL/DCCO,SIGACC,VCO,HSURF
      COMMON/FUEL/DCF,B,E,BETA,BETAI,CCLAMI,FFLUXC,AKINF,VEL,
     1   SIGAF,SIGFF,SIGAB,SIGFB,DENF
      COMMON/GP/ GP,NORD
      COMMON/INP/DR,HEIGHT,NPR,NEZ,NFE
      COMMON/JACINV/ STJ11,STJ22,DETJ
      COMMON/K1MAT/XK1,XK2
      COMMON /MATRIX/ H12, H3, F
      COMMON/MTRXH4/ H4
      COMMON/REACT/ RHOA,RHOB
```

```
      COMMON/SHAPFUN/SN, DESN, DXSN
      COMMON/TIME/ FF,G,RHO
      COMMON /WEIGHT/ WT
   10 FORMAT (4I5,F10.5)
   11 FORMAT('0',9X,'JSXF = ',I5)
   15 FORMAT (8F10.5)
   20 FORMAT ('0',8(8F15.6,/))
   25 FORMAT ('0',10X,'ORDER OF GAUSS QUADRATURE IS',I5,//,10X,'NUMBER O
     1F RADIAL FUEL ELEMENTS IS',I5,//,10X,'NUMBER OF AXIAL FUEL ELEMENT
     2S IS',I5,//,10X,'NUMBER OF RADIAL NODAL POINTS IS',I5,//,10X,
     3  'FUEL ROD HEIGHT (CM) IS',F10.5)
   30 FORMAT (F10.5)
   35 FORMAT ('0','     RADIAL NODAL COORDINATES',/,5X,13F9.4)
   40 FORMAT('0',14X,'DCF',10X,'B',11X,'E',9X,'BETA',8X,'BETAI',6X,
     1    'COLAMI',8X,'NU',9X,'KINF')
   41 FORMAT (9X,9E12.5)
   42 FORMAT('0',12X,'FFLUXO',8X,'VEL',8X,'SIGAF',7X,'SIGFF',7X,
     1    'SIGAB',7X,'SIGFB',7X,'SIGAC',6X,'SIGACC')
   43 FORMAT('0',14X,'DCC',9X,'CPC',8X,'CENC',9X,'TKC',8X,'CCCC',
     1    10X,'VCO',8X,'HSURF',8X,'DENF')
   44 FORMAT('0',5X,'RHO = RHOA + RHOB*T',//,6X,'RHOA = ',F10.3,
     1 10X,'RHOB = ',F10.3)
C     INPUT THE ORDER OF THE GAUSS QUADRATURE ---- 3,4, OR 5
C     INPUT THE NUMBER OF RADIAL ELEMENTS IN THE FUEL ---1 OR 2
C     INPUT THE NUMBER OF AXIAL ELEMENTS
C     INPUT THE NUMBER OF NODAL POINTS IN THE RADIAL DIRECTION--2*NFE+7
C     INPUT THE HEIGHT OF THE FUEL ROD ---- CM
      READ (5,10) NORD,NFE,NEZ,NPR,HEIGHT
      WRITE (6,25) NORD,NFE,NEZ,NPR,HEIGHT
C     INPUT THE RADIAL NODAL DISTANCES
      READ (5,30)(DR(I), I = 1,NPR)
      WRITE (6,35) (DR(I),I=1,NPR)
      CALL GINNY (ITYPE,NELCON,NSTART,R,Z)
      CALL CFCOMP (IBP,JA,JB,NAME,NELCON,NSTART)
      CALL INIT (IBP,NELCON,R,Z,Y)
      CALL SHAPE
      DO 45 I = 1,JC
      BIGH2(I) = 0.0
      BIGH3(I) = 0.0
      BIGH5(I) = 0.0
      BIGK(I) =0.0
   45 CONTINUE
      DO 50 I = 1,NP
      BIGF(I) = 0.0
C
C     STORE YIT -- THE INITIAL TEMPERATURE DISTRIBUTION
C
      YIT(I) = Y(1,I+NP)
```

```
   50 CONTINUE
      CALL MATK1 (NELCON)
      DO 100 MM= 1,NEL
      CALL JACOB (MM,NELCON,R,Z)
      CALL MATH12 (MM,NELCON,R,Z)
      CALL SYSH12 (MM,BIGH12,BIGH3,BIGH5,BIGF,JA,JB,NAME,NELCON)
      IF(NELCON(11,MM).EQ. 0) GO TO 100
      CALL SYSK12 (MM,JA,JB,NAME,NELCON,R,Z,BIGK)
  100 CONTINUE
C *** INPUT FUEL PHYSICAL CONSTANTS
      READ(5,15) DOF,B,E,BETA,BETAI,DOLAMI,FFLUXO,ANU,VEL,SIGAF,SIGFF,
     1   SIGAB,SIGFB,RHOA,RHOB,DENF
      AKINF = ANU*SIGFF/SIGAF
C *** INPUT CLAD PHYSICAL CONSTANTS
      READ(5,15) DOC,CPC,DENC,TKC,SIGAC
C *** INPUT COOLANT PHYSICAL CONSTANTS
      READ(5,15) DOCO,SIGACC,VCO,HSURF
      WRITE (6,40)
      WRITE(6,41) DOF,B,E,BETA,BETAI,DOLAMI,ANU,AKINF
      WRITE (6,42)
      WRITE(6,41) FFLUXO,VEL,SIGAF,SIGFF,SIGAB,SIGFB,SIGAC,SIGACC
      WRITE (6,43)
      WRITE(6,41) DOC,CPC,DENC,TKC,DOCC,VCO,HSURF,DENF
      WRITE(6,44) RHOA, RHOB
      JSKF = 0
      NY = NP*2
      NL = 0
      M = NY
      EPS = 0.01
      READ(5,15) T,TEND,H,HMIN,HMAX
  200 CALL SDESOL (Y,YL,T,TEND,NY,NL,M,JSKF,6,1,H,HMIN,HMAX,EPS,W,
     1 BIGH12,BIGH3,BIGH5,BIGK,BIGF,IBP,ITYPE,JA,JB,NAME,NELCON,R,Z,YIT,
     2  BIGH4)
      WRITE(6,11) JSKF
      STOP
      END
```

```
      SUBROUTINE GINNY (ITYPE,NELCON,NSTART,R,Z)
C
C     SUBROUTINE GINNY DEVELOPES THE SYSTEM MESH
C     IT ALLOWS FOR ONE OR TWO RADIAL ELEMENTS IN THE FUEL
C     AND ONE ELEMENT IN THE CLAD AND COOLANT
C    NFE SETS THE NUMBER OF RADIAL FUEL ELEMENTS
C     THE GENERATOR ALLOWS FOR ANY NUMBER OF AXIAL ELEMENTS DESIRED
C     NUMBER OF AXIAL ELEMENTS SET BY NEZ
C     THE  GENERATOR WILL GIVE THE R AND Z DIMENSION FOR EACH NODE
C     IT ALSO DEVELOPES THE CONNECTIVE MATRIX
C
C     ITYPE -- AN ARRAY USED TO INDICATE THE TYPE OF NODE
C              0 -- FUEL NODE NOT IN AN INTERFACE ELEMENT
C              1 -- FUEL NODE IN AN INTERFACE ELEMENT
C              2 -- CLADDING NODE
C              3 -- COOLANT NODE
C     NELCON -- THE CONNECTIVE MATRIX
C     R -- RADIAL DIMENSION OF THE ITH NODE
C    Z -- AXIAL DIMENSION OF THE ITH NODE
C
      IMPLICIT INTEGER*2(I-N)
      DIMENSION DR(13)
      DIMENSION ITYPE(1)
      DIMENSION NELCON(11,1)
      DIMENSION NSTART(1)
      DIMENSION R(1), Z(1)
      COMMON/COAN/ NP,NEL,JC
      COMMON/INP/DR,HEIGHT,NPR,NEZ,NFE
      LL = 0
      NF = 0
      KK = 1
      M = 2*NFE + 1
      MM = M + 4
      MMM = M + 2
      NEL = NFE + 2
      NPZ = NEZ*2
      NACC =  3*NFE + 14
      EZ = NEZ
      Z1 = HEIGHT/(2.0*EZ)
      DO 100 I = 1,NPZ
      T = I
      IF (KK .EQ. 1) GO TO 80
      LL = LL + 1
      NSTART(LL) = NP + 1
   60 DO  70 J = 1,NPR
      NP = NP + 1
      Z(NP) = Z1*T
      R(NP) = DR(J)
```

```
      KK = 1
   70 CONTINUE
      GO TO 100
   80 DO 90 JJ = 1,NPR,2
      IF (JJ .EQ. MMM) GO TO 90
      NP = NP + 1
      Z(NP) = Z1*T
      R(NP) = DR(JJ)
      IF ((JJ .EQ. M) .OR. (JJ .EQ. MM)) GO TO85
      GO TO 90
   85 NP = NP + 1
      Z(NP) = Z1*T
      R(NP) = DR(JJ)
      KK = 0
   90 CONTINUE
  100 CONTINUE
      DO 125 J = 1,NPR
      NP = NP + 1
      Z(NP) = 0.0
      R(NP) = DR(J)
  125 CONTINUE
      NNEZ = NEZ - 1
      IF(NNEZ .EQ.0) GO TO 151
      DO 150 LL = 1,NNEZ
      NST = NSTART(LL)
      NOUT = NST + M + 1
      NCHA = NOUT - 2
      NEND = NST + NPR - 3
      NCOUNT = 0
      DO 150 NN = NST,NEND,2
      IF (NN .EQ. NCHA) GO TO 150
      NNN = NN
      NEL = NEL + 1
      NCOUNT = NCOUNT + 1
      IF (NN .EQ. NOUT) NNN = NN - 1
      NELCON (1,NEL) = NNN + NADD
      NELCON (2,NEL) = NELCON (1,NEL) - 1
      NELCON (3,NEL) = NELCON (2,NEL) - 1
      NELCON (4,NEL) = NNN + NPR + 1 - NCOUNT
      NELCON (5,NEL) = NNN
      NELCON (6,NEL) = NNN + 1
      NELCON (7,NEL) = NNN + 2
      NELCON (8,NEL) = NELCON(4,NEL) + 1
  150 CONTINUE
  151 NST = NSTART(1)
      NEND = NST + NPR - 3
      NOUT = NST + M + 1
      NCHA = NOUT - 2
```

```
      N = 0
      DO 153 I = NST,NEND,2
      II = 0
      IF(I .EQ. NOUT) II=1
      IF (I .EQ. NCPA) GO TO 153
      N = N +1
      NELCON(1,N) = I + 2- II
      NELCON(2,N) = I + 1- II
      NELCON(3,N) = I - II
      NELCON(4,N) = I - NFE - 4 - N - II
      IF (I .EQ. NEND) II=2
      NELCON(5,N) = NP - NPR + 2*N - 1 + II
      NELCON (6,N) = NELCON(5,N) + 1
      NELCON (7,N) = NELCON(5,N) + 2
      NELCON (8,N) = NELCON(4,N) + 1
  153 CONTINUE
      M = NFE + 2
      DO 155 I = 1,NFE
      IF(I .EQ. NFE) GO TO 156
      DO 155 J = I,NEL,M
      NELCON(11,J) = 0
  155 CONTINUE
      GO TO 159
  156 DO 158 J = I,NEL,M
      NELCON(11,J) = 1
      NELCON(11,J+1) = 2
      NELCON(11,J+2) = 3
  158 CONTINUE
  159 CONTINUE
      DO 180 J = 1,NEL
      JJ = NELCON(11,J)
      DO 180 I = 1,6
      II = NELCON(I,J)
      ITYPE(II) = JJ
  180 CONTINUE
      WRITE (6,15)
      DO 160 I = 1,NP,3
      I1 = I + 1
      IF(I1 .GT. NP) GO TO 161
      I2 = I + 2
      IF(I2 .GT. NP) GO TO 162
  160 WRITE (6,20) I,R(I),Z(I),I1,R(I1),Z(I1),I2,R(I2),Z(I2)
      GO TO 165
  161 WRITE(6,20) I,R(I), Z(I)
      GO TO 165
  162 WRITE(6,20) I,R(I), Z(I),I1, R(I1), Z(I1)
  165 WRITE (6,25)
      DO 170 J = 1,NEL
```

```
170 WRITE (6,30)  (J, (NELCON(I,J), I = 1,8))
 15 FORMAT (10X,'NODAL COORDINATES',//,10X,'NODE',4X,'R VALUE',6X,'Z V
   1ALUE',10X,'NODE',4X,'R VALUE',6X,'Z VALUE',10X,'NODE',4X,'R VALUE'
   2,6X,'Z VALUE',//)
 20 FORMAT (10X,I4,2(3X,F10.4),9X,I4,2(3X,F10.4),9X,I4,2(3X,F10.4))
 25 FORMAT (10X,'CONNECTIVITY MATRIX',//,10X,'ELEM',3X,'NOD1',3X,'NOD2
   1',3X,'NOD3',3X,'NOD4',3X,'NOD5',3X,'NOD6',3X,'NOD7',3X,'NOD8',//)
 30 FORMAT (7X, 9(3X,I4))
    RETURN
    END
```

```
      SUBROUTINE OPCOMP (IBP,JA,JB,MAME,NAME,NELCON,NSTART)
C
C     SUBROUTINE OPCOMP CALCULATES THE NAME ARRAY,
C     THE JA ARRAY, AND THE JB ARRAY WHICH
C     ARE USED IN THE OPTIMUM COMPACTING SCHEME
C
C    IBP -- AN ARRAY USED TO STORE THE FUEL-CLAD INTERFACE NODES
C    JA -- AN ARRAY WHICH INDICATES THE NUMBER OF NODES CONTRIBUTING
C          TO THE ITH NODE
C    JB -- THE POINTER ARRAY WHICH INDICATES WHERE THE ITH
C          EQUATION BEGINS IN NAME
C     MAME -- TWO-DIMENSIONAL ARRAY USED TO DEVELOP NAME
C    NAME -- THE ARRAY USED FOR THE OPTIMUM COMPACTING SCHEME
C     NELCON -- CONNECTIVE MATRIX
C     NSTART -- AN ARRAY USED TO STORE CENTERLINE NODAL POINTS
C
      IMPLICIT INTEGER*2(I-N)
      DIMENSION DR(13)
      DIMENSION IBP(1)
      DIMENSION JA(1), JB(1), NAME(1), MAME(26,1)
      DIMENSION NELCON(11,1)
      DIMENSION NSTART(1)
      COMMON/BOUND/ NODUMT
      COMMON/CONN/ NP,NEL,JC
      COMMON/INP/DR,HEIGHT,NPR,NEZ,NFE
      NELDOF = 8
      WRITE (6,10) NP,NEL,NELDOF
   10 FORMAT(/2X,'NUMNP=',I5,5X,'NUMEL=',I5,5X,'NELDOF=',I5)
      DO 40 I = 1,NP
      JA(I)=1
   40 CONTINUE
      DO 60 I = 1,NP
      DO 50J = 1,26
      MAME(J,I)=0
   50 CONTINUE
   60 CONTINUE
      DO 65 I=1,NP
      MAME(1,I)=I
   65 CONTINUE
C
      DO 100 I = 1,NEL
      DO 50 J=1,NELDOF
      JJ = NELCON(J,I)
      DO 80 K=1,NELDOF
      IF(K.EQ.J) GO TO 80
      KK = NELCON(K,I)
      JA(JJ)=JA(JJ)+1
      JAA=JA(JJ)
```

```
      DC 7C L=2,JAA
      JJL=MAME(L,JJ)
      IF(JJL.EQ.KK) JA(JJ)=JA(JJ)-1
      IF(JJL.EQ.KK) GO TO 80
      IF(JJL.EQ.0) MAME(JAA,JJ)=KK
   7C CCNTINUE
   EC CCNTINUE
   SO CCNTINUE
  1GC CCNTINUE
C
C *** TC  ACCCUNT FOR THE INTERFACE CONDITIONS
C ***
      NCCUNT = 3
      IEP(1) = NF - 6
      IBP(2) = NFE + 1
      NN = NFE + 7
      NUM = 2*NFE
      WRITE (6,1000) (NSTART(I),I=1,NEZ)
 1000 FCRMAT (10X,11I5)
      DC 300 I = 1,NEZ
      IEP(NCOUNT) = NSTART(I) + NUM
      IF (I .EQ. NEZ) GC TO 300
      IEP(NCOUNT + 1) = IEP(NCOUNT) + NN
      NCCUNT = NCOUNT + 2
  3CC CCNTINUE
      WRITE (6,1000) (IBP(I),I=1,NCCUNT)
      KK = 1
      DC 4CO I = 1,NCOUNT
      JJ = IBP(I)
      IF (KK .EC. 0) GO TO 350
      IF (I .EQ. NCCUNT) GO TO 350
      IF (I .EQ. 1) GO TO 350
      DC 325 J = 1,13
      MAME (J+13,JJ) = MAME (J,JJ+1)
      MAME (J+13,JJ+1) = MAME (J,JJ)
      MAME (J+13,JJ+3) = MAME (J,JJ+4)
      MAME (J+13,JJ+4) = MAME (J,JJ+3)
  325 CCNTINUE
      JA(JJ) = JA(JJ) + 13
      JA (JJ+1) = JA(JJ+1) + 13
      JA (JJ+3) = JA(JJ+3) + 13
      JA (JJ+4) = JA(JJ+4) + 13
      KK = 0
      GC TO 400
  35C KK = 1
      DC 375 J = 1,8
      MAME (J+8,JJ ) = MAME (J,JJ+1)
      MAME (J+8,JJ+1 ) = MAME (J,JJ)
```

```
      IF ((I .EQ.1) .OR. (I .EQ. NEZ1)) JJ = JJ + 1
      NAME (J+8,JJ+2) = NAME (J,JJ+3)
      NAME (J+8,JJ+3) = NAME (J,JJ+2)
      IF ((I .EQ.1) .OR. (I .EQ. NEZ1)) JJ = JJ - 1
  375 CONTINUE
      JA (JJ) = JA (JJ) + 8
      JA (JJ+1) = JA (JJ+1) + 8
      IF ((I .EQ.1) .OR. (I .EQ. NEZ1)) JJ = JJ + 1
      JA (JJ+2) = JA (JJ+2) + 8
      JA (JJ+3) = JA (JJ+3) + 8
      IF (I .EQ.1) KK = C
  400 CONTINUE
C ***
C ***
      JE(1)=1
      JC=C
      DO200 I = 1,NP
      JB=JA(I)
      JE(I+1)=JB(I)+JA(I)
      JC=JC+JA(I)
  200 CONTINUE
C     WRITE(7,5) (JA(I),I=1,NP)
C     WRITE(7,5) (JB(I),I=1,NP),JC
    5 FORMAT(16I5)
  205 FORMAT (25I4)
      WRITE(6,215) JC
  215 FORMAT(/2X,'JC=',I10)
      DO250 I = 1,NP
      JAA=JA(I)
      JBL=JB(I)
      DO 240 J=1,JAA
      JJ=JBL+J-1
      NAME(JJ)=NAME(J,I)
  240 CONTINUE
  250 CONTINUE
C     WRITE(7,5) (NAME(I),I=1,JC)
      RETURN
      END
```

```
      SUBROUTINE INIT (IBP,NELCON,R,Z,Y)
C
C**   INITIAL SETS THE STARTING VALUES
C**   FOR THE TEMPERATURE AND THE NEUTRON FLUX
C
      IMPLICIT INTEGER*2(I-N)
      DIMENSION CR(13)
      DIMENSION IBP(1)
      DIMENSION NELCON(11,1)
      DIMENSION R(1), Z(1)
      DIMENSION Y(7,1)
      COMMON/BOUND/ NCOUNT
      COMMON/CONN/ NP,NEL,JC
      COMMON/INP/DR,HEIGHT,NPR,NEZ,NFE
      K = 0
      DO 100 N = 1,NCOUNT
      IB = IBP(N)
      IF(K .EQ. 1) GO TO 50
      K = 1
      IBF = IB - 2*NFE + NP
      IBCC = IB + 4 + NP
      GO TO 75
   50 IBF = IB - NFE + NP
      IBCC =  IB + 3 + NP
      K = 0
   75 IBC = IB + 1 + NP
C**
C**   INPUT INITIAL TEMPERATURES FOR THE FUEL CENTERLINE, FUEL
C**   SURFACE, CLADDING, AND THE COOLANT
C**   ALONG THE AXIAL DIRECTION
C**
      READ (5,1000) Y(1,IBF), Y(1,IB+NP), Y(1,IBC), Y(1,IBCC)
 1000 FORMAT (4F10.5)
  100 CONTINUE
C**
C**   CALCULATE THE RADIAL TEMPERATURES USING INPUT
C**   TEMPERATURES.  CLAD TEMPERATURES AND THE COOLANT
C**   TEMPERATURES ARE INITIALLY ASSUMED CONSTANT
C**   IN THE RADIAL  DIRECTION.
C**
      DO 600 M = 1,NEL
      IT = NELCON(11,M) + 1
      GO TO (200,300,400,400),IT
  200 DO 250 K = 1,8
      NODE = NELCON(K,M)
      IF (K .GT. 3) GO TO 230
      NODES = NELCON(1,M+1)
      NODEM = NELCON(3,M)
```

```
      A2 = R(NODES)**2
      R2 = R(NODE)**2
      Y(1,NODE+NP) = Y(1,NODEM+NP)*(1.0-R2/A2) + Y(1,NODES+NP)*R2/A2
      GO TO 250
  230 IF((K .EQ. 4) .OR. (K .EQ. 8)) GO TO 240
      NODES = NELCON(7,M+1)
      NODEM = NELCON(5,M)
      A2 = R(NODES)**2
      R2 = R(NODE)**2
      Y(1,NODE+NP) = Y(1,NODEM+NP)*(1.0-R2/A2) + Y(1,NODES+NP)*R2/A2
      GO TO 250
  240 NODES = NELCON(8,M+1)
      NODEM = NELCON (4,M)
      A2 = R(NODES)**2
      R2 = R(NODE)**2
      Y(1,NODE+NP) = Y(1,NODEM+NP)*(1.0-R2/A2) + Y(1,NODES+NP)*R2/A2
  250 CONTINUE
      GO TO 600
  300 KK = 1
      IF(NFE .EQ. 1) KK = 0
      NODE = NELCON(2,M)
      NODES = NELCON(1,M)
      NODEM = NELCON(3,M-KK)
      A2 = R(NODES)**2
      R2 = R(NODE)**2
      Y(1,NODE+NP) = Y(1,NODEM+NP)*(1.0-R2/A2) + Y(1,NODES+NP)*R2/A2
      NODE = NELCON(6,M)
      NODES = NELCON(7,M)
      NODEM = NELCON(5,M-KK)
      Y(1,NODE+NP) = Y(1,NODEM+NP)*(1.0-R2/A2) + Y(1,NODES+NP)*R2/A2
      GO TO 600
  400 NODE1 = NELCON(1,M) + NP
      NODE2 = NELCON(2,M) + NP
      NODE3 = NELCON(3,M) + NP
      NODE4 = NELCON(4,M) + NP
      NODE5 = NELCON(5,M) + NP
      NODE6 = NELCON(6,M) + NP
      NODE7 = NELCON(7,M) + NP
      NODE8 = NELCON(8,M) + NP
      Y(1,NODE1) = Y(1,NODE3)
      Y(1,NODE2) = Y(1,NODE3)
      Y(1,NODE6) = Y(1,NODE5)
      Y(1,NODE7) = Y(1,NODE5)
      Y(1,NODE8) = Y(1,NODE4)
  600 CONTINUE
C**
C**   INPUT THE MAXIMUM FLUX (I.E. THE FLUX
C**   AT THE AXIAL CENTER)  RADIAL FLUX WILL BE ASSUMED
```

```
C**    TO REMAIN CONSTANT (FLAT FLUX ASSUMPTION)
C**    AXIALLY THE FLUX ASSUMED TO VARY AS THE
C**    SHAPE OF THE SINE FUNCTION
       READ(5,1001) FMAX
 1001  FORMAT (F10.5)
       DO 700 M = 1,NP
       X = Z(M)*3.1415926/HEIGHT
       S = SIN(X)
       Y(1,M)   = FMAX*S
  700  CONTINUE
       WRITE (6,1050)
 1050  FORMAT ('1',9X,'NODAL',5X,'INITIAL',3X,'INITIAL',/,10X,'POINT',5X,
     1   'FLUX',6X,'TEMP',//)
       DO 800 I = 1,NP
       WRITE (6,1100) I, Y(1,I),Y(1,I+NP)
  800  CONTINUE
 1100  FORMAT (9X,I4,E13.3,F10.3)
       RETURN
       END
```

```
      SUBROUTINE SHAPE
C
C     SHAPE EVALUATES THE SHAPE FUNCTION AND
C     ITS DERIVATIVE WITH RESPECT TO XI AND
C     WITH RESPECT TO ETA AT EACH OF THE GAUSS POINTS
C     SUBROUTINE SHAPE ALSO SETS THE WEIGHTS AND LOCATION
C     OF THE GAUSS POINTS DEPENDING UPON THE ORDER
C     OF GAUSSIAN QUADRATURE USED
C
      IMPLICIT INTEGER*2(I-N)
      REAL*8 GP,ETA,SN,DESN,DXSN,XI,ETA1,ETA2,XI1,XI2,ETASQ,XISQ
      REAL*8 XW, WT
      DIMENSION SN(8,25), DESN(8,25), DXSN(8,25), WT(25), GP(5), XW(5)
      COMMON/GP/ GP,NORD
      COMMON/SHAFUN/SN, DESN, DXSN
      COMMON/WEIGHT/ WT
      NO = NORD-2
      N = 0
      GO TO (4,6,8),NO
    4 GP(1) = 0.774596669241483 4
      GP(2) = 0.0
      GP(3) = -GP(1)
      XW(1) = 5.0/9.0
      XW(2) = 8.0/9.0
      XW(3) = XW(1)
      GO TO 10
    6 GP(1) = 0.861136311594053
      GP(2) = 0.339981043584856
      GP(3) = -GP(2)
      GP(4) = -GP(1)
      XW(1) = 0.347854845137454
      XW(2) = 0.652145154862546
      XW(3) = XW(2)
      XW(4) = XW(1)
      GO TO 10
    8 GP(1) = 0.906179845938664
      GP(2) = 0.538469310105683
      GP(3) = 0.0
      GP(4) = -GP(2)
      GP(5) = -GP(1)
      XW(1) = 0.236926885056189
      XW(2) = 0.478628670499366
      XW(3) = 0.568888888888889
      XW(4) = XW(2)
      XW(5) = XW(1)
   10 DO 13 I = 1,NORD
      DO 13 J = 1,NORD
      N = N + 1
```

```
12 WT(N) = XW(I)*XW(J)
   N = 0
   DO 15 I = 1,NORD
   ETA = GP(I)
   DO 15 J = 1,NORD
   XI = GP(J)
   N = N + 1
   ETA1 = 1.0 + ETA
   ETA2 = 1.0 - ETA
   XI1 = 1.0 + XI
   XI2 = 1.0 - XI
   ETASQ = ETA*ETA
   XISQ = XI*XI
   SN(1,N) = 0.25*ETA1*XI1*(XI+ETA-1.0)
   DESN(1,N) = 0.25*XI1*(2.0*ETA+XI)
   DXSN(1,N) = 0.25*ETA1*(2.0*XI+ETA)
   SN(2,N) = 0.5*(1.0-XISQ)*ETA1
   DESN(2,N) = SN(2,N)/ETA1
   DXSN(2,N) = -XI*ETA1
   SN(3,N) = 0.25*XI2*ETA1*(-XI+ETA-1.0)
   DESN(3,N) = 0.25*XI2*(2.0*ETA-XI)
   DXSN(3,N) = 0.25*ETA1*(2.0*XI-ETA)
   SN(4,N) = 0.5*XI2*(1.0-ETASQ)
   DESN(4,N) = -ETA*XI2
   DXSN(4,N) = -SN(4,N)/XI2
   SN(5,N)= -0.25*XI2*ETA2*(XI+ETA+1.0)
   DESN(5,N) = 0.25*XI2*(2.0*ETA+XI)
   DXSN(5,N) = 0.25*ETA2*(2.0*XI+ETA)
   SN(6,N) = 0.5*(1.0-XISQ)*ETA2
   DESN(6,N) = -SN(6,N)/ETA2
   DXSN(6,N) = -XI*ETA2
   SN(7,N) = 0.25*XI1*ETA2*(XI-ETA-1.0)
   DESN(7,N) = 0.25*XI1*(2.0*ETA-XI)
   DXSN(7,N) = 0.25*ETA2*(2.0*XI-ETA)
   SN(8,N) = 0.5*XI1*(1.0-ETASQ)
   DESN(8,N) = -ETA*XI1
15 DXSN(8,N) = SN(8,N)/XI1
   RETURN
   END
```

```
      SUBROUTINE MATK1 (NELCON)
C
C     SUBROUTINE MATK1 CALCULATES THE8X8 ELEMENT K1
C     AND K2 MATRICES FOR THE ELEMENTSBEARDERING
C     ONE OF THE TWO INTERFACES
C
      IMPLICIT INTEGER*2(I-N)
      REAL*8 WT,GP,ETA,XSN,X,Z,XW,Y
      DIMENSION GP(5), XSN(5,5), WT(25)
      DIMENSION NELCON(11,1)
      DIMENSION XK1(8,8), XK2(8,8)
      COMMON/COMM/ NP,NEL,JC
      COMMON/GP/ GP,NORD
      COMMON/K1MAT/XK1,XK2
      COMMON /WEIGHT/ WT
      XW = WT(1)**0.5
      DO 15 I = 1,8
      DO 15 J = 1,8
      XK1(I,J) = 0.0
      XK2(I,J) = 0.0
   15 CONTINUE
      DO 30 K = 1,NORD
      ETA = GP(K)
      XSN(1,K) = 0.5*(ETA+1.0)*ETA
      XSN(2,K) =  0.5*(ETA-1.0)*ETA
      XSN(3,K) = 1.0 - ETA*ETA
   30 CONTINUE
      DO 100 I = 1,3
      DO 80 J = I,3
      Z = 0.0
      DO 60 K = 1,NORD
      X = XSN(I,K)
      Y = XSN(J,K)
      Z = Z + X*Y*WT(K)/XW
   60 CONTINUE
      XK1(I,J) = Z
   80 CONTINUE
  100 CONTINUE
      XK1 (1,7) = XK1 (1,2)
      XK1 (1,8) = XK1 (1,3)
      XK1 (7,7) = XK1 (2,2)
      XK1 (7,8) = XK1 (2,3)
      XK1 (8,8) = XK1 (3,3)
  120 XK2(3,3) = XK1(1,1)
      XK2(3,4) = XK1(1,3)
      XK2(3,5) = XK1(1,2)
      XK2(4,4) = XK1(3,3)
      XK2(4,5) = XK1(2,3)
```

```
      XK2(5,5) = XK1(2,2)
140   DO 160 I = 1,3
      DO 160 J = 2,3
      XK1(I,J) = 0.0
160   CONTINUE
      DO 180 I = 1,8
      DO 180 J = 1,8
      XK1(J,I) = XK1(I,J)
      XK2(J,I) = XK2(I,J)
180   CONTINUE
      RETURN
      END
```

```
      SUBROUTINE JACOB  (M,NELCON,R,Z)
C
C
C     JACOB EVALUATES THE JACOBIAN MATRIX,
C     ITS INVERSE, AND ITS DETERMINATE
C     FOR EACH OF THE GAUSS POINTS
C
C     M IS NUMBER OF THE ELEMENT UNDER CONSIDERATION
C
      IMPLICIT INTEGER*2(I-N)
      REAL*8 DR,DZ,DETJ,XJ11,XJ22,STJ11,STJ22
      REAL*8 GP
      DIMENSION GP(5)
      DIMENSION NELCON(11,1)
      DIMENSION R(1), Z(1)
      DIMENSION STJ11(25), STJ22(25)
      COMMON/GP/ GP,NORD
      COMMON/JACINV/ STJ11,STJ22,DETJ
      COMMON/COMM/ NP,NEL,JC
C     CALCULATE THE DETERMINATE OF THE JACOBIAN
      L = NELCON(1,M)
      K = NELCON(3,M)
      DR = R(L) -R(K)
      L = NELCON(5,M)
      DZ = Z(K) - Z(L)
      DETJ = 0.25*DR*DZ
      XJ11 = 2.0/DR
      XJ22 = 2.0/DZ
      NO = NORD*NORD
      DO 100 I = 1,NO
C     CALCULATE THE INVERSE OF THE JACOBIAN MATRIX
      STJ11(I) = XJ11
  100 STJ22(I) = XJ22
      RETURN
      END
```

```
      SUBROUTINE MATH12  (M,NELCON,R,Z)
C
C     SUBROUTINE MATH12 CALCULATES THE 8X8 ELEMENTT H12,
C     H3 AND H5 MATRICES AND CALCULATES THE 8X1 VECTOR F
C     H5 IS STORED IN THE H4 ARRAY TO SAVE CORE STORAGE
C
      IMPLICIT INTEGER*2(I-N)
      REAL*8 SN,DESN,DXSN,STJ11,STJ22,DETJ,WT,ZX,ZY,ZZ,ZZZ,X,Y,XX,YY,RR
      REAL*8 XXX,YYY,FF,RD,GP
      DIMENSION GP(5)
      DIMENSION H12(8,8),H3(8,8), F(8)
      DIMENSION H4(8,8)
      DIMENSION NELCON(11,1)
      DIMENSION R(1), Z(1)
      DIMENSION SN(8,25), DESN(8,25), DXSN(8,25), WT(25)
      DIMENSION STJ11(25), STJ22(25)
      COMMON/CONN/ NP,NEL,JC
      COMMON/GP/ GP,NORD
      COMMON/JACINV/ STJ11,STJ22,DETJ
      COMMON /MATRIX/ H12, H3, F
      COMMON/MTRXH4/ H4
      COMMON/SHAFUN/SN, DESN, DXSN
      COMMON /WEIGHT/ WT
      NO = NORD*NORD
      LE = NELCON(11,M)
      DO 100 I = 1,8
      FF = 0.0
      DO 80 J = 1,8
      ZX= 0.0
      ZY = 0.0
      ZZ = 0.0
      ZZZ = 0.0
      DO 60 K = 1,NO
      X = DXSN(I,K)*STJ11(K)
      Y = DXSN(J,K)*STJ11(K)
      XX= DESN(I,K)*STJ22(K)
      YY= DESN(J,K)*STJ22(K)
      XXX = SN(I,K)
      YYY = SN(J,K)
      RR = 0.0
      DO 40 L = 1,8
      LL = NELCON(L,M)
      RD = R(LL)
      RR = RR + SN(L,K)*RD
   40 CONTINUE
      ZX= ZX+ X*Y*RR*WT(K)
      ZY = ZY + XXX*YY*RR*WT(K)
      ZZ = ZZ + XX*YY*RR*WT(K)
```

```
      ZZZ = ZZZ + XXX*YYY*RR*WT(K)
      IF(J .NE. I) GO TO 60
      IF((LE .EQ. 2) .OR. (LE .EQ. 3)) GO TO 60
      FF = FF + XXX*RR*WT(K)
   60 CONTINUE
      F12(I,J) = (ZX + ZZ)*DETJ
      F3(I,J) = ZZZ*DETJ
      F4(I,J) = ZY*DETJ
      F(I) = FF*DETJ
   80 CONTINUE
  100 CONTINUE
      RETURN
      END
```

```
      SUBROUTINE MATH4 (N,NELCON,R,Z,YIT,Y)
C
C     SUBROUTINE MATH4 CALCULATES THE 8X8, TEMPERATURE
C     DEPENDENT ELEMENT H4 MATRIX
C
      IMPLICIT INTEGER*2(I-N)
      REAL*8 SN,DESN,DXSN,WT,XXX,YYY,RR,HH,TEMP,TAUO
      REAL*8XX,YY,TT,RD,GP
      DIMENSION H4(8,8)
      DIMENSION NELCON(11,1)
      DIMENSION R(1),Z(1)
      DIMENSION SN(8,25), DESN(8,25), DXSN(8,25), WT(25), GP(5)
      DIMENSION Y(7,1)
      DIMENSION YIT(1)
      COMMON/COMM/ NP,NEL,JC
      COMMON/GP/ GP,NORD
      COMMON/MTRXH4/ H4
      COMMON/SHAPFUN/SN, DESN, DXSN
      COMMON /WEIGHT/ WT
      N = NORD*NORD
      I = NELCON(1,M)
      J = NELCON(3,M)
      K = NELCON(5,M)
      DETJ = 0.25*(R(I)-R(J))*(Z(J)-Z(K))
      DO 100 I = 1,8
      DO 80 J = 1,8
      HH = 0.0
      DO 60 K = 1,N
      XXX = SN(I,K)
      YYY = SN(J,K)
      RR = 0.0
      TEMP = 0.0
      TAUO = 0.0
      DO 40 L = 1,8
      LL = NELCON(L,M)
      RD = R(LL)
      XX= Y(1,LL+NP)
      YY = YIT(LL)
      RR = RR + SN(L,K)*RD
      TEMP = TEMP + SN(L,K)*XX
      TAUO = TAUO + SN(L,K)*YY
   40 CONTINUE
      IF (TEMP .LE. 1.) TEMP = 1.0
      IF(TAUO .LE. 1.)TAUO=1.0
      TAU1 = TEMP/TAUO
      IF (TAU1 .GE. 0.) GO TO 50
      WRITE(6,999) I,J,M,TEMP,TAUO,RR
  999 FORMAT(5X,3I10,5X,3G18.4)
```

```
      DO 45 II = 1,8
      LL = NELCON(II,M)
      WRITE(6,888)  SN(II,K),Y(1,LS+NP),YIT(LL)
888   FORMAT(5X,3G18.4,//)
 45   CONTINUE
 50   TAUNL = ALOG(TAU1)
      TT = TAUNL
      HH = HH + XXX*YYY*RR*WT(K)*TT
 60   CONTINUE
      H4(I,J) = HH*DETJ
 80   CONTINUE
100   CONTINUE
      RETURN
      END
```

```
      SUBROUTINE SYSH12 (N,BIGH12,BIGH3,BIGH5,BIGF,JA,JB,NAME,NELCON)
C
C     SUBROUTINE SYSH12 DEVELOPES THE SYSTEM MATRICES
C     BIGH12, BIGH3, BIGH5, AND BIGF  FROM THE ELEMENT
C     H12, H3, H4,AND F MATRICES ,RESPECTIVELY
C
C     BIGH12 -- SYSTEM MATRIX FOR THE LAPLACIAN TERM
C               D NI/DR X D NJ/DR + D NI/DZ X D NJ/DZ
C     BIGH3 -- SYSTEM MATRIX FOR THE NI X NJ TERM
C     BIGH5 -- SYSTEM MATRIX FOR THE NI X D NJ/DZ TERM
C     BIGF -- SYSTEM VECTOR FOR THE INITIAL DELAYED NEUTRON EFFECT
      IMPLICIT INTEGER*2(I-N)
      DIMENSION BIGH12(1), BIGH3(1), BIGH5(1)
      DIMENSION BIGF(1)
      DIMENSION H12(8,8),H3(8,8), F(8)
      DIMENSION H4(8,8)
      DIMENSION JA(1), JB(1), NAME(1)
      DIMENSION NELCON(11,1)
      COMMON/CONN/ NP,NEL,JC
      COMMON /MATRIX/ H12, H3, F
      COMMON/MTRXH4/ H4
      DO 120 K = 1,8
      KK = NELCON(K,M)
      KKK = JA(KK)
      LLL = JB(KK) - 1
      DO 100 I = 1,8
      II = NELCON(I,M)
      DO 60 L = 1,KKK
      LL = LLL + L
      KKM = NAME(LL)
      IF (II .EQ. KKM) GO TO 80
   60 CONTINUE
   80 BIGH12(LL) = BIGH12(LL) + H12(K,I)
      BIGH3(LL) = BIGH3(LL) + H3(K,I)
      BIGH5(LL) = BIGH5(LL) + H4(K,I)
  100 CONTINUE
      BIGF(KK) = BIGF(KK) + F(K)
  120 CONTINUE
      RETURN
      END
```

```
      SUBROUTINE SYSH4 (M,JA,JB,NAME,NELCON,BIGH4)
C     SYSH4 DEVELOPES THE SYSTEM H4 MATRIX
C     FROM THE  ELEMENT H4 MATRICES
C
C     BIGH4 --- SYSTEM MATRIX FOR  THE TEMPERATURE DEPENDENT MATRIX
C               NATURAL LOG(T/TO) X NI X NJ
      IMPLICIT INTEGER*2(I-N)
      DIMENSION BIGH4(1)
      DIMENSION H4(8,8)
      DIMENSION JA(1), JB(1), NAME(1)
      DIMENSION NELCON(11,1)
      COMMON/CONN/ NP,NEL,JC
      COMMON/MTRXH4/ H4
   50 DO 120 K = 1,8
      KK = NELCON(K,M)
      KKK = JA(KK)
      LLL = JB(KK) - 1
      DO 100 I = 1,8
      II = NELCON(I,M)
      DO 60 L = 1,KKK
      LL = LLL + L
      KKM = NAME(LL)
      IF (II .EQ. KKM) GO TO 80
   60 CONTINUE
   80 BIGH4(LL) = BIGH4(LL) + H4(K,I)
  100 CONTINUE
  120 CONTINUE
      RETURN
      END
```

```
      SUBROUTINE SYSK12  (M,JA,JB,NAME,NELCON,R,Z,BIGK)
C
C     SYSK DEVELOPES THE SYSTEM K MATRIX
C     FROM THE ELEMENT MATRICES
C
C     BIGK -- SYSTEM MATRIX FOR THE THERMAL INTERFACE CONDITIONS
C
      IMPLICIT INTEGER*2(I-N)
      DIMENSION BIGK(1)
      DIMENSION JA(1), JB(1), NAME(1)
      DIMENSION NDUM(3)
      DIMENSION NELCON(11,1)
      DIMENSION R(1), Z(1)
      DIMENSION XK1(8,8), XK2(8,8)
      COMMON/CONN/ NP,NEL,JC
      COMMON/K1MAT/XK1,XK2
      NDUM(1) = 1
      NDUM(2) = 7
      NDUM(3) = 8
      MM = NELCON(11,M)
      GO TO (1,1,2),MM
    1 DO 120 K = 1,3
      N = NDUM(K)
      KK = NELCON(N,M)
      KKK = JA(KK)/2
      LLL = JB(KK) - 1
      DO 100 I = 1,3
      NN = NDUM(I)
      II = NELCON(NN,M)
      JJ = II + 1
      N1 = 0
      N2 = 0
      DO 80 L = 1,KKK
      LL = LLL+ L
      LS = LL + KKK
      KKM = NAME(LL)
      KKS = NAME(LS)
      IF(II .NE. KKM) GO TO 60
      BIGK(LL) = BIGK(LL) + XK1(N,NN)
      N1 = 1
   60 IF(JJ .NE. KKS) GO TO 70
      BIGK(LS) = BIGK(LS) - XK1(N,NN)
      N2 = 1
   70 IF((N1 .EQ. 1) .AND. (N2 .EQ. 1)) GO TO 100
   80 CONTINUE
  100 CONTINUE
  120 CONTINUE
      IF (MM .EQ. 1) GO TO 4
```

```
    2 JE = NELCCN(3,M)
      CC 220 K = 3,5
      KK = NELCCN(K,M)
      KKK = JA(KK)/2
      LLL = JB(KK) - 1
      CC 200 I = 3,5
      II = NELCCN(I,M)
      J. = II - 1
      N1 = 0
      N2 = 0
      CC 180 L = 1,KKK
      LL = LLL + L
      LS = LL + KKK
      KKM = NAME(LL)
      KKS = NAME(LS)
      IF(II .NE. KKM) GC TO 160
      BIGK(LL) = BIGK(LL) + XK2(K,I)
      N1 = 1
  160 IF(JJ .NE. KKS) GG TO 170
      BIGK(LS) = BIGK(LS) - XK2(K,I)
      N2 = 1
  170 IF((N1 .EQ. 1) .AND. (N2 .EC. 1)) GO TO 2C0
  180 CCNTINUE
  200 CCNTINUE
  220 CCNTINUE
    4 RETURN
      END
```

```
      SUBROUTINE DIFFUN(Y,YL,T,HINV,DY,BIGH12,BIGH3,BIGH4,BIGH5,BIGK,
     1 BIGF,IBP,ITYPE,JA,JB,NAME,NELCON,R,Z,YIT)
C
C     SUBROUTINE DIFFUN FORMS THE NODAL EQUATIONS.
C     IT SETS THE ITH EQUATION FOR FLUX EQUAL TO DYI
C     AND FOR TEMPERATURE TO DYII
C
      IMPLICIT INTEGER*2(I-N)
      REAL*8 DYI,DYII
      DIMENSION BIGH12(1), BIGH3(1), BIGH5(1)
      DIMENSION BIGH4(1)
      DIMENSION BIGK(1)
      DIMENSION BIGF(1)
      DIMENSION YIT(1)
      DIMENSION DR(13)
      DIMENSION IBP(1), ITYPE(1)
      DIMENSION JA(1), JB(1), NAME(1)
      DIMENSION NELCON(11,1)
      DIMENSION R(1),Z(1)
      DIMENSION Y(7,1), DY(1)
      COMMON/BCUND/ NCOUNT
      COMMON/CLAD/ DCC,CPC,DENC,TKC,SIGAC,HGAP
      COMMON/CONN/ NP,NEL,JC
      COMMON/COOL/DCCO,SIGACC,VCO,FSURF
      COMMON/FUEL/DCF,B,E,BETA,BETAI,DCLAMI,FFLUXC,AKINF,VEL,
     1   SIGAF1,SIGFF1,SIGAB,SIGFB,DENF
      COMMON/INP/DR,HEIGHT,NPR,NEZ,NFE
      COMMON/TIME/ F,G,RHO
      DATA TOLD/-1.0/
C***  CALCULATE THE TIME DEPENDENT TERMS
      IF (T .EQ. TOLD) GO TO 75
      CALL FUNC (T,HINV)
C***  CALCULATE THE SYSTEM H4 MATRIX
C***  WHICH IS TEMPERATURE DEPENDENT
      DO 30 I = 1,JC
   30 BIGH4(I) = 0.0
      DO 50 I = 1,NEL
      IF (NELCON(11,I) .GT. 1) GO TO 50
      CALL MATH4 (I,NELCON,R,Z,YIT,Y)
      CALL SYSH4 (I,JA,JB,NAME,NELCON,BIGH4)
   50 CONTINUE
      TOLD = T
   75 HINV = 1.0/VEL
      Z1=Z(IBP(2))-Z(IBP(1))
      B1 = 1.0 - BETA
      SIGFF = SIGFF1
      SIGAF = SIGAF1
      CONST1 = AKINF*B1 - 1.0
```

```
      CCNST2 = SIGAF*B1*RHC
      TC = 0.98
      HMCD = 1.0/(0.55*HEIGHT)
      DO 510 I = 1,NP
      JAA = JA(I)
      JBB = JB(I)
      JAB = JAA + JBB - 1
      IT = ITYPE(I) + 1
      II = NP + I
      DYI = 0.0
      DYII = 0.0
      GO TO (100,200,300,400),IT
  100 DO 150 J = JBB,JAB
      NN = NAME(J)
      NNN = NN + NP
      DYI = DYI + (DCF*DBLE(BIGH12(J))-((CONST1+F)*SIGAF+CCNST2)*
     1DBLE(BIGH3(J))+B*SIGAF*B1*DBLE(BIGH4(J)))*Y(1,NN)-G*DBLE(BIGF(NN))
     2 + VINV*HINV*DBLE(BIGH3(J))*Y(2,NN)
      TDK = Y(1,NNN) + 273.
      TKF=((1.0-2.5*(1.0-TC))*(45.1/(135.+TDK) + 4.79E-13*TDK**3))*0.239
      CPF =(18.45 + 2.431E-3*TDK - 2.272E5/TDK**2)/270.07
      DYII = DYII + TKF*DBLE(BIGH12(J))*Y(1,NNN) + HINV*DENF*CPF*
     1 DBLE(BIGH3(J))*Y(2,NNN)-E*SIGFF*DELE(BIGH3(J))*Y(1,NN)
  150 CONTINUE
      GO TO 500
C
C     DETERMINE THE TYPE OF NODE BEING CONSIDERED
C     K = 0     NODE NOT ON THE FUEL-CLAD INTERFACE
C     K = 1     NODE ON THE FUEL-CLAD INTERFACE
C
  200 K = 0
      DO 210 IB = 1,NCOUNT
      IF(IBP(IB) .EQ. I) GO TO 215
  210 CONTINUE
      GO TO 220
  215 K = 1
  220 DO 250 J = JBB,JAB
      NN = NAME(J)
      NNN = NN + NP
      DYI = DYI + (DCF*DBLE(BIGH12(J))-((CONST1+F)*SIGAF+CONST2)*
     1DBLE(BIGH3(J))+B*SIGAF*B1*DBLE(BIGH4(J)))*Y(1,NN)-G*DBLE(BIGF(NN))
     2 + VINV*HINV*DBLE(BIGH3(J))*Y(2,NN)
      RA = R(NN)
      TDK = Y(1,NNN) + 273.
      TKF=((1.0-2.5*(1.0-TC))*(45.1/(135.+TDK) + 4.79E-13*TDK**3))*0.239
      CPF =(18.45 + 2.431E-3*TDK - 2.272E5/TDK**2)/270.07
      HGAP =(1000.0 + 247.0*COS(3.14159*(Z(NN)*HMCD-0.81818)))*1.356E-4
      CONST3 = HGAP*ZL
```

```
  24C DYII = DYII + (TKF*DBLE(BIGH12(J))+RA*CONST3*DBLE(BIGK(J)))*
     1 Y(1,NNN) + DENF*CPF*HINV*DBLE(BIGH3(J))*Y(2,NNN)
     2 - E*SIGFF*DBLE(BIGH3(J))*Y(1,NN)
      IF(K .EQ. 0) GO TO 250
      JJ = J + JAA/2
      NP = NAME(JJ)
      DYI = DYI + (DCC*DBLE(BIGH12(JJ)) + SIGAC*DBLE(BIGH3(JJ)))*Y(1,NN)
     1 + VINV*HINV*DBLE(BIGH3(JJ))*Y(2,NP)
  25C CONTINUE
      GO TO 500
C
C     DETERMINE THE TYPE OF NODE BEING CONSIDERED
C     K = 1     NODE NOT ON AN INTERFACE
C     K = 2     NODE ON THE FUEL-CLAD INTERFACE
C     K = 3     NODE ON THE CLAD-COOLANT INTERFACE
C
  300 K = 1
      NCOC = 0
      DO 320 IB = 1,NCCLNT
      LBP = IBP(IB) + 1
      IF(LBP .EQ. 1) GO TO 325
      NBP = LBP + 2
      IF(NOCC .EQ. 0) GO TO 305
      NBP = NBP - 1
      NCOC = 0
      GO TO 310
  305 NCOC = 1
  310 IF(NBP .EQ. 1) GO TO 330
  320 CONTINUE
      GO TO 340
  325 K = 2
      GO TO 340
  330 K = 3
  340 DO 380 J = JBB,JAB
      NP = NAME(J)
      NNN = NN + NP
      IF(K .EQ. 2) GO TO 360
      DYI = DYI + (DCC*DBLE(BIGH12(J))  + SIGAC*DBLE(BIGH3(J))) *Y(1,NN)
     1 + VINV*HINV*DBLE(BIGH3(J)) *Y(2,NN)
  360 HGAP =(1000.0 + 247.0*COS(3.14159*(Z(NN)*HPCO-0.81818)))*1.356E-4
      H = HGAP
      IF(K .EQ. 3)H =  HSURF
      RA = R(NN)
      DYII = DYII + (TKC*DBLE(BIGH12(J)) + RA*H*ZI*DBLE(BIGK(J)))*
     1Y(1,NNN) +  DENC*CPC*DBLE(BIGH3(J))*HINV*Y(2,NNN)
      IF(K .NE. 3) GO TO 380
      JJ = J + JAA/2
      NP = NAME(JJ)
```

```
      DYI = DYI + (DCCO*DBLE(BIGH12(JJ)) + SIGACO*DBLE(BIGH3(JJ)))*
     1Y(1,NN) +  VINV*HINV*DBLE(BIGH3(JJ))*Y(2,NN)
  380 CONTINUE
      IF(K .NE. 2) GO TO 500
      DYI = Y(1,I) - Y(1,I-1)
      GO TO 500
C
C     DETERMINE THE TYPE OF NODE BEING CONSIDERED
C     K = 1     NODE NOT ON CLAD-COOLANT INTERFACE
C     K = 2     NODE ON THE CLAD-COOLANT INTERFACE
  400 K = 1
      NODD = 0
      DO 420 IB = 1,NOGUNT
      LEP = IBP(IB) + 4
      IF(NODD .EQ. 0) GO TO 410
      LEP = LBP - 1
      NODD = 0
      GO TO 415
  410 NODD = 1
  415 IF(LBP .EQ. I) GO TO 425
  420 CONTINUE
      GO TO 430
  425 K = 2
  430 DO 480 J = JBB,JAB
      NN = NAME(J)
      NNN = NN + NP
      IF(K .EQ. 2) GO TO 450
      DYI = DYI + (DCCO*DBLE(BIGH12(J)) + SIGACO*DBLE(BIGH3(J)))*
     1Y(1,NN) +  VINV*HINV*DBLE(BIGH3(J)) *Y(2,NN)
  450 RE = R(NN)
      TDF = 1.8*Y(1,NNN) + 32.0
      TKCO = (54.306 - 1.878E-2*TDF + 2.0914E-6*TDF**2)*4.184E-3
      DENCO = (59.566 - 7.9504E-3*TDF - 0.2872E-6*TDF**2 +
     1    0.06039E-9*TDF**3)*0.01601
      CPCO = 0.34574 -0.79226E-4*TDF + 0.34086E-7*TDF**2
      DYII = DYII + (TKCO*DBLE(BIGH12(J)) + RB*HSURF*ZI*DBLE(BIGK(J)) +
     1 VCO*DENCO*CPCO*DBLE(BIGH5(J)))*Y(1,NNN) + DENCO*CPCO*
     2DBLE(BIGH3(J))*HINV*Y(2,NNN)
  480 CONTINUE
      IF(K .NE. 2) GO TO 500
      DYI = Y(1,I) - Y(1,I-1)
  500 DY(I) = DYI
      DY(II) = DYII
  510 CONTINUE
C**
C**
C     TO ACCOUNT FOR THE BOUNDARY CONDITIONS
C**
```

```
C**
      NPP = NP + 1
      NN = NPR*2
      NN = NPP - NN
      DO 600 I = NN,NP
      DY(I) = 0.0
  600 CONTINUE
C**
C**
C     TO ACCOUNT FOR THE TEMP BOUNDARY CONDITIONS
C     (CONSTANT COOLANT INLET TEMPERATURES)
C**
C**
      NN = NP - 2
      DO 700 I = NN,NP
      DY(I+NP) = 0.0
  700 CONTINUE
      RETURN
      END
```

```
      SUBROUTINE FUNC(T,HINV)
C
C***  CALCULATES TIME DEPENDENT FUNCTIONS
C***  FOR THIS ANALYSIS DELAYED NEUTRON GROUPS
C***  TAKEN TO BE ONE AVERAGED GROUP
C
      COMMON/FUEL/DCF,B,E,BETA,BETAI,DCLAMI,FFLUXO,AKINF,VEL,
     1   SIGAF,SIGFF,SIGAB,SIGFB,DENF
      COMMON/REACT/ RHOA,RHOB
      COMMON/TIME/ F,G,RHO
      DATA ECLD/1.0/, TOLD/0.0/, FI/0.0/
C***  CALCULATE REACTIVITY INPUT
      RHO = RHOA + RHOB*T
      RHOLD = RHOA + RHOB*TOLD
C**   CALCULATE THE G FUNCTION
      C11 = BETAI*AKINF*SIGAF*FFLUXO/DCLAMI
      X = DCLAMI*T
      EX= EXP(X)
      EE = EXP(-X)
      G = C11*DCLAMI*EE
C***  CALCULATE THE F FUNCTION
      C = DCLAMI*BETAI*EE
      CC = AKINF + RHO
      CCOLD = AKINF + RHOLD
      FI = FI + 0.5*(EOLD*CCOLD +EX*CC)/HINV
      F = C*FI
      TOLD = T
      ECLD = EX
      RETURN
      END
```

```
      SUBROUTINE JACMAT (Y,YL,T,HINV,A2,N,NY,EPS,DY,F1,PW,BIGH12,BIGH3,
     1 BIGH4,BIGH5,BIGK,IBP,ITYPE,JA,JB,NAME,NELCON,R,Z)
C
C     SUBROUTINE JACMAT CALCULATES THE JACOBIAN MATRIX.
C     FLUX JACOBIAN STORED IN THE FIRST JC ELEMENTS OF THE
C     PW ARRAY AND THE TEMPERATURE JACOBIAN STORED IN
C     THE SECOND JC ELEMENTS OF THE PW ARRAY
C
      IMPLICIT INTEGER*2(I-N)
      INTEGER*4 N,NY
      DIMENSION BIGH12(1), BIGH3(1), BIGH5(1)
      DIMENSION BIGH4(1)
      DIMENSION BIGK(1)
      DIMENSION DR(13)
      DIMENSION IBP(1), ITYPE(1)
      DIMENSION JA(1), JB(1), NAME(1)
      DIMENSION NELCON(11,1)
      DIMENSION R(1),Z(1)
      DIMENSION Y(7,1), DY(1), PW(1)
      COMMON/BCUND/ NCGUAT
      COMMON/CLAD/ DCC,CPC,DENC,TKC,SIGAC,HGAP
      COMMON/CCAN/ NP,NEL,JC
      COMMON/CCOL/DCCO,SIGACC,VCO,HSURF
      COMMON/FUEL/DCF,B,E,BETA,BETAI,DCLAMI,FFLUX    INF,VEL,
     1   SIGAF1,SIGFF1,SIGAB,SIGFB,DENF
      COMMON/INP/DR,HEIGHT,NPR,NEZ,NFE
      COMMON/TIME/ F,G,RHO
      AH = -A2*HINV
      Z1=Z(IBP(2))-Z(IBP(1))
      VINV = 1.0/VEL
      B1 = 1.0 - BETA
      SIGFF = SIGFF1
      SIGAF = SIGAF1
      CONST1 = AKINF*B1 - 1.0
      CONST2 = SIGAF*B1*RHO
      TC = 0.58
      HMCD = 1.0/(0.55*HEIGHT)
      DO 500 I = 1,NP
      JAA = JA(I)
      JBB = JB(I)
      JAE = JAA + JBB - 1
      JA2 = JAA/2
      JA3 = JA2 + JBB
      IT = ITYPE(I) + 1
      GO TO (100,200,300,400),IT
  100 DO 150 J = JBB,JAE
      NNN = NAME(J) + NP
      PW(J) = DCF*BIGH12(J)-((CONST1+F)*SIGAF+CONST2-AH*VINV)*BIGH3(J)
```

```
     1 + B*SIGAF*B1*BIGH4(J)
      TDK = Y(1,NNN) + 273.
      TKF=((1.0-2.5*(1.0-TD))*(45.1/(135.+TDK) + 4.79E-13*TDK**3))*C.239
      CPF =(18.45 + 2.431E-3*TDK - 2.272E5/TDK**2)/270.07
      PW(J+JC) = TKF*BIGH12(J)+DENF*CPF*AH*BIGH3(J)
  15C CONTINUE
      GO TO 500
C
C     DETERMINE THE TYPE OF NODE BEING CONSIDERED
C     K = 0     NODE NOT ON THE FUEL-CLAD INTERFACE
C     K = 1     NODE ON THE FUEL-CLAD INTERFACE
  2CC K = C
      DO 210 IB = 1,NCOUNT
      IF(IBP(IB) .EQ. I) GO TO 215
  21C CONTINUE
      GO TO 220
  215 K = 1
  22C DO 250 J = JBB,JAB
      PW(J) = DCF*BIGH12(J)-((CONST1+F)*SIGAF+CONST2-AH*VINV)*BIGH3(J)
     1 + B*SIGAF*B1*BIGH4(J)
      NF = NAME(J)
      NNN = NAME(J) + NF
      RA = R(NN)
      HGAP =(1000.0 + 247.0*COS(3.14159*(Z(NN)*HPCD-0.5181818)*1.256E-4
      CONST3 = HGAP*Z1
      TDK = Y(1,NNN) + 273.
      TKF=((1.0-2.5*(1.0-TD))*(45.1/(135.+TDK) + 4.79E-13*TDK**3))*C.239
      CPF =(18.45 + 2.431E-3*TDK - 2.272E5/TDK**2)/270.07
      PW(J+JC) = TKF*BIGH12(J)+DENF*CPF*AH*BIGH3(J)+RA*CONST3*BIGK(J)
      IF(K .EQ. 0) GO TO 250
      IF(J .LT. JA3) GO TO 250
      JJ = JAB + J - JA3 + 1
      PW(J) = DCC*BIGH12(JJ)+ (SIGAC + AH*VINV)*BIGH3(JJ)
      IF(J .NE. JA3) GO TO 25C
      PW(JBB) = PW(JBB) + PW(J)
      PW(J) = 0.C
  25C CONTINUE
      GO TO 5CO
C
C     DETERMINE THE TYPE OF NODE BEING CONSIDERED
C     K = 1     NODE NOT ON AN INTERFACE
C     K = 2     NODE ON THE FUEL-CLAD INTERFACE
C     K = 3     NODE ON THE CLAD-COOLANT INTERFACE
C
  3CC K = 1
      NCOC = 0
      DO 320 IB = 1,NCOUNT
      LEF = IBP(IB) + 1
```

```
      IF(LBP .EQ. I) GO TO 325
      LBP = LBP + 2
      IF (NCCC .EQ. 0) GO TO 305
      LBP = LBP - 1
      NCCC = 0
      GO TO 310
  305 NCCC = 1
  310 IF(LBP .EQ. I) GO TO 330
  320 CONTINUE
      GO TO 340
  325 K = 2
      GO TO 340
  330 K = 3
  340 DO 380 J = JBB,JAB
      NN = NAME(J)
      NNN = NAME(J) + NP
      RA = R(NN)
      PW(J) = 0.0
      IF(K .EQ.2) GO TO 360
      PW(J) = DCC*BIGH12(J) + (SIGAC + AH*VINV)*BIGH3(J)
  360 HGAP =(1000.0 + 247.0*COS(3.14159*(Z(NN)*HMCD-0.81818)))*1.356E-4
      H = HGAP
      IF(K .EQ. 3) H =  HSURF
      PW(J+JC) = TKC*BIGH12(J)+RA*H*Z1*BIGK(J)+AH*DENC*CPC*BIGH3(J)
      IF(K .NE. 3) GO TO 380
      IF(J .LT. JA3) GO TO 380
      JJ = JAB + J - JA3 + 1
      PW(J) = DCCO*BIGH12(JJ) + (SIGACC + AH*VINV)*BIGH3(JJ)
      IF(J .NE. JA3) GO TO 380
      PW(JBB) = PW(JBB) + PW(J)
      PW(J) = 0.0
  380 CONTINUE
      IF(K .NE. 2) GO TO 500
      PW(JBB) = 1.0
      PW(JA3) = -1.0
      GO TO 500
C
C     DETERMINE THE TYPE OF NODE BEING CONSIDERED
C     K = 1     NODE NOT ON CLAD-COOLANT INTERFACE
C     K = 2     NODE ON THE CLAD-COOLANT INTERFACE
C
  400 K = 1
      NCCC = 0
      DO 420 IB = 1,NCOLNT
      LBP = IBP(IB) + 4
      IF(NCCD .EQ. 0) GO TO 410
      LBP = LBP - 1
      NCCC = 0
```

```
      GO TO 415
  410 NCCC = 1
  415 IF(LBP .EQ. 1) GO TO 425
  420 CONTINUE
      GO TO 430
  425 K = 2
  430 DO 480 J = JBB,JAB
      NN = NAME(J)
      NNN = NAME(J) + NP
      PH(J) = 0.0
      IF(K .EQ. 2) GO TO 450
      PH(J) = DCCO*BIGH12(J) + (SIGACC + AH*VINV)*BIGH3(J)
  450 RB = R(NN)
      TDF = 1.8*Y(1,NNN) + 32.0
      TKCO = (54.306 - 1.878E-2*TDF + 2.0914E-6*TDF**2)*4.134E-3
      CPCO = 0.34574 -0.79226E-4*TDF + 0.34086E-7*TDF**2
      DENCO = (59.566 - 7.9504E-3*TDF - 0.2872E-6*TDF**2 +
     1   0.06035E-9*TDF**3)*0.01601
      A = DENCO*CPCO
      PH(J+JC) = TKCO*BIGH12(J) + VCO*A*BIGH5(J) + AH*A*BIGH3(J)
     1 + RB*HSURF*Z1*BIGK(J)
  480 CONTINUE
      IF(K .NE. 2) GO TO 500
      PH(JBB) = 1.0
      PH(JA3) = -1.0
  500 CONTINUE
C**
C**
C     TO ACCOUNT FOR THE FLUX AXIAL BOUNDARY CONDITIONS
C**
C**
      NPP = NP + 1
      NN = NPP*2
      NN = NPP - NN
      DO 600 I = NN,NP
      PH(JB(I)) = 1.0
      JS = JB(I) + 1
      JE = JB(I) + JA(I) - 1
      DO 600 J = JS,JE
      PH(J) = 0.0
  600 CONTINUE
C**
C**
C     TO ACCOUNT FOR THE TEMP BOUNDARY CONDITIONS
C     (CONSTANT COOLANT INLET TEMPERATURES)
C**
C**
      NN = NP - 2
```

```
      DO 700 I = NN,NP
      FK(JB(I)+JC) = 1.0
      JS = JB(I) + 1 + JC
      JE = JB(I) + JA(I) - 1 + JC
      DO 700 J = JS,JE
      FK(J) = 0.0
  700 CONTINUE
      RETURN
      END
```

```
      SUBROUTINE NUITSL (PW,DY,F1,N,NY,EPS,YMAX,NEWPW,KRET,BIGH3,
     1 ITYPE,JA,JB,NAME,NELCON)
C
C     SUBROUTINE NUITSL CALCULATES THE NEWTON-ITERATES
C     USING A 'SOR' TECHNIQUE WITH AN OVER-RELAXATION
C     FACTOR EQUAL TO OMEGA1
C
      IMPLICIT INTEGER*2(I-N)
      INTEGER*4 N,NY,NEWPW,KRET
      REAL*8 PN,TN
      DIMENSION BIGH3(1)
      DIMENSION ITYPE(1)
      DIMENSION JA(1), JB(1), NAME(1)
      DIMENSION NELCON(11,1)
      DIMENSION PW(1), DY(1), F1(1), YMAX(1)
      COMMON/CONN/ NP,NEL,JC
      COMMON/FUEL/CCF,B,E,BETA,BETA1,CCLAMI,FFLUXC,AKINF,VEL,
     1   SIGAF,SIGFF,SIGAB,SIGFB,DENF
      DATA OMEG,OMEGM1/1.02,0.02/
      TEST = 1.E35
      KRET = 0
      EPSS = EPS**2
      EPSA2 = EPSS*0.0001
      NCIT = N
      E1 = E*SIGFF
      DO 100 I = 1,NP
      F1(I) = DY(I)/PW(JB(I))
  100 F1(I+NP) = DY(I+NP)/PW(JB(I)+JC)
      DO 300 ITT = 1,NGIT
      RCH = 0.
      CH = 0.
      RCH1 = 0.
      RCH2 = 0.
      CH1 = 0.
      CH2 = 0.
      DO 200 I = 1,NP
      JS = JB(I) + 1
      JE = JB(I+1) - 1
      IT = ITYPE(I)
      PN = DY(I)
      TN = DY(I+NP)
      DO 150 J = JS,JE
      PN = PN - DBLE(PW(J))*F1(NAME(J))
      TN = TN - DBLE(PW(J+JC))*F1(NAME(J)+NP)
      IF(IT .GT. 1) GO TO 150
      TN = TN + E1*DBLE(BIGH3(J))*F1(NAME(J))
  150 CONTINUE
      PN = PN/PW(JS-1)
```

```
      TN = TN/PW(JS+JC-1)
      PN = PN*OMEG - F1(I)*OMEGM1
      TN = TN*OMEG - F1(I+NP)*OMEGM1
      PCH = F1(I) - PN
      TCH = F1(I+NP) - TN
      IF((ABS(PCH).GT.TEST).OR.(ABS(TCH).GT.TEST))GO TO 180
      CH1 = CH1 + (PCH/YMAX(I))**2
      CH2 = CH2 + (TCH/YMAX(I+NP))**2
      RCH1 = RCH1 + (PCH/AMAX1(ABS(SNGL(PN)),EPS))**2
      RCH2 = RCH2 + (TCH/AMAX1(ABS(SNGL(TN)),EPS))**2
      GO TO 190
  180 CH1 = 1.
      CH2 = 1.
      RCH1 = 1.
      RCH2 = 1.
  190 F1(I) = PN
  200 F1(I+NP) = TN
      CH = CH1 + CH2
      RCH = RCH1 + RCH2
      IF(RCH .LT. EPSS) RETURN
      IF(CH .LT. EPSA2) RETURN
  300 CONTINUE
      KRET = 1
      RETURN
      END
```

```
      SUBROUTINE LDASUB (Y,YL,T,TEND,N,NY,M,JSTART,KFLAG,MAXOR,IPRT,H,   LDA    10
     1 HMIN,HMAX,RMSEPS,SAVE,YLSV,YMAX,ER,ESV,F1,DY,PW,BIGH12,BIGH3,
     2 BIGH4,BIGH5,BIGK,BIGF,IBP,ITYPE,JA,JB,NAME,NELCON,RR,Z,VIT)
C                                                                       LDA    30
C     SUBROUTINE LDASUB IS A MODIFICATION OF SUBROUTINE DFASUB          LDA    40
C     WHICH IS DUE TO R. L. BROWN AND C. W. GEAR.  DFASUB IS DOCUMENTED LDA    50
C     IN THE REPORT                                                     LDA    60
C        DOCUMENTATION FOR DFASUB--                                     LDA    70
C        BY R. L. BROWN AND C. W. GEAR                                  LDA    80
C        REPORT UIUCDCS-R-73-575, JULY 1973                             LDA    90
C        UNIVERSITY OF ILLINOIS AT URBANA-CHAMPAIGN                     LDA   100
C        URBANA, ILLINOIS  61801                                        LDA   110
C     THIS REPORT IS AVAILABLE FROM THE NATIONAL TECHNICAL INFORMATION  LDA   120
C     SERVICE OF THE U. S. DEPARTMENT OF COMMERCE UNDER ACCESSION NUMBERLDA   130
C     COD-1469-225.                                                     LDA   140
C                                                                       LDA   150
C     THE MODIFICATION HERE IS DOCUMENTED IN THE REPORT                 LDA   160
C        A PROGRAM FOR THE NUMERICAL SOLUTION OF LARGE SPARSE SYSTEMS OFLDA   170
C        ALGEBRAIC AND IMPLICITLY DEFINED STIFF DIFFERENTIAL EQUATIONS  LDA   180
C        BY RICHARD FRANKE                                              LDA   190
C        REPORT NPS53FE76051, MAY 1976                                  LDA   200
C        NAVAL POSTGRADUATE SCHOOL                                      LDA   210
C        MONTEREY, CALIFORNIA  93940                                    LDA   220
C                                                                       LDA   230
C     ------------------------------------------------------------------LDA   240
C                                                                       LDA   250
C     THE CALLING SEQUENCE FOR LDASUB IS                                LDA   260
C                                                                       LDA   270
C     CALL LDASUB(Y,YL,T,TEND,N,NY,M,JSTART,KFLAG,MAXOR,IPRT,H,HMIN,    LDA   280
C     HMAX,RMSEPS,SAVE,YLSV,YMAX,ER,ESV,F1,DY,PW)                       LDA   290
C                                                                       LDA   300
C     WHERE THE PARAMETERS ARE DEFINED AS FOLLOWS.                      LDA   310
C        Y          - ARRAY DIMENSIONED (7,NY).  THIS ARRAY CONTAINS THE LDA   320
C                     DEPENDENT VARIABLES AND THEIR SCALED DERIVATIVES. LDA   330
C                     Y(J+1,I) CONTAINS THE J-TH DERIVATIVE OF THE I-TH VARLDA   340
C                     IABLE TIMES H**J/J-FACTORIAL, WHERE H IS THE CURRENT LDA   350
C                     STEPSIZE.  ON FIRST ENTRY THE CALLER SUPPLIES THE LDA   360
C                     INITIAL VALUES OF EACH VARIABLE IN Y(1,I) AND AN  LDA   370
C                     ESTIMATE OF THE INITIAL VALUES OF THE DERIVATIVES LDA   380
C                     IN Y(2,I).  ON SUBSEQUENT ENTRIES IT IS ASSUMED THAT LDA   390
C                     THE ARRAY HAS NOT BEEN CHANGED.  TO INTERPOLATE TO LDA   400
C                     NON-MESH POINTS, THESE VALUES CAN BE USED AS FOLLOWS.LDA   410
C                     IF H IS THE CURRENT STEPSIZE AND VALUES AT TIME T+E LDA   420
C                     NEEDED, LET S = E/H  AND THEN                     LDA   430
C                                                                       LDA   440
C                                                 NC                    LDA   450
C                          I-TH VARIABLE AT  T+E IS  SUM Y(J+1,I)*S**J  LDA   460
C                                                 J=0                   LDA   470
```

```
C                THE VALUE OF NQ IS OBTAINED IN THE CALLING PROGRAM
C                BY  NC = JSTART.
C
C     YL       - ARRAY OF NL = N - NY VARIABLES WHICH APPEAR LINEARLY.
C                THE USER SUPPLIES INITIAL VALUES FOR THESE VARIABLES.
C     T        - CURRENT VALUE OF THE INDEPENDENT VARIABLE (TIME)
C     TEND     - END TIME
C     N        - TOTAL NUMBER OF VARIABLES
C     NY       - NUMBER OF DIFFERENTIAL EQUATIONS AND NONLINEAR
C                VARIABLES.
C     M        - NUMBER OF VARIABLES INCLUDED IN THE ERROR TEST.
C                THIS NUMBER CAN BE NO GREATER THAN NY.  IF IT IS
C                GREATER THAN NY, NY VARIABLES ARE USED IN THE ERROR
C                TEST.
C     JSTART   - INPUT AND OUTPUT INDICATOR.
C                ON INPUT JSTART HAS THE FOLLOWING MEANINGS.
C                     <0   THIS INDICATES A RE-START FROM A PREVIOUS
C                          POINT FOLLOWING TERMINATION OF THE RUN OR
C                          SOLUTION OF ANOTHER PROBLEM DURING THE SAME
C                          RUN.  PARAMETERS IN THE CALLING SEQUENCE
C                          MUST HAVE BEEN PRESERVED FROM THE PREVIOUS
C                          USE, PARTICULARLY THE ARRAYS
C                              SAVE, YLSV, ESV, AND PW.
C                          THESE ARRAYS MUST BE SAVED AFTER A CALL
C                          TO SUBROUTINE LDASAV, WHICH ALSO SAVES
C                          NECESSARY PARAMETERS INTERNAL TO LDASUB.
C                     =0   INDICATES AN INITIAL CALL TO LDASUB.  THE
C                          ROUTINE INITIALIZES ITSELF, SCALES THE
C                          DERIVATIVES IN Y(2,I) AND THEN PERFORMS THE
C                          INTEGRATION UNTIL T > TEND.
C                     >0   INDICATES THE SOLUTION IS TO BE CONTINUED.
C                          AFTER THE INITIAL ENTRY IT IS NEITHER
C                          DESIRABLE NOR NECESSARY TO RE-ENTER WITH
C                          JSTART = 0, SINCE THIS RE-INITIALIZES
C                          THE CODE, BEGINNING WITH A FIRST ORDER
C                          METHOD AGAIN.
C                ON OUTPUT, JSTART IS SET TO THE VALUE OF NQ, THE
C                ORDER OF THE FORMULA CURRENTLY BEING USED.
C     KFLAG    - THE COMPLETION CODE INDICATOR, WITH THE FOLLOWING
C                MEANINGS
C                     +1   THE INTEGRATION WAS SUCCESSFUL
C                     -1   ERROR TEST FAILURE FOR H > HMIN
C                     -3   CORRECTOR FAILED TO CONVERGE FOR H > HMIN
C                     -4   CORRECTOR FAILED TO CONVERGE FOR FIRST
C                          ORDER METHOD
C                     -5   ERROR RETURN FROM SUBROUTINE NLITSL
C     MAXOR    - MAXIMUM ORDER DERIVATIVE THAT SHOULD BE USED IN THE
```

```
C                 METHOD.  IT MUST BE NO GREATER THAN SIX.  IF IT IS   LDA   960
C                 GREATER THAN SIX, THE MAXIMUM ORDER USED WILL BE SIX.LDA   970
C      IPRT     - INTERNAL PRINT CONTROL INDICATOR                     LDA   980
C                     = 0  NO PRINT                                    LDA   990
C                     > 0  PRINT COUNTERS, STEPSIZE, CURRENT TIME      LDA  1000
C                          AND VALUES OF DEPENDENT VARIABLES AT        LDA  1010
C                          EACH STEP.                                  LDA  1020
C      H        - CURRENT STEPSIZE.  AN INITIAL VALUE MUST BE SUPPLIED LDA  1030
C                 BUT NEED NOT BE THE ONE WHICH WILL BE USED, SINCE THELDA  1040
C                 SUBROUTINE WILL CHOOSE A SMALLER ONE IF NECESSARY TOLDA  1050
C                 KEEP THE ERROR PER STEP SMALLER THAN THE SPECIFIED   LDA  1060
C                 VALUE.  IT IS BETTER TO UNDERESTIMATE THE INITIAL    LDA  1070
C                 STEPSIZE THAN TO OVERESTIMATE IT.  THE STEPSIZE IS   LDA  1080
C                 NORMALLY NOT CHANGED BY THE USER.                    LDA  1090
C      HMIN     - MINIMUM STEPSIZE ALLOWED                             LDA  1100
C      HMAX     - MAXIMUM STEPSIZE ALLOWED                             LDA  1110
C      RMSEPS   - THE ERROR TEST CONSTANT.  THE ROOT-MEAN-SQUARE OF    LDA  1120
C                 THE SINGLE STEP ERROR ESTIMATES,  ER(I), DIVIDED BY  LDA  1130
C                 YMAX(I) = (MAXIMUM TO CURRENT TIME OF Y(I)) MUST BE  LDA  1140
C                 LESS THAN RMSEPS.  THE STEPSIZE AND/OR ORDER ARE     LDA  1150
C                 VARIED TO ACHIEVE THIS.                              LDA  1160
C      SAVE     - AN ARRAY OF LENGTH AT LEAST 7*NY                     LDA  1170
C      YLSV     - AN ARRAY OF LENGTH AT LEAST NL                       LDA  1180
C      YMAX     - A VECTOR OF LENGTH NY WHICH CONTAINS THE MAXIMUM     LDA  1190
C                 OF EACH Y SEEN SO FAR.  ON THE FIRST CALL, THESE WILLLDA  1200
C                 BE INITIALIZED AS YMAX(I) = MAX(1,|Y(1,I)|)          LDA  1210
C      ER       - A VECTOR OF LENGTH NY                                LDA  1220
C      ESV      - A VECTOR OF LENGTH NY                                LDA  1230
C      F1       - A VECTOR OF LENGTH N = NY + NL                       LDA  1240
C      GY       - A VECTOR OF LENGTH N = NY + NL                       LDA  1250
C      PW       - AN ARRAY IN WHICH THE  J  MATRIX COMPUTED            LDA  1260
C                 IN SUBROUTINE JACMAT WILL BE STORED.  SIZE WHICH     LDA  1270
C                 MUST BE ALLOWED IS DETERMINED BY THE STORAGE TECH-   LDA  1280
C                 NIQUE USED FOR IT, BUT NORMALLY WON'T BE MORE THAN   LDA  1290
C                 N**2 + 2*N LOCATIONS, THE LATTER 2*N BEING REQUIRED  LDA  1300
C                 BY THE LINEAR EQUATION SOLVER.                       LDA  1310
C                                                                      LDA  1320
C-----------------------------------------------------------------------LDA  1330
      INTEGER*2 IBP,ITYPE,JA,JB,NAME,NELCON
      DIMENSION BIGH12(1), BIGH3(1), BIGH5(1)
      DIMENSION BIGH4(1)
      DIMENSION BIGK(1)
      DIMENSION BIGF(1)
      DIMENSION IBP(1), ITYPE(1)
      DIMENSION JA(1), JB(1), NAME(1)
      DIMENSION NELCON(11,1)
      DIMENSION RR(1),Z(1)
      DIMENSION VIT(1)
```

```
      DIMENSION Y(7,1), YL(1), SAVE(7,1), YMAX(1), ER(1), YLSV(1), F1(1)LDA 1340
     1, PERT(6,3), COF(21), ESV(1), DY(1), PW(1), SAV(1), A(29)         LDA 1350
      EQUIVALENCE (A(8),END), (A(9),BR), (A(10),E), (A(11),EDWN),       LDA 1360
     1(A(12),ENQ1), (A(13),ENQ2), (A(14),ENC3), (A(15),EFS), (A(16),EUP)LDA 1370
     2,(A(17),HNEW), (A(18),PEPSH), (A(19),IDCUB), (A(20),IHEVAL),      LDA 1380
     3(A(21),K), (A(22),LCOPYL), (A(23),LCOPYY), (A(24),MAXCER),        LDA 1390
     4(A(25),M1), (A(26),NL), (A(27),NC), (A(28),NS), (A(29),NW)        LDA 1400
C                                                                       LDA 1410
C     ------------------------------------------------------------------LDA 1420
C                                                                       LDA 1430
C     THE COEFFICIENTS IN THE PERT ARRAY ARE USED FOR ERROR TESTING AND LDA 1440
C     CHANGING STEPSIZE AND NEED TO BE ACCURATE TO ONLY A FEW DIGITS.   LDA 1450
C                                                                       LDA 1460
C     ------------------------------------------------------------------LDA 1470
      DATA PERT/4.,9.,16.,25.,36.,49.,9.,16.,25.,36.,49.,64.,1.,1.,.25, LDA 1480
     12.7889E-2,1.70569E-3,6.83929E-5/                                  LDA 1490
C     ------------------------------------------------------------------LDA 1500
C                                                                       LDA 1510
C     THE ENTRIES IN THE COF ARRAY ARE THE COEFFICIENTS FOR THE STIFFLY LDA 1520
C     STABLE METHODS USED IN THIS PROGRAM AND ARE TO BE THE MACHINE     LDA 1530
C     PRECISION EQUIVALENTS OF THE FOLLOWING CONSTANTS.                 LDA 1540
C                                                                       LDA 1550
C     -1                                                                LDA 1560
C     -3/2 , -1/2                                                       LDA 1570
C     -11/6 , -1 , -1/6                                                 LDA 1580
C     -25/12 , -35/24 , -5/12 , -1/24                                   LDA 1590
C     -137/60 , -15/8 , -17/24 , -1/8 , -1/120                          LDA 1600
C     -147/60, -203/90 , -49/48 , -35/144 , -7/240 , -1/720             LDA 1610
C                                                                       LDA 1620
C     ------------------------------------------------------------------LDA 1630
      DATA COF/-1.,-1.5,-.5,-1.833333,-1.,-.1666667,-2.083333,-1.458333,LDA 1640
     1-.4166667,-.04166667,-2.283333,-1.875,-.7083333,-.125,-.00833333,LDA 1650
     2-2.45,-2.255556,-1.020833,-.2430556,-.02916667,-.00138889/        LDA 1660
      IF (JSTART) 100,110,150                                           LDA 1670
C     ------------------------------------------------------------------LDA 1680
C     IF THIS IS A RESTART ENTRY, RESTORE Y AND YL FROM THE SAVE AND    LDA 1690
C     YLSV ARRAYS, WHERE THEY WERE SAVED BY A PREVIOUS CALL TO LDASAV.  LDA 1700
C     ------------------------------------------------------------------LDA 1710
  100 CALL COPYZ (Y,SAVE,LCOPYY)                                        LDA 1720
      CALL COPYZ (YL,YLSV,LCOPYL)                                       LDA 1730
      GO TO 150                                                         LDA 1740
C     ------------------------------------------------------------------LDA 1750
C     IF THIS IS THE FIRST CALL, INITIALIZE YMAX, SCALE DERIVATIVES, ANDLDA 1760
C     INITIALIZE INDICATORS AND SET ORDER TO ONE.                       LDA 1770
C     FOR DOUBLE PRECISION, SET LCOPYL = 14*NY AND LCOPYL = 2*NL IF     LDA 1780
C     SUBROUTINE COPYZ IS IN SINGLE PRECISION.                          LDA 1790
C     ------------------------------------------------------------------LDA 1800
  110 NL = N-NY                                                         LDA 1810
```

```
      LCCPYY = 7*NY                                                     LDA 1820
      LCCPYL = NL                                                       LDA 1830
      M1 = MINO(M,NY)                                                   LDA 1840
      EPS = SQRT(FLOAT(M1))*RMSEPS                                      LDA 1850
      MAXCER = MINO(MAXOR,6)                                            LDA 1860
      IF (IPRT.LE.0) GO TO 120                                          LDA 1870
      PRINT 3, N,NL,RMSEPS,TEND,H                                       LDA 1880
      PRINT 4                                                           LDA 1890
  120 NS = 0                                                            LDA 1900
      NW = 0                                                            LDA 1910
C                                                                       LDA 1920
      DO 130 J=1,NY                                                     LDA 1930
      YMAX(J) = AMAX1(1.,ABS(Y(1,J)))                                   LDA 1940
  130 Y(2,J) = Y(2,J)*H                                                 LDA 1950
C                                                                       LDA 1960
      NQ = 1                                                            LDA 1970
      RR = 1.                                                           LDA 1980
      ASSIGN 190 TO IRET                                                LDA 1990
C     ------------------------------------------------------------------LDA 2000
C     SET COEFFICIENTS FOR THE ORDER CURRENTLY BEING USED.              LDA 2010
C     E IS A TEST FOR ERRORS OF THE CURRENT ORDER NQ                    LDA 2020
C     EUP IS TO TEST FOR INCREASING THE ORDER, EDWN FOR DECREASING THE  LDA 2030
C     ORDER.                                                            LDA 2040
C     ------------------------------------------------------------------LDA 2050
  140 K = NQ*(NQ-1)/2                                                   LDA 2060
      CALL COPYZ (A(2),COF(K+1),NQ)                                     LDA 2070
      K = NQ+1                                                          LDA 2080
      IDOUB = NQ                                                        LDA 2090
      ENQ1 = .5/NQ                                                      LDA 2100
      ENQ2 = .5/K                                                       LDA 2110
      ENQ3 = .5/(NQ+2)                                                  LDA 2120
      PEPSH = EPS**2                                                    LDA 2130
      E = PERT(NQ,1)*PEPSH                                              LDA 2140
      ELP = PERT(NQ,2)*PEPSH                                            LDA 2150
      EDWN = PERT(NQ,3)*PEPSH                                           LDA 2160
      BND = (EPS*ENQ3)**2                                               LDA 2170
      IBEVAL = 1                                                        LDA 2180
      GO TO IRET, (190,200,450,570)                                     LDA 2190
  150 IF (H.EQ.HNEW) GO TO 190                                          LDA 2200
C     ------------------------------------------------------------------LDA 2210
C     IF CALLER HAS CHANGED H, RESCALE DERIVATIVES TO REFLECT THAT HNEW LDA 2220
C     WAS USED ON THE LAST CALL.                                        LDA 2230
C     ------------------------------------------------------------------LDA 2240
      R = H/HNEW                                                        LDA 2250
      ASSIGN 190 TO IRET                                                LDA 2260
      GO TO 610                                                         LDA 2270
C     ------------------------------------------------------------------LDA 2280
C     SET JSTART TO NQ, THE CURRENT ORDER OF THE METHOD, BEFORE EXIT,   LDA 2290
```

```
C     AND SAVE THE CURRENT STEPSIZE IN HNEW.                          LDA 2300
C     ---------------------------------------------------------------- LDA 2310
  160 JSTART = NC                                                     LDA 2320
      HNEW = H                                                        LDA 2330
      RETURN                                                          LDA 2340
  170 NS = NS+1                                                       LDA 2350
      IF (IPRT.LE.0) GO TO 180                                        LDA 2360
C     ---------------------------------------------------------------LDA 2370
C     PRINT DATA IF DESIRED BY USER                                   LDA 2380
C     ---------------------------------------------------------------LDA 2390
      PRINT 1, NS,NW,NQ,H,T,(Y(1,I),I=1,NY)                           LDA 2400
  180 CONTINUE                                                        LDA 2420
      IF (KFLAG.LT.0) GO TO 160                                       LDA 2430
      IF (T.GE.TEND) GO TO 160                                        LDA 2440
C     ---------------------------------------------------------------LDA 2450
C     TAKE ANOTHER STEP IF T < TEND                                   LDA 2460
C     ---------------------------------------------------------------LDA 2470
      JSTART = 1                                                      LDA 2480
C     ---------------------------------------------------------------LDA 2490
C     SAVE DATA FOR TRIAL WITH A SMALLER TIMESTEP IF THIS STEP FAILS  LDA 2500
C     ---------------------------------------------------------------LDA 2510
  190 CALL COPYZ (SAVE,Y,LCOPYY)                                      LDA 2520
      CALL COPYZ (YLSV,YL,LCOPYL)                                     LDA 2530
      RACUM = 1.                                                      LDA 2540
      KFLAG = 1                                                       LDA 2550
      HOLD = H                                                        LDA 2560
      NOLD = NQ
      TOLD = T                                                        LDA 2580
  200 T = T+H                                                         LDA 2590
      HINV = 1./H                                                     LDA 2600
C     ---------------------------------------------------------------LDA 2610
C     COMPUTE PREDICTED VALUES BY EFFECTIVELY MULTIPLYING DERIVATIVE  LDA 2620
C     VECTOR BY PASCAL TRIANGLE MATRIX                                LDA 2630
C     ---------------------------------------------------------------LDA 2640
C                                                                     LDA 2650
      DO 210 J=2,K                                                    LDA 2660
      J3 = K+J-1                                                      LDA 2670
C                                                                     LDA 2680
      DO 210 J1=J,K                                                   LDA 2690
      J2 = J3-J1                                                      LDA 2700
C                                                                     LDA 2710
      DO 210 I=1,NY                                                   LDA 2720
  210 Y(J2,I) = Y(J2,I)+Y(J2+1,I)                                     LDA 2730
C                                                                     LDA 2740
C                                                                     LDA 2750
      DO 220 I=1,NY                                                   LDA 2760
  220 ER(I) = 0.                                                      LDA 2770
C                                                                     LDA 2780
```

```
C     ------------------------------------------------------------------LDA 2790
C     DO UP TO THREE CORRECTOR ITERATIONS.  CONVERGENCE IS OBTAINED WHENLDA 2800
C     CHANGES ARE LESS THAN BND WHICH IS DEPENDENT ON THE ERROR TEST    LDA 2810
C     CONSTANT.  THE SUM OF CORRECTIONS IS ACCUMULATED IN ER(I).  IT IS LDA 2820
C     EQUAL TO THE K-TH DERIVATIVE OF Y TIMES H**K/(K-FACTORIAL*A(K)),  LDA 2830
C     AND THUS IS PROPORTIONAL TO THE ACTUAL ERRORS TO THE LOWEST POWER LDA 2840
C     OF H PRESENT, WHICH IS H**K.                                      LDA 2850
C     ------------------------------------------------------------------LDA 2860
C                                                                       LDA 2870
      DO 270 L=1,3                                                      LDA 2880
      CALL DIFFUN (Y,YL,T,HINV,DY,BIGH12,BIGH3,BIGH4,BIGH5,BIGK,BIGF,
     1 IEP,ITYPE,JA,JB,NAME,NELCON,RR,Z,YIT)
      IF (IWEVAL.LT.1) GO TO 230                                        LDA 2900
C     ------------------------------------------------------------------LDA 2910
C     IF THERE HAS BEEN A CHANGE OF ORDER OR THERE HAS BEEN TROUBLE     LDA 2920
C     WITH CONVERGENCE, PW IS RE-EVALUATED PRIOR TO STARTING THE        LDA 2930
C     CORRECTOR ITERATION.  IWEVAL IS THEN SET TO -1 AS AN INDICATOR    LDA 2940
C     THAT IT HAS BEEN DONE.  NEWPW IS SET NONZERO TO INDICATE TO       LDA 2950
C     SUBROUTINE NUITSL THAT A NEW PW HAS BEEN PROVIDED.                LDA 2960
C     ------------------------------------------------------------------LDA 2970
      CALL JACMAT (Y,YL,T,HINV,A(2),N,NY,EPS,DY,F1,PW,BIGH12,BIGH3,
     1 BIGH4,BIGH5,BIGK,IBF,ITYPE,JA,JB,NAME,NELCON,RR,Z)
      KFLAG = 1                                                         LDA 2990
      IWEVAL = -1                                                       LDA 3000
      NN = NN+1                                                         LDA 3010
      NEWPW = 1                                                         LDA 3020
  230 CALL NUITSL (PW,DY,F1,N,NY,EPS,YMAX,NEWPW,KFRET,BIGH3,ITYPE,
     1 JA,JB,NAME,NELCON)
      IF (KFRET.NE.0) GO TO 600                                         LDA 3040
      IF (NL.LE.0) GO TO 250                                            LDA 3050
C                                                                       LDA 3060
      DO 240 I=1,NL                                                     LDA 3070
  240 YL(I) = YL(I)-F1(I+NY)                                            LDA 3080
C                                                                       LDA 3090
  250 CONTINUE                                                          LDA 3100
      DEL = 0.                                                          LDA 3110
C                                                                       LDA 3120
      DO 260 I=1,NY                                                     LDA 3130
      Y(1,I) = Y(1,I)-F1(I)                                             LDA 3140
      Y(2,I) = Y(2,I)+A(2)*F1(I)                                        LDA 3150
      ER(I) = ER(I)+F1(I)                                               LDA 3160
      DEL = DEL+(F1(I)/AMAX1(YMAX(I),ABS(Y(1,I))))**2                   LDA 3170
  260 CONTINUE                                                          LDA 3180
C                                                                       LDA 3190
      IF (L.GE.2) BR = AMAX1(.9*BR,DEL/DEL1)                            LDA 3200
      DEL1 = DEL                                                        LDA 3210
      IF (AMIN1(DEL,BR*DEL*2.).LE.BND) GO TO 330                        LDA 3220
  270 CONTINUE                                                          LDA 3230
```

```
C                                                                       LCA 3240
C     ------------------------------------------------------------------LDA 3250
C     THE CORRECTION ITERATION FAILED TO CONVERGE IN 3 TRIES.  VARIOUS  LDA 3260
C     POSSIBILITIES ARE CHECKED FOR.  IF H IS ALREADY HMIN AND PW HAS   LDA 3270
C     ALREADY BEEN RE-EVALUATED, A NO CONVERGENCE EXIT IS TAKEN.        LDA 3280
C     OTHERWISE THE MATRIX PW IS RE-EVALUATED AND/OR (IN THAT ORDER) THELDA 3290
C     STEP IS REDUCED TO TRY AND GET CONVERGENCE.                       LDA 3300
C     ------------------------------------------------------------------LDA 3310
      T = TOLD                                                          LDA 3320
      IF (IWEVAL) 280,300,290                                           LDA 3330
  280 IF (H.LE.HMIN*1.00001) GO TO 310                                  LDA 3340
  290 RACUM = RACUM*.25                                                 LDA 3350
  300 CONTINUE                                                          LDA 3360
      GO TO 560                                                         LDA 3370
  310 KFLAG = -3                                                        LDA 3380
C     ------------------------------------------------------------------LDA 3390
C     RESTORE Y AND YL AFTER CONVERGENCE FAILURE                        LDA 3400
C     ------------------------------------------------------------------LDA 3410
  320 CALL COPYZ (Y,SAVE,LCOPYY)                                        LDA 3420
      CALL COPYZ (YL,YLSV,LCOPYL)                                       LDA 3430
      H = HOLD                                                          LDA 3440
      NQ = NQOLD                                                        LDA 3450
      GO TO 170                                                         LDA 3460
C     ------------------------------------------------------------------LDA 3470
C     THE CORRECTOR CONVERGED, SO NOW THE ERROR TEST IS MADE.           LDA 3480
C     ------------------------------------------------------------------LDA 3490
  330 D = 0.                                                            LDA 3500
C                                                                       LDA 3510
      DO 340 I=1,N1                                                     LDA 3520
      YM = AMAX1(ABS(Y(1,I)),YMAX(I))                                   LDA 3530
  340 D = D+(ER(I)/YM)**2                                               LDA 3540
C                                                                       LDA 3550
      IWEVAL = 0                                                        LDA 3560
      IF (D.GT.E) GO TO 380                                             LDA 3570
C     ------------------------------------------------------------------LDA 3580
C     THE ERROR TEST IS OKAY, SO THE STEP IS ACCEPTED.  IF IDOUB        LDA 3590
C     NOW BECOMES NEGATIVE, A TEST IS MADE TO SEE IF THE STEP SIZE      LDA 3600
C     CAN BE INCREASED AT THIS ORDER OR ONE HIGHER OR ONE LOWER.        LDA 3610
C     THE CHANGE IS MADE ONLY IF THE STEP CAN BE INCREASED BY AT        LDA 3620
C     LEAST 10%.  IDOUB IS SET TO NQ TO PREVENT FURTHER TESTING         LDA 3630
C     FOR A WHILE.  IF NO CHANGE IS MADE, IDOUB IS SET TO 5.            LDA 3640
C     ------------------------------------------------------------------LDA 3650
      IF (K.LT.3) GO TO 360                                             LDA 3660
C                                                                       LDA 3670
      DO 350 J=3,K                                                      LDA 3680
C                                                                       LDA 3690
      DO 350 I=1,NY                                                     LDA 3700
  350 Y(J,I) = Y(J,I)+A(J)*ER(I)                                        LDA 3710
```

```
C                                                                       LDA 3720
  36C KFLAG = 1                                                         LDA 3730
      ICCUB = ICCUB-1                                                   LDA 3740
      IF (ICCUB) 410,37C,510                                            LDA 3750
  37C CALL CCPYZ (ESV,ER,M1)                                            LDA 3760
      GC TO 51C                                                         LDA 3770
C     ------------------------------------------------------------------LDA 3780
C     THE ERRCR TEST FAILED.  IF JSTARTT = 0, THE CERIVATIVES IN THE    LDA 3790
C     SAVE ARRAY ARE UPCATED.  TESTS ARE THEN MACE TC FIX THE STEPSIZE  LDA 3800
C     ANC PERHAPS REDUCE THE ORDER.  AFTER RESTCRING AND SCALING THE    LDA 3810
C     Y VARIAELES, THE STEP IS RETRIED.                                 LDA 3820
C     ------------------------------------------------------------------LDA 3830
  38C IF (JSTART.GT.0) GC TO 400                                        LDA 3840
C                                                                       LDA 3850
      CC 35C I=1,NY                                                     LDA 3860
  35C SAVE(2,I) = Y(2,I)                                                LDA 3870
C                                                                       LDA 3880
  4CC KFLAG = KFLAG-2                                                   LDA 3890
      IF (H.LE.HMIN) GC TO 550                                          LDA 3900
      T = TOLC                                                          LDA 3910
      IF (KFLAG.LE.-5) GC TO 530                                        LDA 3920
  41C FR2 = (C/E)**ENQ2*1.2                                             LDA 3930
      L = 0                                                             LDA 3940
      IF (NQ.LE.1) GO TO 430                                            LDA 3950
      D = 0.                                                            LDA 3960
C                                                                       LDA 3970
      CC 420 J=1,M1                                                     LDA 3980
      YM = AMAX1(ABS(Y(1,J)),YMAX(J))                                   LDA 3990
  42C C = C+(Y(K,J)/YM)**2                                              LDA 4000
C                                                                       LDA 4010
      PR1 = (C/EDWN)**ENC1*1.3                                          LDA 4020
      IF (PR1.GE.PR2) GO TO 430                                         LDA 4030
      PR2 = PR1                                                         LDA 4040
      L = -1                                                            LDA 4050
  43C IF (KFLAG.LT.0.OR.NC.GE.MAXDER) GC TO 45C                         LDA 4060
      C = 0                                                             LDA 4070
C                                                                       LDA 4080
      CC 440 J=1,M1                                                     LDA 4090
      YM = AMAX1(ABS(Y(1,J)),YMAX(J))                                   LDA 4100
  44C C = C+((ER(J)-ESV(J))/YM)**2                                      LDA 4110
C                                                                       LDA 4120
      PR1 = (C/ELP)**ENC3*1.4                                           LDA 4130
      IF (PR1.GE.PR2) GO TO 450                                         LDA 4140
      PR2 = PR1                                                         LDA 4150
      L = 1                                                             LDA 4160
  45C R = 1./AMAX1(PR2,1.E-5)                                           LDA 4170
      IF (KFLAG.LT.0.OR.R.GE.1.1) GO TC 460                             LDA 4180
      ICCUB = 9                                                         LDA 4190
```

```
      GO TO 510                                                         LDA 4200
  460 NEWQ = NQ+1                                                       LDA 4210
      K = NEWQ+1                                                        LDA 4220
      IF (NEWQ.LE.NQ) GO TO 480                                         LDA 4230
      R1 = A(NEWQ)/FLOAT(NEWQ)                                          LDA 4240
C                                                                       LDA 4250
      DO 470 J=1,NY                                                     LDA 4260
  470 Y(K,J) = ER(J)*R1                                                 LDA 4270
C                                                                       LDA 4280
  480 CONTINUE                                                          LDA 4290
C     ------------------------------------------------------------------LDA 4300
C     IF THE STEP WAS OKAY, SCALE THE Y VARIABLES IN ACCORDANCE         LDA 4310
C     WITH THE NEW VALUE OF H.  IF KFLAG < 0, HOWEVER, USE THE          LDA 4320
C     SAVED VALUES (IN SAVE AND YLSV).  IN EITHER CASE, IF THE ORDER    LDA 4330
C     HAS CHANGED IT IS NECESSARY TO FIX CERTAIN PARAMETERS BY CALLING  LDA 4340
C     THE PROGRAM SEGMENT AT STATEMENT NUMBER 140.                      LDA 4350
C     ------------------------------------------------------------------LDA 4360
      IDCUB = NQ                                                        LDA 4370
      IF (NEWQ.EQ.NQ) GO TO 490                                         LDA 4380
      NQ = NEWQ                                                         LDA 4390
      ASSIGN 490 TO IRET                                                LDA 4400
      GO TO 140                                                         LDA 4410
  490 IF (KFLAG.GT.0) GO TO 500                                         LDA 4420
      RACUM = RACUM*R                                                   LDA 4430
      GO TO 560                                                         LDA 4440
  500 R = AMAX1(AMIN1(HMAX/H,R),HMIN/H)                                 LDA 4450
      H = H*R                                                           LDA 4460
      IHEVAL = 1                                                        LDA 4470
      ASSIGN 510 TO IRET                                                LDA 4480
      GO TO 610                                                         LDA 4490
C                                                                       LDA 4500
  510 DO 520 I=1,N1                                                     LDA 4510
  520 YMAX(I) = AMAX1(ABS(Y(1,I)),YMAX(I))                              LDA 4520
C                                                                       LDA 4530
      GO TO 170                                                         LDA 4540
C     ------------------------------------------------------------------LDA 4550
C     THE ERROR TEST HAS NOW FAILED THREE TIMES, SO THE DERIVATIVES ARE LDA 4560
C     IN BAD SHAPE.  RETURN TO FIRST ORDER METHOD AND TRY AGAIN.  OF    LDA 4570
C     COURSE, IF NQ = 1 ALREADY, THEN THERE IS NO HOPE AND WE EXIT WITH LDA 4580
C     KFLAG = -4.                                                       LDA 4590
C     ------------------------------------------------------------------LDA 4600
  530 IF (NQ.EQ.1) GO TO 540                                            LDA 4610
      NQ = 1                                                            LDA 4620
      IDCUB = 1                                                         LDA 4630
      ASSIGN 570 TO IRET                                                LDA 4640
      GO TO 140                                                         LDA 4650
  540 NCCLD = 1                                                         LDA 4660
      KFLAG = -4                                                        LDA 4670
```

```
      GC TO 320                                                         LDA 4680
  55C KFLAG = -1                                                        LDA 4690
      GC TO 17C                                                         LDA 4700
C     ------------------------------------------------------------------LDA 4710
C     THIS SECTION RESTORES THE SAVED VALUES OF Y AND YL, SCALING THE   LDA 4720
C     Y DERIVATIVES AS NECESSARY, AND THEN RETURNS TO THE PREDICTOR LOOPLDA 4730
C     ------------------------------------------------------------------LDA 4740
  56C H = HOLD*RACUM                                                    LDA 4750
      H = AMAX1(HMIN,AMIN1(H,HMAX))                                     LDA 4760
  57C RACUM = H/HOLD                                                    LDA 4770
      R1 = 1.                                                           LDA 4780
      DO 580 J=2,K                                                      LDA 4800
      R1 = R1*RACUM                                                     LDA 4810
C                                                                       LDA 4820
      DO 580 I=1,NY                                                     LDA 4830
  58C Y(J,I) = SAVE(J,I)*R1                                             LDA 4840
C                                                                       LDA 4850
C                                                                       LDA 4860
      DO 590 I=1,NY                                                     LDA 4870
  590 Y(1,I) = SAVE(1,I)                                                LDA 4880
C                                                                       LDA 4890
      CALL COPYZ (YL,YLSV,LOOPYL)                                       LDA 4900
      IHEVAL = 1                                                        LDA 4910
      GO TO 200                                                         LDA 4920
  600 KFLAG = -5                                                        LDA 4930
      GO TO 160                                                         LDA 4940
C     ------------------------------------------------------------------LDA 4950
C     THIS SECTION SCALES THE Y DERIVATIVES BY R**J                     LDA 4960
C     ------------------------------------------------------------------LDA 4970
  61C R1 = 1.                                                           LDA 4980
C                                                                       LDA 4990
      DO 620 J=2,K                                                      LDA 5000
      R1 = R1*R                                                         LDA 5010
C                                                                       LDA 5020
      DO 620 I=1,NY                                                     LDA 5030
  62C Y(J,I) = Y(J,I)*R1                                                LDA 5040
C                                                                       LDA 5050
      GO TO IRET, (190,510)                                             LDA 5060
C     ------------------------------------------------------------------LDA 5070
C     THIS SECTION ALLOWS FOR RESTARTS AFTER SOLVING ANOTHER PROBLEM, ORLDA 5080
C     HAVING TERMINATED THE CURRENT COMPUTER RUN.  SUBROUTINE LDASAV    LDA 5090
C     SAVES THE NECESSARY VALUES WHICH ARE INTERNAL TO LDASUB.  FOR     LDA 5100
C     DOUBLE PRECISION, WITH COPYZ IN SINGLE PRECISION, THE NUMBER OF   LDA 5110
C     LOCATIONS TO BE SAVED AND RESTORED, LOCPYS AND LOCPYR, MUST BE    LDA 5120
C     SET TO 58.                                                        LDA 5130
C     IT IS ASSUMED THAT IN ADDITION TO THE VARIABLES IN THE ARRAY A    LDA 5140
C     SAVED BY CALLING LDASAV, THE USER ALSO SAVES THE ARRAYS SAVE,     LDA 5150
C     YLSV, YMAX, ESV, AND PW.                                          LDA 5160
```

```
C
C     TO RESTART THE USER FIRST CALLS LDARST TO RESTORE THE VALUES SAVED      LDA 5170
C     BY LDASAV, THEN RE-ENTERS LDASUB WITH JSTART < 0, AND WITH THE          LDA 5180
C     OTHER PARAMETERS THE SAME AS RETURNED FROM THE LAST ENTRY TO            LDA 5190
C     LDASUB, PARTICULARLY THOSE ARRAYS MENTIONED ABOVE.                      LDA 5200
C     ------------------------------------------------------------------------LDA 5210
      ENTRY LDASAV(SAV)                                                       LDA 5220
      LCOPYS = 2S                                                             LDA 5230
      CALL COPYZ (SAV,A,LCOPYS)                                               LDA 5240
      CALL COPYZ (SAVE,Y,LCOPYY)                                              LDA 5250
      CALL COPYZ (YLSV,YL,LCOPYL)                                             LDA 5260
      RETURN                                                                  LDA 5270
C                                                                             LDA 5280
      ENTRY LDARST(SAV)                                                       LDA 5290
      LCOPYR = 2S                                                             LDA 5300
      CALL COPYZ (A,SAV,LCOPYR)                                               LDA 5310
      RETURN                                                                  LDA 5320
C                                                                             LDA 5330
C     ------------------------------------------------------------------------LDA 5340
C                                                                             LDA 5350
    1 FORMAT (2I5,I2,1P2E10.2,7E14.6/(32X,7E14.6))                            LDA 5360
    2 FORMAT (32X,1P7E14.6)                                                   LDA 5370
    3 FORMAT ('1   N =',I3,'   [illegible] =',I3,'   RMSEPS =',1PE5.2,'   TEND =' LDA 5380
     1  ,E5.2,'   h =',E5.2//)                                                LDA 5390
    4 FORMAT ('   NS   [illegible]   H',8X,'T    ',8X,'Y(1,*) AND YL(*)'//)  LDA 5400
      END                                                                     LDA 5410
                                                                              LDA 5420
                                                                              LDA 5430
```

```
      SUBROUTINE SDESOL (Y,YL,T,TEND,NY,NL,M,JSKF,MAXDER,IPRT,H,HMIN,    SDE    10
     1 HMAX,RMSEPS,W,BIGH12,BIGH3,BIGH5,BIGK,BIGF,IBP,ITYPE,JA,JB,NAME,
     2 NELCON,R,Z,YIT,BIGH4)
C                                                                       SDE    30
C     ------------------------------------------------------------------SDE    40
C                                                                       SDE    50
C     SUBROUTINE SDESOL IS A DRIVER ROUTINE FOR SUBROUTINE LDASUB.      SDE    60
C     ITS PURPOSE IS TO SET UP THE NECESSARY REFERENCES TO A LARGE      SDE    70
C     BLOCK OF AUXILLARY STORAGE, AND  OBTAIN INITIAL VALUES OF         SDE    80
C     DERIVATIVES.                                                      SDE    90
C     THE CALLING SEQUENCE FOR SDESOL IS                                SDE   100
C                                                                       SDE   110
C CALL SDESOL(Y,YL,T,TEND,NY,NL,M,JSKF,MAXDER,IPRT,H,HMIN,HMAX,RMSEPS,W)SDE   120
C                                                                       SDE   130
C     WHERE THE PARAMETERS ARE DEFINED AS FOLLOWS.                      SDE   140
C                                                                       SDE   150
C        Y        - ARRAY DIMENSIONED (7,NY).  THIS ARRAY CONTAINS THE SDE   160
C                   DEPENDENT VARIABLES AND THEIR SCALED DERIVATIVES.   SDE   170
C                   Y(J+1,I) CONTAINS THE J-TH DERIVATIVE OF THE I-TH VARSDE   180
C                   IABLE TIMES H**J/J-FACTORIAL, WHERE H IS THE CURRENT SDE   190
C                   STEPSIZE.  ON FIRST ENTRY THE CALLER SUPPLIES THE   SDE   200
C                   INITIAL VALUES OF EACH VARIABLE IN Y(1,I).  ON SUB- SDE   210
C                   SEQUENT ENTRIES IT IS ASSUMED THE ARRAY HAS NOT     SDE   220
C                   BEEN CHANGED.  TO INTERPOLATE TO NON-MESH POINTS,   SDE   230
C                   THESE VALUES CAN BE USED AS FOLLOWS.  IF H IS THE   SDE   240
C                   CURRENT STEPSIZE AND VALUES AT TIME  T+E  ARE       SDE   250
C                   NEEDED, LET  S = E/H  AND THEN                      SDE   260
C                                                                       SDE   270
C                                                   JS                  SDE   280
C                        I-TH VARIABLE AT  T+E  IS  SUM Y(J+1,I)*S**J   SDE   290
C                                                  J=0                  SDE   300
C                                                                       SDE   310
C                   THE VALUE OF JS IS OBTAINED IN THE CALLING PROGRAM  SDE   320
C                   BY  JS = IABS(JSKF/10)                              SDE   330
C        YL       - ARRAY OF NL VARIABLES WHICH APPEAR LINEARLY.       SDE   340
C        T        - CURRENT VALUE OF THE INDEPENDENT VARIABLE (TIME)   SDE   350
C        TEND     - END TIME                                           SDE   360
C        NY       - NUMBER OF DIFFERENTIAL EQUATIONS AND NONLINEAR     SDE   370
C                   VARIABLES.                                          SDE   380
C        NL       - NUMBER OF LINEAR VARIABLES                         SDE   390
C        M        - NUMBER OF VARIABLES INCLUDED IN THE ERROR TEST     SDE   400
C        JSKF     - AN INDICATOR USED BOTH ON INPUT AND OUTPUT         SDE   410
C                   ON INPUT, JSKF = -1 INDICATES A RESTART CALL TO     SDE   420
C                   SDESOL.  JSKF = 0 INDICATES AN INITIAL CALL TO      SDE   430
C                   SDESOL.  JSKF > 0 INDICATES A CONTINUATION OF THE   SDE   440
C                   PREVIOUS CALL TO SDESOL.  JSKF < -1 MAY HAVE RESULTEDSDE   450
C                   FROM THE USER NEGLECTING TO TEST FOR ERROR RETURNS  SDE   460
C                   FROM SDESOL.  BECAUSE OF THIS POSSIBILITY, JSKF < -1 SDE   470
```

```
C                 RESULTS IN TERMINATION OF THE RUN WITH THE            SDE  480
C                 APPROPRIATE COMMENT.                                  SDE  490
C                 ON OUTPUT, JSKF CONSISTS OF TWO DIGITS AND SIGN,      SDE  500
C                 + OR - OF.  Q IS THE ORDER OF THE FORMULA CURRENTLY   SDE  510
C                 BEING USED.  P INDICATES THE TYPE OF RETURN, AS       SDE  520
C                 FOLLOWS.                                              SDE  530
C                 JSKF > 0, P = 1 IS THE NORMAL RETURN                  SDE  540
C                 JSKF < 0 IS AN ERROR RETURN, WITH THE FOLLOWING       SDE  550
C                 MEANINGS.                                             SDE  560
C                      P = 1  ERROR TEST FAILURE FOR H > HMIN           SDE  570
C                      P = 3  CORRECTOR FAILED TO CONVERGE FOR H > HMIN SDE  580
C                      P = 4  CORRECTOR FAILED TO CONVERGE FOR FIRST    SDE  590
C                             ORDER METHOD                              SDE  600
C                      P = 5  ERROR RETURN FROM SUBROUTINE NLITSL       SDE  610
C                      P = 6  ERROR RETURN FROM SUBROUTINE DERVAL       SDE  620
C       MAXDER  - MAXIMUM ORDER DERIVATIVE THAT SHOULD BE USED IN       SDE  630
C                 METHOD.  IT MUST BE NO GREATER THAN SIX.              SDE  640
C       IPRT    - INTERNAL PRINT CONTROL INDICATOR FOR LDASUB.          SDE  650
C                      IPRT = 0  NO PRINT                               SDE  660
C                      IPRT > 0  PRINT COUNTERS, STEPSIZE, CURRENT TIME SDE  670
C                                AND VALUES OF DEPENDENT VARIABLES AT   SDE  680
C                                EACH STEP.                             SDE  690
C       H       - CURRENT STEPSIZE.  AN INITIAL VALUE MUST BE SUPPLIED  SDE  700
C                 BUT NEED NOT BE THE ONE WHICH MUST BE USED, SINCE THE SDE  710
C                 SUBROUTINE WILL CHOSE A SMALLER ONE IF NECCESSARY TO  SDE  720
C                 KEEP THE ERROR PER STEP SMALLER THAN THE SPECIFIED    SDE  730
C                 VALUE.  IT IS BETTER TO UNDERESTIMATE THE INITIAL     SDE  740
C                 STEPSIZE THAN TO OVERESTIMATE IT.  THE STEPSIZE IS    SDE  750
C                 NORMALLY NOT CHANGED BY THE USER.                     SDE  760
C       HMIN    - MINIMUM STEPSIZE ALLOWED                              SDE  770
C       HMAX    - MAXIMUM STEPSIZE ALLOWED                              SDE  780
C       RMSEPS  - THE ERROR TEST CONSTANT.  THE ROOT-MEAN-SQUARE OF     SDE  790
C                 THE SINGLE STEP ERROR ESTIMATES,  ER(I), DIVIDED BY   SDE  800
C                 YMAX(I) = (MAXIMUM TO CURRENT TIME OF Y(I) ) MUST BE  SDE  810
C                 LESS THAN EPS.  THE STEPSIZE AND/OR THE ORDER         SDE  820
C                 ARE VARIED TO ACHIEVE THIS.                           SDE  830
C       W       - SCRATCH STORAGE ARRAY.  MUST BE AT LEAST 13*NY + 5*NLSDE  840
C                 LOCATIONS, PLUS THOSE REQUIRED FOR STORAGE OF THE     SDE  850
C                 MATRIX  PW (SEE DESCRIPTION OF SUBROUTINE JACMAT).    SDE  860
C                 THE STORAGE OF PW WILL NORMALLY REQUIRE NO MORE THAN  SDE  870
C                 N**2 + 2*N LOCATIONS, AND IF COMPACT STORAGE TECH-    SDE  880
C                 NIQUES ARE USED, CAN BE MUCH FEWER.                   SDE  890
C                                                                       SDE  900
C-----------------------------------------------------------------------SDE  910
      INTEGER*2 IBP,ITYPE,JA,JB,NAME,NELCON
      DIMENSION Y(7,1), YL(1), W(1)                                     SDE  920
      DIMENSION BIGH2(1), BIGH3(1), BIGH5(1)
      DIMENSION BIGH4(1)
```

```
      DIMENSION BIGK(1)
      DIMENSION BIGF(1)
      DIMENSION IBP(1), ITYPE(1)
      DIMENSION JA(1), JB(1), NAME(1)
      DIMENSION NELCON(11,1)
      DIMENSION R(1), Z(1)
      DIMENSION YIT(1)
      IF (JSKF.GT.0) GO TO 120                                          SDE  930
      IF (JSKF.LT.-1) GO TO 140                                         SDE  940
      N = NY+NL                                                         SDE  950
      IF (JSKF.LT.0) GO TO 110                                          SDE  960
C                                                                       SDE  970
C     IF THIS IS THE FIRST ENTRY, OBTAIN VALUES OF THE DERIVATIVES.     SDE  980
      CALL DERVAL (Y,YL,T,N,NY,W,KRETR,BIGH12,BIGH3,BIGH4,BIGH5,BIGK,
     1 BIGF,IBP,ITYPE,JA,JB,NAME,NELCON,R,Z,YIT)
      IF (KRETR.NE.0) GO TO 130                                         SDE 1000
C                                                                       SDE 1010
C     NOW SET UP STORAGE BLOCKS IN THE W ARRAY.  THIS NEEDS TO BE DONE  SDE 1020
C     ONLY INITIALLY AND ON RESTARTS.                                   SDE 1030
C                                                                       SDE 1040
C        THE ARRAY   SAVE    STARTS AT LOCATION  1      IN THE W ARRAY SDE 1050
C        THE ARRAY   YLSV    STARTS AT LOCATION  NSVL   IN THE W ARRAY SDE 1060
C        THE ARRAY   YMAX    STARTS AT LOCATION  NYMAX  IN THE W ARRAY SDE 1070
C        THE ARRAY   ER      STARTS AT LOCATION  NER    IN THE W ARRAY SDE 1080
C        THE ARRAY   ESV     STARTS AT LOCATION  NESV   IN THE W ARRAY SDE 1090
C        THE ARRAY   F1      STARTS AT LOCATION  NF1    IN THE W ARRAY SDE 1100
C        THE ARRAY   DY      STARTS AT LOCATION  NDY    IN THE W ARRAY SDE 1110
C        THE MATRIX  PW      STARTS AT LOCATION  NPW    IN THE W ARRAY SDE 1120
C                                                                       SDE 1130
  110 NSVL = 7*NY+1                                                     SDE 1140
      NYMAX = NSVL+NL                                                   SDE 1150
      NER = NYMAX+NY                                                    SDE 1160
      NESV = NER+NY                                                     SDE 1170
      NF1 = NESV+NY                                                     SDE 1180
      NDY = NF1+N                                                       SDE 1190
      NPW = NDY+N                                                       SDE 1200
  120 JS = JSKF                                                         SDE 1210
      CALL LOASUB (Y,YL,T,TEND,N,NY,N,JS,KF,MAXDEF,IPRT,H,HMIN,HMAX,    SDE 1220
     1RMSEPS,W(NSVL),W(NYMAX),W(NER),W(NESV),W(NF1),W(NDY),W(NPW),
     2BIGH12,BIGH3,BIGH4,BIGH5,BIGK,BIGF,IBP,ITYPE,JA,JB,NAME,NELCON,
     3R,Z,YIT)
C                                                                       SDE 1240
C     CODE JSKF ON RETURN FROM LOASUB                                   SDE 1250
C                                                                       SDE 1260
      JSKF = ISIGN(JS*10+IABS(KF),KF)                                   SDE 1270
      RETURN                                                            SDE 1280
  130 JSKF = -6                                                         SDE 1290
      RETURN                                                            SDE 1300
```

```
  140 PRINT 1, JSKF                                                     SDE 1310
      STOP                                                              SDE 1320
C                                                                       SDE 1330
C                                                                       SDE 1340
    1 FORMAT ('0IT IS AN ERROR TO ENTER SDESOL WITH JSKF = ',I10//      SDE 1350
     1 '    RUN HAS BEEN TERMINATED.')                                  SDE 1360
      END                                                               SDE 1370
```

```
      SUBROUTINE COPYZ(S,Y,L)                                           COP    10
      DIMENSION S(1),Y(1)                                               COP    20
C     ------------------------------------------------------------------COP    30
C                                                                       COP    40
C     THIS SUBROUTINE COPIES THE ARRAY Y, OF LENGTH L, INTO THE ARRAY S COP    50
C                                                                       COP    60
C     ------------------------------------------------------------------COP    70
      IF(L.LE.0)RETURN                                                  COP    80
      DO 100 J=1,L                                                      COP    90
  100 S(J) = Y(J)                                                       COP   100
      RETURN                                                            COP   110
      END                                                               COP   120
```

```
      SUBROUTINE DERVAL (Y,YL,T,N,NY,W,KERET,BIGH12,BIGH3,BIGH4,BIGH5,
     1 BIGK,BIGF,IBP,ITYPE,JA,JB,NAME,NELCON,R,Z,YIT)
      INTEGER*2 IBP,ITYPE,JA,JB,NAME,NELCON
      DIMENSION BIGH12(1), BIGH3(1), BIGH5(1)
      DIMENSION BIGH4(1)
      DIMENSION BIGK(1)
      DIMENSION BIGF(1)
      DIMENSION IBP(1), ITYPE(1)
      DIMENSION JA(1), JB(1), NAME(1)
      DIMENSION NELCON(11,1)
      DIMENSION R(1),Z(1)
      DIMENSION YIT(1)
C
C     THIS SUBROUTINE CALCULATES THE INITIAL VALUES OF THE DERIVATIVES   DER    20
C     IN THE GENERAL CASE.  IT IS WRITTEN SO THAT IT SHOULD WORK IF THE  DER    30
C     FIRST NY EQUATIONS ALL INVOLVE DERIVATIVES.  IT ATTEMPTS TO SOLVE  DER    40
C     THE FIRST NY EQUATIONS USING NEWTON'S METHOD, BUT SINCE IT TRIES   DER    50
C     TO EVALUATE DF/DY' BY CALLING JACMAT IN SUCH A WAY AS TO MAKE THE  DER    60
C     DF/DY TERM INSIGNIFICANT, IT IS POSSIBLE THAT IT MAY FAIL FOR THAT DER    70
C     REASON.  IT MAY FAIL FOR OTHER REASONS, AS WELL.  IF IT DOES FAIL  DER    80
C     THE USER CAN SUPPLY HIS OWN VERSION OF DERVAL, OR MODIFY THIS      DER    90
C     ROUTINE IN SUITABLE FASHION.  THIS ROUTINE ASSUMES THAT VALUES OF  DER   100
C     THE LINEAR VARIABLES HAVE BEEN SUPPLIED PREVIOUSLY.  IF THOSE      DER   110
C     MUST BE SOLVED FOR SIMULTANEOUSLY WITH THE DERIVATIVES, THE USER   DER   120
C     MUST SUPPLY HIS OWN VERSION OF DERVAL.                             DER   130
C                                                                        DER   140
C     THE CALLING SEQUENCE FOR THIS SUBROUTINE IS                        DER   150
C                                                                        DER   160
C     CALL DERVAL(Y,YL,T,N,NY,W,KERET)                                   DER   170
C                                                                        DER   180
C     WHERE THE PARAMETERS ARE DEFINED AS FOLLOWS                        DER   190
C                                                                        DER   200
C        Y       - SAME AS IN LDASUB AND SDESOL.  Y(1,I) CONTAINS THE    DER   210
C                  INITIAL VALUES OF THE DEPENDENT VARIABLES.   THE      DER   220
C                  VALUES OF THE DERIVATIVES ARE RETURNED IN Y(2,I).     DER   230
C        YL      - SAME AS IN LDASUB AND SDESOL.  THE INITIAL VALUES OF  DER   240
C                  THE LINEAR VARIABLES MUST BE SUPPLIED TO THIS VERSION DER   250
C        T       - INITIAL TIME                                          DER   260
C        N       - SAME AS IN LDASUB, TOTAL NUMBER OF VARIABLES          DER   270
C        NY      - SAME AS IN LDASUB, NUMBER OF DIFFERENTIAL EQUATIONS   DER   280
C                  AND NONLINEAR VARIABLES                               DER   290
C        W       - SCRATCH ARRAY W FROM THE CALLING SEQUENCE OF SDESOL.  DER   300
C                  THIS CAN BE USED AS NEEDED IN THIS SUBROUTINE.        DER   310
C        KERET   - RETURN INDICATOR                                      DER   320
C                       =0  NORMAL RETURN                                DER   330
C                       =1  ERROR RETURN                                 DER   340
C                                                                        DER   350
C                                                                        DER   360
C-----------------------------------------------------------------------DER   370
```

```
C       DIMENSION Y(7,1), YL(1), W(1)
        DO 100 I=1,NY                                                   DER  380
        W(2*N+I) = AMAX1(ABS(Y(1,I)),1.)                                DER  390
  100   Y(3,I) = 0.                                                     DER  400
C                                                                       DER  410
        HINV = 16.**20                                                  DER  420
        KERET = 0                                                       DER  430
        EPS2 = NY/1.E5                                                  DER  440
        EPS = SQRT(EPS2)                                                DER  450
C
C       DO 140 IT=1,10                                                  DER  470
C                                                                       DER  480
        DO 110 I=1,NY                                                   DER  490
  110   Y(2,I) = Y(3,I)/HINV                                            DER  500
C                                                                       DER  510
        CALL DIFFUN (Y,YL,T,HINV, W,BIGH2,BIGH3,BIGH4,BIGH5,BIGK,BIGF,  DER  520
     1  IBP,ITYPE,JA,JB,NAME,NELCON,R,Z,YIT)                            DER  530
        CALL JACMAT (Y,YL,T,HINV,-1.,NY,NY,EPS,W,W(N+1),W(2*N+1),BIGF2,
     1  BIGH3,BIGH4,BIGH5,BIGK,IBP,ITYPE,JA,JB,NAME,NELCON,R,Z)
        NEWPW = 1
C
        DO 120 I=1,NY                                                   DER  560
  120   W(I) = W(I)*HINV                                                DER  570
C                                                                       DER  580
        CALL NUITSL (W(3*N+1),W,W(N+1),NY,NY,EPS,W(2*N+1),NEWPW,KRET,   DER  590
     1  BIGH3,ITYPE,JA,JB,NAME,NELCON)                                  DER  600
        IF (KRET.NE.0) GO TO 170
        ER = 0.
C                                                                       DER  620
        DO 130 I=1,NY                                                   DER  630
        Y(3,I) = Y(3,I)-W(N+I)                                          DER  640
        W(2*N+I) =AMAX1(ABS(Y(3,I)),1.)                                 DER  650
  130   ER = ER+(W(N+I)/AMAX1(ABS(Y(3,I)),1.))**2                       DER  660
C
        IF (ER.LT.EPS2) GO TO  50                                       DER  670
  140   CONTINUE                                                        DER  680
        GO TO 170                                                       DER  690
C                                                                       DER  700
C                                                                       DER  720
  150   DO 160 I=1,NY                                                   DER  710
  160   Y(2,I) = Y(3,I)                                                 DER  730
C                                                                       DER  740
        RETURN                                                          DER  750
  170   KERET = 1                                                       DER  760
        RETURN                                                          DER  770
        END                                                             DER  780
                                                                        DER  790
```

LIST OF REFERENCES

1. Apostolakis, G. E., "Analytical Estimate of the Error in Conventional Point-Kinetic Reactivity Due to Spatial Effects," Nucl. Sci. Engr., 53, p. 141-152, 1974.

2. Yasinsky, J. B., "On the Use of Point Kinetics for the Analysis of Rod Ejection Accidents," Nucl. Sci. Engr., 39, p. 241-256, 1970.

3. Jackson, J. F. and Kastenburg, W. S., "Space-time Dynamics Studies in Large LMFBR's with Feedback," Nucl. Sci. Engr., 42, p. 278-294, 1970.

4. Nguyen, D. H. and D. Salinas, "Finite Element Solution of Space-Time Nonlinear Reactor Dynamics," Nucl. Sci. Engr., 60, p. 120-130, 1976.

5. Hanford Engineering Development Laboratory Report HEDL-TME 92-128, User's Guide for GAPCON: A Computer Program to Predict Fuel-to-Cladding Heat Transfer Coefficients in Oxide Fuel Pins, by E. R. Horn and F. E. Panisko, 1972.

6. Hanford Engineering Development Laboratory Report HEDL-TME 74-47, Melt III-A Neutronics Thermal-Hydraulic Computer Program for Fast Reactor Safety, v. 1, by A. S. Walter and others, 1974

7. Hanford Engineering Development Laboratory Report HEDL-TME 75-50, An Analysis of the Unprotected Transient Overpower Accident in the FTR, by A. S. Walter and others, 1975.

8. Naval Postgraduate School Report NPS-69Zc-76111, An Optimal Compact Storage Scheme for Nonlinear Reactor Problems by FEM, by D. Salinas, D. H. Nguyen, and R. Franke, 1976.

9. Naval Postgraduate School Report NPS-53Fe-76051, A Program for the Numerical Solution of Large Sparse Systems of Algebraic and Implicitly Defined Stiff Differential Equations, by R. Franke, 1976.

10. Lamarsh, J. R., Introduction to Nuclear Reactor Theory, Addison, Wesley, 1972.

11. Salinas, D., D. H. Nugyen and T. W. Southworth, "Finite Element Solution of a Nonlinear Nuclear Reactor Dynamics Problem," International Conference on Computational Methods in Nonlinear Mechanics, Austin, Texas, p. 541-550, 1974.

12. Semenze, L. A., Lewis, E. E., and Rossow, E. C.,"The Application of the Finite Element Method to the Multigroup Neutron Diffusion Equation," Nucl. Sci. Engr., 47, p. 302-310, 1972.

13. Zienkiewicz, O. C., The Finite Element Method in Engineering Science, McGraw-Hill, 1970.

14. Zlamal, M.,"On the Finite Element Method," Numer. Meth., 12, p. 394-409, 1968.

15. Personal conversation with Dr. G. Cantin of the Naval Postgraduate School, 1976.

16. Cook, R. D., Concepts and Applications of Finite Element Analysis, Wiley, 1974.

17. Zienkiewicz, O. C. and C. J. Parekh, "Transient Field Problems: Two-Dimensional and Three-Dimensional Analysis by Isoparametric Finite Elements," Int. J. for Numer. Meth. in Engr., v. 2, p. 61-71, 1970.

18. Barsoum, R. S., "On the Use of Isoparametric Finite Elements in Linear Fracture Mechanics," Int. J. for Numer. Meth. in Engr., v. 10, no. 1, p. 25-37, 1976.

19. Belle, J., Uranium Dioxide: Properties and Nuclear Applications, Naval Reactors, Div. of Reactor Development, U. S. Atomic Energy Commission, p. 189, 1961.

20. Lew, G. T., A Three Dimensional Solution of the Transient Field Problem Using Isoparametric Finite Elements, Masters Thesis, Naval Postgraduate School, 1972.

INITIAL DISTRIBUTION LIST

		No. Copies
1.	Defense Documentation Center Cameron Station Alexandria, Virginia 22314	2
2.	Library, Code 0142 Naval Postgraduate School Monterey, California 93940	2
3.	Department Chairman, Code 69 Department of Mechanical Engineering Naval Postgraduate School Monterey, California 93940	1
4.	Dr. D. H. Nguyen (thesis advisor) 4625 Larchmont NE Albuquerque, New Mexico 87115	1
5.	Assoc. Professor D. Salinas (thesis advisor) Department of Mechanical Engineering Naval Postgraduate School Monterey, California 93940	1
6.	Assoc. Professor R. Franke (second reader) Department of Mathematics Naval Postgraduate School Monterey, California 93940	1
7.	Professor Gilles Cantin Department of Mechanical Engineering Naval Postgraduate School Monterey, California 93940	1
8.	LT R. E. Kasdorf, USN (student) 129 Redondo Ct. Marina, California 93933	2